

# SIOS Protection Suite for Linux

Version v8.4.1

[Core Messages](#)

[DB2 Kit Messages](#)

[DMMP Kit Messages](#)

[File System Kit Messages](#)

[Gen/App Kit Messages](#)

[IP Kit Messages](#)

[Oracle Listener Kit Messages](#)

[Oracle Kit Messages](#)

[SCSI Kit Messages](#)

[DataKeeper Messages](#)

## Combined Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
000200	ERROR	pam_start() failed	
000201	ERROR	pam_authenticate failed (user %s, retval %d	
000202	ERROR	pam_end() failed?!?!	
000203	ERROR	Did not find expected group 'lkguest'	
000204	ERROR	Did not find expected group 'lkoper'	
000205	ERROR	Did not find expected group 'lkadmin'	
000902	ERROR	Error removing system name from loopback address line in /etc/hosts file. You must do this manually before starting the GUI server.	<p><b>Cause:</b> System name did not get removed from /etc/hosts file.</p> <p><b>Action:</b> Remove system name manually then restart the GUI server, then enter the following: run &lt;action name&gt;</p>
000918	ERROR	LifeKeeper GUI Server error during Startup	<p><b>Cause:</b> The GUI server terminated due to an abnormal condition.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
001052	FATAL	Template resource "%s" on server "%s" does not exist	<p><b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.</p>
001053	ERROR	Cannot access canextend script "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to run pre-extend checks because it was unable to find the script CANEXTEND on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>

Code	Severity	Message	Cause/Action
001054	ERROR	Cannot extend resource "%s" to server "%s"	<b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}.
001055	ERROR	Cannot access extend script "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to extend the resource hierarchy because it was unable to find the script EXTEND on {server}. <b>Action:</b> Check your LifeKeeper configuration.
001057	ERROR	Cannot extend resource "%s" to server "%s"	<b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}.
001059	ERROR	Resource with tag "%s" already exists	<b>Cause:</b> The name provided for a resource is already in use. <b>Action:</b> Either choose a different name for the resource, or use the existing resource.
001060	ERROR	Resource with either matching tag "%s" or id "%s" already exists on server "%s" for App "%s" and Type "%s"	<b>Cause:</b> The name or id provided for a resource is already in use. <b>Action:</b> Either choose a different name or id for the resource or use the existing resource.
001061	ERROR	Error creating resource "%s" on server "%s"	<b>Cause:</b> An unexpected failure occurred while creating a resource. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
001081	WARN	IP address \"%\$ip\" is neither v4 nor v6	<b>Cause:</b> The IP address provided is neither an IPv4 nor an IPv6 address. <b>Action:</b> Please check the name or address provided and try again. If a name was provided, verify that name resolution returns a valid IP address.

Code	Severity	Message	Cause/Action
004024	ERROR		<p><b>Cause:</b> LCD failed to fetch resource information for resource id {id} during resource recovery.</p> <p><b>Action:</b> Verify the input resource id and retry the recovery operation.</p>
004028	ERROR	%s occurred to resource \"%s\"	<p><b>Cause:</b> Local recovery failed for resource {resource}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004055	ERROR	attempt to remote-remove resource \"%s\" that can't be found	<p><b>Cause:</b> Remotely removing a resource from service failed while attempting to find the resource by tag name {tag}.</p> <p><b>Action:</b> Check input tag name and retry the recovery operation.</p>
004056	ERROR	attempt to remote-remove resource \"%s\" that is not a shared resource	<p><b>Cause:</b> Remotely removing a resource from service failed given that the tag name {tag} is not a shared resource.</p> <p><b>Action:</b> Check input tag name and retry the recovery operation.</p>
004060	ERROR	attempt to transfer-restore resource \"%s\" that can't be found	<p><b>Cause:</b> Remote transfer of an in service resource failed given tag name {tag}.</p> <p><b>Action:</b> Check input tag name and retry the recovery operation.</p>
004061	ERROR	attempt to transfer-restore resource \"%s\" that is not a shared resource with machine \"%s\"	<p><b>Cause:</b> LifeKeeper failed to find a shared resource by {tag} name during remote transfer of a resource in service from a remote {machine}.</p> <p><b>Action:</b> Check input tag name and retry the recovery operation.</p>

Code	Severity	Message	Cause/Action
004089	ERROR	ERROR: Parallel recovery initialization failed.\n	<p><b>Cause:</b> Parallel recovery failed to initialize the list of resources in the hierarchy.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004093	ERROR	ERROR: reserve failed. continuing to next resource\n	<p><b>Cause:</b> Parallel recovery failed to reserve a single resource from the collective hierarchy.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004096	ERROR	ERROR: clone %d is hung, attempting to kill it\n	<p><b>Cause:</b> A single sub process of a resource recovery is hung during parallel recovery of a whole resource hierarchy.</p> <p><b>Action:</b> A kill of the hanging sub process will be executed automatically.</p>
004097	ERROR	ERROR: Could not kill clone %d\n	<p><b>Cause:</b> Failed to kill the hung sub process.</p>
004116	ERROR	%s	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed attempting to create the intermediate folder. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the intermediate folder is not created.</p>
004117	ERROR	open(%s	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed while attempting to open a temporary file. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the file is not successfully opened.</p>

Code	Severity	Message	Cause/Action
004118	ERROR	write(%s	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed while attempting to write to a temporary file. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the file writing is failed.</p>
004119	ERROR	fsync(%s	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed while attempting to fsync a temporary file. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the "fsync" is failed.</p>
004120	ERROR	close(%s	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed while attempting to close a temporary file. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the file closing is failed.</p>
004121	ERROR	rename(%s, %s	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed while attempting to rename a temporary file {file} to original file {file}. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the file renaming is failed.</p>
004122	ERROR	open(%s	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed while attempting to open an intermediate directory {directory}. This is a system error."</p> <p><b>Action:</b> Check log for the error information in detail and determine why the directory open is failed.</p>

Code	Severity	Message	Cause/Action
004123	ERROR	fsync(%s	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed while attempting to fsync an intermediate directory {directory}. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the directory "fsync" is failed.</p>
004124	ERROR	close(%s	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed while attempting to close an intermediate directory {directory}. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the directory close is failed.</p>
004125	ERROR	wrote only %d bytes of requested %d\n	<p><b>Cause:</b> Writing an on-disk version of an in-memory data object failed as the final size {size} bytes of written data is less than the requested number {number} of bytes.</p> <p><b>Action:</b> Check log for the related error information in detail and determine why the data writing is failed.</p>
004126	ERROR	open(%s	<p><b>Cause:</b> Attempting to open a data file failed during the reading of an on-disk version of the data object into the buffer. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the file open is failed.</p>
004127	ERROR	open(%s	<p><b>Cause:</b> Attempting to open a temporary data file failed during the reading of an on-disk version of the data object into the buffer. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the file open is failed.</p>

Code	Severity	Message	Cause/Action
004128	ERROR	read(%s	<p><b>Cause:</b> Reading a data file failed during the loading of an on-disk version of the data object into the buffer. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the file reading is failed.</p>
004129	ERROR	read buffer overflow (MAX=%d)\n	<p><b>Cause:</b> The read buffer limit {max} was reached while attempting to read an on-disk version of the data object into the buffer.</p> <p><b>Action:</b> Check the LifeKeeper configuration and restart the LifeKeeper.</p>
004130	ERROR	close(%s	<p><b>Cause:</b> Failed to close a data file during reading an on-disk version of the data object into the buffer. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the file close is failed.</p>
004131	ERROR	rename(%s, %s	<p><b>Cause:</b> Failed to rename a temporary data file during reading an on-disk version of the data object into the buffer. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the file renaming is failed.</p>
004132	ERROR	Can't open %s : %s	<p><b>Cause:</b> Failed to open a directory {directory} with error {error} during reading an on-disk version of the application and resource type information into the buffer. This is a system error.</p> <p><b>Action:</b> Check log for the error information in detail and determine why the open directory is failed.</p>



Code	Severity	Message	Cause/Action
004133	ERROR	path argument may not be NULL	<p><b>Cause:</b> The command "lcdrp" failed during a file copy because the input source path is missing.</p> <p><b>Action:</b> Check the input source path and retry "lcdrp".</p>
004134	ERROR	destination path argument may not be NULL	<p><b>Cause:</b> The "lcdrp" command failed during a file copy because the input destination path is missing.</p> <p><b>Action:</b> Check the input destination path and retry "lcdrp".</p>
004135	ERROR	destination path can't be zero length string	<p><b>Cause:</b> Input destination path was empty during file copy when using "lcdrp".</p> <p><b>Action:</b> Check the input destination path and retry "lcdrp".</p>
004136	ERROR	open(%s	<p><b>Cause:</b> Failed to open source file path during file copy using "lcdrp". This is a system error.</p> <p><b>Action:</b> Check the existence/availability of the input source path and retry "lcdrp". Also check the related log for error information in detail.</p>
004137	ERROR	fstat(%s	<p><b>Cause:</b> Failed to fetch file attributes using "fstat" during file copy by "lcdrp". This is a system error.</p> <p><b>Action:</b> Check the log for error information in detail.</p>
004138	ERROR	file \"%s\" is not an ordinary file (mode=0%o	<p><b>Cause:</b> Detected source file as a none ordinary file during file copy using "lcdrp".</p> <p><b>Action:</b> Check the input source file path and retry "lcdrp".</p>
004152	ERROR	having \"%s\" depend on \"%s\" would produce a loop	<p><b>Cause:</b> Adding the requested dependency would produce a loop of dependent relationship.</p> <p><b>Action:</b> Correct the requested dependency and retry the dependency creation.</p>

Code	Severity	Message	Cause/Action
004164	ERROR	Priority mismatch between resources %s and %s. Dependency creation failed.	<p><b>Cause:</b> The priorities for {resource1} and {resource2} do not match.</p> <p><b>Action:</b> Resource priorities must match. Change one or both priorities to the same value and retry creating the dependency.</p>
004176	ERROR	%s	<p><b>Cause:</b> The command "doabort" failed to create the {directory} for writing the core file. This is a system error.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004190	ERROR	%s: ::receive(%d) did not receive message within %d seconds on incoming_mailbox %s	<p><b>Cause:</b> In function {function}, attempting to receive message within timeout {timeout} seconds failed with incoming mailbox {mailbox}.</p> <p><b>Action:</b> Check the status of the connections inside the cluster and retry the process.</p>
004205	ERROR	destination system \"%s\" is unknown	<p><b>Cause:</b> Sending message failed due to an unknown destination system name {system}.</p> <p><b>Action:</b> Check the configuration and status of the system and check the logs for related errors. Retry the same process after the system is full initialized.</p>
004206	ERROR	destination mailbox \"%s\" at system \"%s\" is unknown	<p><b>Cause:</b> Sending message failed due to an unknown mailbox {mailbox} on destination system name {system}. This error may be caused by sending a message before the LCD is fully initialized.</p> <p><b>Action:</b> Check the configuration and status of the system and check the logs for related errors. Retry the same process after the system is full initialized.</p>

Code	Severity	Message	Cause/Action
004208	ERROR	destination system \"%s\" is alive but the mailbox process is not listening.	<p><b>Cause:</b> Sending message failed. The network connection to destination system {system} is alive but the contact to the destination mailbox is lost.</p> <p><b>Action:</b> Check the configuration and status of the system and check the logs for related errors. Retry the same process after the system is full initialized.</p>
004209	ERROR	destination system \"%s\" is dead.	<p><b>Cause:</b> Sending message failed due to losing connection with the destination system {system}.</p> <p><b>Action:</b> Check the configuration and status of the system and check the logs for related errors. Retry the same process after the system is full initialized.</p>
004211	ERROR	can't send to destination \"%s\" error=%d	<p><b>Cause:</b> Sending message to destination system {system} failed due to internal error {error}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004217	ERROR	destination system \"%s\" is out of service.	<p><b>Cause:</b> Sending message failed due to losing connection with the destination system {system}.</p> <p><b>Action:</b> Check the configuration and status of the system and check the logs for related errors. Retry the same process after the system is full initialized.</p>
004221	ERROR	destination system \"%s\" went out of service.	<p><b>Cause:</b> Sending message failed due to losing connection with the destination system {system}.</p> <p><b>Action:</b> Check the configuration and status of the system and check the logs for related errors. Retry the same process after the system is full initialized.</p>

Code	Severity	Message	Cause/Action
004228	ERROR	Can't get host name from getaddrinfo(	<p><b>Cause:</b> Creating network object failed due to a failure when getting host name using "getaddrinfo()".</p> <p><b>Action:</b> Check the configuration and status of the system. Do the same process again.</p>
004234	ERROR	IP address pair %s already in use	<p><b>Cause:</b> Creating network object failed due to the IP address pair {pair} is already used for a TCP communication path.</p> <p><b>Action:</b> Check the input IP address pair and do the network creation again.</p>
004258	WARN	Communication to %s by %s FAILED	<p><b>Cause:</b> Communication to system {system} by communication path {path} failed.</p> <p><b>Action:</b> Check system configuration and network connection.</p>
004261	WARN	COMMUNICATIONS failover from system \"%s\" will be started.	<p><b>Cause:</b> A failover from system {system} will be started due to all the communications path are down.</p> <p><b>Action:</b> Check system configuration and network connection status. Confirm the system status when failover is done.</p>
004292	ERROR	resource \"%s\" %s	<p><b>Cause:</b> A resource could not be brought in service because its current state is unknown.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004293	ERROR	resource \"%s\" %s	<p><b>Cause:</b> A resource could not be brought into service because its current state disallows it.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
004294	ERROR	resource \"%s\" requires a license (for Kit %s/%s) but none is installed	<p><b>Cause:</b> The resource's related recovery kit requires a license.</p> <p><b>Action:</b> Install a license for the recovery kit on the server where the resource was to be brought into service.</p>
004297	ERROR	secondary remote resource \"%s\" on machine \"%s\" is already in-service, so resource \"%s\" on machine \"%s\" can't be brought in-service.	<p><b>Cause:</b> A resource {resource} could not be brought into service on machine {machine} because its secondary remote resource {resource} is already in service on machine {machine}.</p> <p><b>Action:</b> Manually change the remote resource out of service and do in service on local resource again.</p>
004300	ERROR	restore of resource \"%s\" has failed	<p><b>Cause:</b> A resource could not be brought into service.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004311	ERROR	can't perform \"remove\" action on resources in state \"%s\"	<p><b>Cause:</b> A resource could not be put out of service due to the current state being {state}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004313	ERROR	remove of resource \"%s\" has failed	<p><b>Cause:</b> A resource {resource} could not be put out of service.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004318	ERROR	%s,priv_globact(%d,%s): script %s FAILED returning %d	<p><b>Cause:</b> A global action script failed with the specified error code.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
004332	ERROR	action \"%s\" has failed on resource \"%s\"	<p><b>Cause:</b> A resource action failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004351	ERROR	a \"%s\" equivalency must have one remote resource	<p><b>Cause:</b> Creating of a {eqvtype} equivalency failed due to the two input tag names exist on the same system.</p> <p><b>Action:</b> Correct the inputs resource tag names and do the same process again.</p>
004376	FATAL	wait period of %u seconds for LCM to become available has been exceeded (lock file \"%s\" not removed	<p><b>Cause:</b> The LCM daemon did not become available within a reasonable time and the LCD cannot operate without the LCM.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004386	ERROR	initlcdMalloc;shmget	<p><b>Cause:</b> A shared memory segment could not be initialized.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Review the product documentation and ensure that the server meets the minimum requirements and that the operating system is configured properly.</p>
004444	WARN	License key (for Kit %s/%s) has EXPIRED	<p><b>Cause:</b> Your license has expired.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
004445	WARN	License key (for Kit %s/%s) will expire at midnight in %ld days	<p><b>Cause:</b> Your license is about to expire.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
004466	ERROR	system \"%s\" not defined on machine \"%s\".	<p><b>Cause:</b> The specified system name is not known.</p> <p><b>Action:</b> Verify the system name, and try the operation again.</p>

Code	Severity	Message	Cause/Action
004467	ERROR	system \"%s\" unknown on machine \"%s\"	<p><b>Cause:</b> The specified system name is not recognized.</p> <p><b>Action:</b> Verify the system name, and try the operation again.</p>
004494	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004495	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004496	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004497	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004498	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
004499	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004500	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004501	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004502	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004503	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004504	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>



Code	Severity	Message	Cause/Action
004505	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004506	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004507	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004508	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004509	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004510	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
004511	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> An action or event script produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004512	ERROR		<p><b>Cause:</b> An error occurred on the remote machine.</p> <p><b>Action:</b> Check the logs on the remote machine for additional details.</p>
004565	ERROR	can't set resource state type to ILLSTATE	<p><b>Cause:</b> An attempt was made to put a resource in an illegal state.</p> <p><b>Action:</b> Do not try to put a resource into an illegal state.</p>
004567	ERROR	resource \"%s\" can't be changed to \"%s\" state because it is a primary resource of a SHARED equivalency to resource \"%s\" on machine \"%s\" which is in state \"%s\"	<p><b>Cause:</b> Change resource {resource} to state {state} failed since its SHARED equivalency primary resource {resource} on machine {machine} is in state {state}.</p> <p><b>Action:</b> Check the input or manually put the primary resource out of service and try the same process again.</p>
004607	ERROR	no resource instance has tag \"%s\"	<p><b>Cause:</b> No resource with the provided tag exists.</p> <p><b>Action:</b> Provide a valid tag, or check the logs for related errors and try to resolve the reported problem.</p>
004608	ERROR	no resource instance has identifier \"%s\"	<p><b>Cause:</b> No resource exists with the provided identifier.</p> <p><b>Action:</b> Provide a valid identifier, or check the logs for related errors and try to resolve the reported problem.</p>
004619	ERROR	resource with tag \"%s\" already exists with identifier \"%s\"	<p><b>Cause:</b> The provided tag name already exists.</p> <p><b>Action:</b> Choose a different tag name.</p>

Code	Severity	Message	Cause/Action
004620	ERROR	resource with identifier \"%s\" already exists with tag \"%s\"	<p><b>Cause:</b> The provided identifier already exists.</p> <p><b>Action:</b> Choose a different identifier to use for this resource.</p>
004643	ERROR	Instance tag name is too long. It must be shorter than %d characters.	<p><b>Cause:</b> Tag name is too long.</p> <p><b>Action:</b> Provide a tag name that is less than 256 characters.</p>
004646	ERROR	Tag name contains illegal characters	<p><b>Cause:</b> Tag name contains an illegal character.</p> <p><b>Action:</b> Specify a tag name that does not include one of these characters: _-./</p>
004691	ERROR	can't set both tag and identifier at same time	<p><b>Cause:</b> Both a tag and an identifier were specified.</p> <p><b>Action:</b> Provide only one of tag or identifier.</p>
004745	ERROR	failed to access lkexterlog path=%s	<p><b>Cause:</b> The utility "lkexterlog" can not be accessed for collecting system information.</p> <p><b>Action:</b> Check the installation of package "steeleye-lk" and make sure the utility "lkexterlog" is accessible.</p>
004746	ERROR	lkexterlog failed runret=%d cmdline=%s	<p><b>Cause:</b> The execution of utility "lkexterlog" failed when collecting system information.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004782	ERROR	Resource \"%s\" was in state \"%s\" before event occurred - recovery will not be attempted	<p><b>Cause:</b> The resource is already in service. Recovery will not be attempted.</p>
004783	ERROR	Resource \"%s\" was already in state \"%s\" before event occurred	<p><b>Cause:</b> A resource was not in an appropriate state to allow recovery.</p> <p><b>Action:</b> Put the resource in the ISP state if recovery is still needed.</p>

Code	Severity	Message	Cause/Action
004786	ERROR	%s on failing resource \"%s\"	<p><b>Cause:</b> An error occurred why attempting to recover a resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004788	EMERG	failed to remove resource '%s'. SYSTEM HALTED.	<p><b>Cause:</b> A error occur that prevented a resource from being taken out of service during a recovery. The system has been restarted to ensure the resource is not active on two systems.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004793	ERROR	lcsendremote transfer resource \"%s\" to \"%s\" on machine \"%s\" failed (rt=%d	<p><b>Cause:</b> A failure occurred while transferring a resource and its dependencies to another system.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Check the log on the other system for related errors.</p>
004797	ERROR	Restore of SHARED resource \"%s\" has failed	<p><b>Cause:</b> There was an error while restoring a resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
004806	ERROR	Restore in parallel of resource \"%s\" has failed; will re-try serially	<p><b>Cause:</b> Parallel recovery failed. Check the logs for related errors and try to resolve the reported problem.</p> <p><b>Action:</b> No action is required. The system will continue to recover serially. If the recovery fails, check for error messages related to the resources which failed to recover to find out what further actions to take.</p>

Code	Severity	Message	Cause/Action
004819	ERROR	read_temporal_recovery_log(): failed to fopen file: %s. fopen() %s.	<p><b>Cause:</b> The opening of the temporal recovery log file {file} in preparation for loading into it into memory failed with the error {error}.</p> <p><b>Action:</b> Check system log files and correct any reported errors before retrying the operation.</p>
004820	ERROR	read_temporal_recovery_log(): failed to malloc initial buf for temporal_recovery_stamp.	<p><b>Cause:</b> Loading the temporal recovery log information into memory failed when attempting to acquire memory to store the log information.</p> <p><b>Action:</b> Check system log files and correct any reported errors before retrying the operation.</p>
004821	ERROR	read_temporal_recovery_log(): failed to reallocate buffer for temporal_recovery_stamp.	<p><b>Cause:</b> Loading the temporal recovery log information into memory failed when attempting to increase the amount of memory required to store the log information.</p> <p><b>Action:</b> Check system log files and correct any reported errors before retrying the operation.</p>
004822	ERROR	write_temporal_recovery_log(): failed to open file: %s.	<p><b>Cause:</b> The update of the temporal recovery log file was terminated when the open of the temporary file {temporary name} failed.</p> <p><b>Action:</b> Check system log files and correct any reported errors before retrying the operation.</p>
004823	ERROR	rename(%s, %s) failed.	<p><b>Cause:</b> The update of the temporal recovery log file was terminated when the rename of the temporary file {temporary name} to the real log file {real name} failed.</p> <p><b>Action:</b> Check system log files and correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
004829	FATAL	err=%s line=%d Semid=%d numops=%zd perror=%s	<p><b>Cause:</b> The modification of semaphore ID {semaphore} failed with error {err} and error message description {perror}.</p> <p><b>Action:</b> Check adjacent log messages for more details. Also, check the system log files and correct any reported errors before retrying the operation.</p>
004860	ERROR	restore ftok failed for resource %s with path %s	<p><b>Cause:</b> The attempt to generate an IPC key for use in semaphore operations for resource {tag} using path {path} failed. This is a system error.</p> <p><b>Action:</b> Check adjacent log messages for more details. Also check system log files and correct any reported errors before retrying the operation.</p>
004861	ERROR	semget failed with error %d	<p><b>Cause:</b> The attempt to retrieve the semaphore identification associated with the instances files has failed. This is a system error.</p> <p><b>Action:</b> Check adjacent log messages for more details. Also check system log files and correct any reported errors before retying the operation.</p>
004862	ERROR	semctl SEMSET failed with error %d	<p><b>Cause:</b> The attempt to create and initialize a semaphore used during the recovery process has failed with the error {error number}. This is a system error.</p> <p><b>Action:</b> Check adjacent log messages for more details. Also, check system log files and correct any reported errors before retying the operation.</p>

Code	Severity	Message	Cause/Action
004863	ERROR	semop failed with error %d	<p><b>Cause:</b> The attempt to set a semaphore used during the recovery process has failed with the error {error number}. This is a system error.</p> <p><b>Action:</b> Check adjacent log messages for more details. Also, check system log files and correct any reported errors before retrying the operation.</p>
004864	ERROR	semctl SEMSET failed with error %d	<p><b>Cause:</b> The attempt to release a semaphore used during the recovery process has failed with the error {error number}. This is a system error.</p> <p><b>Action:</b> Check adjacent log messages for more details. Also, check system log files and correct any reported errors before retrying the operation.</p>
004865	ERROR	restore action failed for resource %s	<p><b>Cause:</b> The attempt to bring resource {tag} In Service has failed.</p> <p><b>Action:</b> Check adjacent log messages for more details. Correct any reported errors and retry the operation.</p>
004872	ERROR	Remote remove of resource \"%s\" on machine \"%s\" failed (rt=%d)	<p><b>Cause:</b> The request to take resource {tag} Out of Service on {server} for transfer to the local system has failed.</p> <p><b>Action:</b> Check adjacent log messages for more details on the local system. Also, check the log messages on {server} for further details on the failure to remove the resource.</p>
004875	ERROR	remote remove of resource \"%s\" on machine \"%s\" failed	<p><b>Cause:</b> The request to take resource {tag} Out of Service on {server} for transfer to the local system has failed.</p> <p><b>Action:</b> Check adjacent log messages for more details on the local system. Also, check the log messages on {server} for further details on the failure to remove the resource.</p>

Code	Severity	Message	Cause/Action
004876	ERROR	remote remove of resource \"%s\" on machine \"%s\" failed	<p><b>Cause:</b> The request to take resource {tag} Out of Service on {server} for transfer to the local system has failed.</p> <p><b>Action:</b> Check adjacent log messages for more details on the local system. Also, check the log messages on {server} for further details on the failure to remove the resource.</p>
005045	ERROR	tli_fdget_i::execute unable to establish a listener port	<p><b>Cause:</b> A network connection could not be properly configured.</p> <p><b>Action:</b> Verify that all network hardware and drivers are properly configured. If this message continues and resources cannot be put into service, contact Support.</p>
005055	ERROR	tli_fdget_o::execute - async connect failure	<p><b>Cause:</b> A network connection could not be properly configured.</p> <p><b>Action:</b> Verify that all network hardware and drivers are properly configured. If this message continues and resources cannot be put into service, contact Support.</p>
005061	ERROR	tli_fdget_o::execute - bind socket	<p><b>Cause:</b> A network connection could not be properly configured.</p> <p><b>Action:</b> Verify that all network hardware and drivers are properly configured. If this message continues and resources cannot be put into service, contact Support.</p>
005145	ERROR	opening the file	<p><b>Cause:</b> A pipe could not be opened or created.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
005225	WARN	so_driver::handle_error: sending/receiving data message erro %d: %s	<p><b>Cause:</b> A message failed to be sent or received.</p> <p><b>Action:</b> Check adjacent log messages for more details. This may be a temporary error, but if this error continues and servers cannot communicate, verify the network configuration on the servers.</p>



Code	Severity	Message	Cause/Action
006012	ERROR	quickCheck script '%s' failed to exit after %u seconds. Forcibly terminated. Please examine the script or adjust the LKCHECKINTERVAL parameter in %s.	<p><b>Cause:</b> A quickCheck script is probably taking too long or hanging.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
006102	ERROR	COMMAND OUTPUT: \$LKROOT/bin/sendevent	<p><b>Cause:</b> This is output from a "sendevent "(event generator) command.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
006103	ERROR	COMMAND OUTPUT: \$LKROOT/bin/sendevent	<p><b>Cause:</b> This is output from a "sendevent" (event generator) command.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
006104	ERROR	COMMAND OUTPUT: \$LKROOT/bin/sendevent	<p><b>Cause:</b> This is output from a "sendevent" (event generator) command.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
007058	ERROR	%s: %s failed on '%s', result:%d, Sense Key = %d.	<p><b>Cause:</b> A SCSI device couldn't be reserved or have its status checked. This may be because the storage is malfunctioning or because the disk has been reserved by another server.</p> <p><b>Action:</b> Check adjacent log messages for more details and verify that resources are being handled properly.</p>
007059	ERROR	%s: %s failed on '%s', result:%d.	<p><b>Cause:</b> A SCSI device couldn't be reserved or have its status checked. This may be because the storage is malfunctioning or because the disk has been reserved by another server.</p> <p><b>Action:</b> Check adjacent log messages for more details and verify that resources are being handled properly.</p>

Code	Severity	Message	Cause/Action
007060	EMERG	%s: failure on device '%s'. SYSTEM HALTED.	<p><b>Cause:</b> A SCSI device couldn't be reserved or have its status checked. This may be because the storage is malfunctioning or because the disk has been reserved by another server. THE SERVER WILL BE REBOOTED/HALTED.</p> <p><b>Action:</b> Verify that the storage is functioning properly and, if so, that resources were handled properly and have been put in service on another server.</p>
007072	ERROR	%s: failed to open SCSI device '%s', initiate recovery. ermo=0x%x, retry count=%d.	<p><b>Cause:</b> The protected SCSI device could not be opened. The device may be failing or may have been removed from the system.</p> <p><b>Action:</b> The system will be halted or a failover to the backup node will be initiated. The default action in this case is a failover, but this can be modified with the SCSIERROR tunable.</p>
007073	ERROR	%s: failed to open SCSI device '%s', RETRY. ermo=%d, retry count=%d.	<p><b>Cause:</b> The protected SCSI device could not be opened. The device may be failing or may have been removed from the system.</p> <p><b>Action:</b> This error is not critical. The operation will be retried in 5 seconds. If the problem persists, the system will perform a halt or resource failover.</p>
007075	ERROR	%s: RESERVATION CONFLICT on SCSI device '%s'. ret=%d, ermo=0x%x, retry count=%d.	<p><b>Cause:</b> A SCSI device couldn't be reserved due to a conflict with another server. This may be because the storage is malfunctioning or because the disk has been reserved by another server.</p> <p><b>Action:</b> Check adjacent log messages for more details and verify that resources are handled properly.</p>

Code	Severity	Message	Cause/Action
007077	ERROR	%s: DEVICE FAILURE on SCSI device '%s', initiate recovery. ret=%d, errno=0x%x, retry count=%d.	<p><b>Cause:</b> A SCSI device couldn't be reserved or have its status checked. This may be because the storage is malfunctioning or because the disk has been reserved by another server.</p> <p><b>Action:</b> Check adjacent log messages for more details and verify that resources are handled properly.</p>
007078	ERROR	%s: DEVICE FAILURE on SCSI device '%s', RETRY. ret=%d, errno=0x%x, retry count=%d.	<p><b>Cause:</b> A SCSI device couldn't be reserved or have its status checked. This may be because the storage is malfunctioning or because the disk has been reserved by another server.</p> <p><b>Action:</b> Check adjacent log messages for more details and verify that resources are handled properly.</p>
010002	WARN	flag \$flag not present, send message again.	<p><b>Cause:</b> This message indicates an incomplete process that will be retried.</p> <p><b>Action:</b> Check adjacent log messages for repeated errors.</p>
010003	ERROR	COMMAND OUTPUT: \$LKBIN/ins_remove	<p><b>Cause:</b> This message is part of the output from an "ins_remove" command.</p> <p><b>Action:</b> Check adjacent log messages for more details. This may not be a true error.</p>
010004	EMERG	Cannot find the \$LKROOT/config/lkstart-hook file. You must install the LifeKeeper Distribution Enabling package before starting \$PRODUCT.	<p><b>Cause:</b> This error may be caused by installing LifeKeeper directly using the rpms, or perhaps by inadvertently removing an rpm from the system.</p> <p><b>Action:</b> You should reinstall LifeKeeper using the 'setup' script on the installation media.</p>

Code	Severity	Message	Cause/Action
010006	WARN	fig_list -d \$i took more than \$pswait seconds to complete...	<p><b>Cause:</b> A flag list operation on a server took much longer than expected. There may be a problem communicating with the other server.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
010007	ERROR	flag \$flag not present, switchovers may occur.	<p><b>Cause:</b> One of the servers in the cluster could not be told to disallow failover operations from the current server.</p> <p><b>Action:</b> Check adjacent log messages for more details and monitor the cluster for unexpected behavior.</p>
010008	WARN	flag \$flag not present, send message again.	<p><b>Cause:</b> A process is incomplete but will be retried.</p> <p><b>Action:</b> Check adjacent log messages for more details and for repeated warnings/errors.</p>
010023	FATAL	LifeKeeper failed to initialize properly.	<p><b>Cause:</b> There was a fatal error while attempting to start LifeKeeper.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
010025	ERROR	`printf 'Unable to get a unique tag name on server "%s" for template resource "%s" \$MACH \$DISK`	<p><b>Cause:</b> A suitable tag during the create process for a storage resource could not be automatically generated.</p> <p><b>Action:</b> Check adjacent log messages for more details. Retry the operation if there are no other errors.</p>
010034	FATAL	Unable to start lcm.	<p><b>Cause:</b> A core component of the software could not be started.</p> <p><b>Action:</b> Check adjacent log messages for more details and try to resolve the reported problem.</p>
010038	WARN	Waiting for LifeKeeper core components to initialize has exceeded 10 seconds. Continuing anyway, check logs for further details.	<p><b>Cause:</b> Some parts of the software are taking longer than expected to start up.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>

Code	Severity	Message	Cause/Action
010039	WARN	Waiting for LifeKeeper core components to initialize has exceeded 10 seconds. Continuing anyway, check logs for further details.	<p><b>Cause:</b> Some parts of the software are taking longer than expected to start up.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
010046	ERROR	The dependency creation failed on server \$SERVER:" 'cat \$TEMP_FILE'	<p><b>Cause:</b> A dependency relationship could not be created on the given server.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem</p>
010063	ERROR	\$REMSH error	<p><b>Cause:</b> A command to request data to backup from another server failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010085	ERROR	lkswitchback(\$MACH): Automatic switchback of \"\$- loctag\" failed	<p><b>Cause:</b> The resource was not switched back over as expected.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010102	ERROR	admin machine not specified	<p><b>Cause:</b> Invalid parameters were specified for the "getlocks" operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation. If this error happens during normal operation, contact Support.</p>
010107	WARN	Lock for \$m is ignored because system is OOS	<p><b>Cause:</b> A lock was ignored because the system for which the lock was created is not alive.</p> <p><b>Action:</b> Check the logs for related errors. This may be a harmless error.</p>

Code	Severity	Message	Cause/Action
010108	ERROR	lock acquisition timeout	<p><b>Cause:</b> Acquiring a lock tool longer than expected/allowed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010109	ERROR	could not get admin locks." `cat /tmp/ER\$\$`	<p><b>Cause:</b> The software failed to acquire a lock that is required to manage resources.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010112	ERROR	lcdrp failed with error no: \$LCDRPCRES	<p><b>Cause:</b> A file could not be copied to another server.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010116	ERROR	unable to set !lkstop flag	<p><b>Cause:</b> A flag could not be set to indicate that the server is being stopped by user request.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010121	ERROR	Extended logs aborted due to a failure in opening \$destination. (\$syserrmsg	<p><b>Cause:</b> The execution of utility "lkexterlog" failed when opening the extended log file.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010132	ERROR	Unable to retrieve reservation id from "%s". Error: "%s". Attempting to regenerate.	<p><b>Cause:</b> Unable to open the file /opt/LifeKeeper/config/.reservation_id to retrieve the unique id used for SCSI 3 persistent reservations.</p> <p><b>Action:</b> None. An attempt will be made to regenerate the ID and update the file.</p>

Code	Severity	Message	Cause/Action
010133	ERROR	No reservation ID exists in "%s". A new ID must be generated by running "%s/bin/genresid -g" on "%s".	<p><b>Cause:</b> A unique reservation id has not been defined.</p> <p><b>Action:</b> Take all resources out of service on this node and then run "/opt/LifeKeeper/bin/genresid -g" to generate a unique reservation id.</p>
010134	ERROR	LifeKeeper does not appear to be running. Unable to determine the uniqueness of the reservation ID within the cluster.	<p><b>Cause:</b> LifeKeeper was not running when an attempt to check the uniqueness of the reservation id was made.</p> <p><b>Action:</b> Start LifeKeeper and rerun the uniqueness check via "/opt/LifeKeeper/bin/genresid -v".</p>
010135	ERROR	The current reservation ID of "%s" is not unique within the cluster. A new ID must be generated by running "%s/bin/genresid -g" on "%s".	<p><b>Cause:</b> The reservation id defined for the system is not unique within the cluster and cannot be used.</p> <p><b>Action:</b> Take all resources out of service on this node and then run "/opt/LifeKeeper/bin/genresid -g" to generate a unique reservation id.</p>
010136	ERROR	Unable to store reservation id in "%s". Error: "%s"	<p><b>Cause:</b> Unable to open the file /opt/LifeKeeper/config.reservation_id to store the unique id used for SCSI 3 persistent reservations.</p> <p><b>Action:</b> Correct the error listed as the reason the open failed and then take all resources out of service on this node and then run "/opt/LifeKeeper/bin/genresid -g" to generate a new unique reservation id.</p>
010137	ERROR	Failed to generate a reservation ID that is unique within the cluster.	<p><b>Cause:</b> The generated reservation id is already defined on another node in the cluster and must be unique within the cluster.</p> <p><b>Action:</b> Take all resources out of service on this node and then run "/opt/LifeKeeper/bin/genresid -g" to generate a new unique reservation id.</p>

Code	Severity	Message	Cause/Action
010222	ERROR	scsifree(%s): LKSCSI_Release(%s) unsuccessful	<p><b>Cause:</b> A SCSI device that appeared to be reserved was not released as expected.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve any reported problems. This error may be benign if the system is functioning properly.</p>
010231	ERROR	scsiplock(%s): reserve failed.	<p><b>Cause:</b> A reservation on a SCSI device could not be acquired.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010250	ERROR	Failed to exec command '%s'	<p><b>Cause:</b> The "lklogmsg" tool failed to execute a sub-command {command}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve any reported problems. Verify that the sub-command exists and is a valid command or program. If this message happens during normal operation, contact Support.</p>
010402	EMERG	local recovery failure on resource \$opts{'N'}, trigger VMware HA...	<p><b>Cause:</b> When in LifeKeeper Single Server Protection operation, a resource could not be recovered and VMware-HA is about to be triggered to handle the failure (if VMware-HA is enabled).</p> <p><b>Action:</b> No action is required. VMware should handle the failure.</p>
010413	ERROR	COMMAND OUTPUT: cat /tmp/err\$\$	<p><b>Cause:</b> This is the output from an "snmptrap" command that may have failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>



Code	Severity	Message	Cause/Action
010420	EMERG	local recovery failure on resource \$opts{'N'}, trigger reboot...	<p><b>Cause:</b> When in LifeKeeper Single Server Protection operation, a resource could not be recovered and a reboot is about to be triggered to handle the failure.</p> <p><b>Action:</b> No action is required.</p>
010440	ERROR	[\$SUBJECT event] mail returned \$err	<p><b>Cause:</b> This indicates a notification email could not be sent via the "mail" command.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010443	ERROR	COMMAND OUTPUT: cat /tmp/err\$\$	<p><b>Cause:</b> This is the output from a "mail" command that may have failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010445	ERROR	COMMAND OUTPUT: cat /tmp/err\$\$	<p><b>Cause:</b> This is the output from a "mail" command that may have failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010463	ERROR	LifeKeeper: name of machine is not specified, ARGS-S=\$ARGS	<p><b>Cause:</b> Invalid arguments were specified for the "comm_down" event.</p> <p><b>Action:</b> Check your LifeKeeper configuration and retry the operation.</p>
010471	ERROR	COMM_DOWN: Attempt to obtain local comm_down lock flag failed	<p><b>Cause:</b> During the handling of a communication failure with another node, a local lock could not be acquired. This will likely stop a failover from proceeding.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. If failovers are not taking place properly, contact Support.</p>

Code	Severity	Message	Cause/Action
010482	ERROR	LifeKeeper: name of machine is not specified, ARGS-S=\$ARGS	<p><b>Cause:</b> Invalid arguments were specified for the "comm_up" event.</p> <p><b>Action:</b> Check your LifeKeeper configuration and retry the operation.</p>
010484	WARN	flg_list -d \$MACH check timed-out (\$delay seconds).	<p><b>Cause:</b> "flg_list" command reached its timeout value {delay} seconds.</p>
010487	WARN	flg_list -d \$MACH check timed-out, unintended switchovers may occur.	<p><b>Cause:</b> "flg_list" command reached its timeout value.</p> <p><b>Action:</b> Switch back the resource tree if unintended switchover occurs.</p>
010492	WARN	\$m	<p><b>Cause:</b> One of other servers looked dead to this server {server}, but witness servers did not agree.</p> <p><b>Action:</b> Ensure other server is dead and switch over the resource manually.</p>
010494	ERROR	LifeKeeper: COMM_UP to machine \$MACH completed with errors.	<p><b>Cause:</b> An unexpected failure occurred during "COMM_UP" event.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
010503	ERROR	lcrecover hung or returned error, attempting kill of process \$FPID	<p><b>Cause:</b> "lcrecover" took too long or errored out.</p>
010506	ERROR	Intelligent Switchback Check Failed	<p><b>Cause:</b> Failed 5 times to perform "lcrecover."</p> <p><b>Action:</b> Switch over the resource tree manually.</p>
010508	ERROR	[\$SUBJECT] sent to \$LK_NOTIFY_ALIAS	<p><b>Cause:</b> This message is for information only.</p>
010600	ERROR	removing hierarchy remnants	
010627	WARN	Equivalency Trim: does not have a full complement of equivalencies. Hierarchy will be unextended from	

Code	Severity	Message	Cause/Action
010629	WARN	Your hierarchy exists on only one server. Your application has no protection until you extend it to at least one other server.	
010712	ERROR	Unextend hierarchy failed	<p><b>Cause:</b> A resource hierarchy failed to be unextended from a server.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
010746	ERROR	\$ERRMSG Target machine \"\$TARGET_MACH\" does not have an active LifeKeeper communication path to machine \"\$aMach\" in the hierarchy. >&2	<p><b>Cause:</b> A hierarchy cannot be unextended because the target server does not have adequate communication with the other servers in the cluster.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Ensure that all servers have communication paths to each other.</p>
011000	ERROR	appremote: unknown command type %d('%c')\n	<p><b>Cause:</b> Internal error.</p> <p><b>Action:</b> Try restarting the product.</p>
011001	ERROR	depremote: unknown command type %d('%c')\n	<p><b>Cause:</b> Internal error.</p> <p><b>Action:</b> Try restarting the product.</p>
011002	ERROR	eqvremote: unknown command type %d('%c')\n	<p><b>Cause:</b> Internal error.</p> <p><b>Action:</b> Try restarting the product.</p>
011003	ERROR	flgremote: unknown command type %d('%c')\n	<p><b>Cause:</b> Internal error.</p> <p><b>Action:</b> Try restarting the product.</p>
011004	WARN	Illegal creation of resource	<p><b>Cause:</b> This will not occur under normal circumstances.</p>
011011	FATAL	%s	<p><b>Cause:</b> LifeKeeper could not get IPC key.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>

Code	Severity	Message	Cause/Action
011012	FATAL	semget(%s,%c	<p><b>Cause:</b> LifeKeeper could not get semaphore set id.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
011013	FATAL	shmget(%s,%c	<p><b>Cause:</b> System could not allocate a shared memory segment.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
011014	FATAL	prefix_lkroot("out"	<p><b>Cause:</b> A system error has occurred while accessing /opt/LifeKeeper/out.</p> <p><b>Action:</b> Determine why /opt/LifeKeeper/out is not accessible.</p>
011015	ERROR	DEMO_UPGRADE_MSG	<p><b>Cause:</b> You are running a demo license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011016	ERROR	lic_single_node_msg	<p><b>Cause:</b> You have a license for LifeKeeper Single Server Protection but you do not have LifeKeeper Single Server Protection installed.</p> <p><b>Action:</b> Either install LifeKeeper Single Server Protection or obtain a license that matches the product you are running.</p>
011017	ERROR	lic_init_fail_msg, "flex_init failed"	<p><b>Cause:</b> License manager initialization failed.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
011018	ERROR	lic_init_fail_msg, lc_errstring(lm_job	<p><b>Cause:</b> License manager initialization failed.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
011019	EMERG	lic_init_fail_msg, "flex_init failed"	<p><b>Cause:</b> License manager initialization failed.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>

Code	Severity	Message	Cause/Action
011020	EMERG	lic_init_fail_msg, lc_errstring(lm_job	<b>Cause:</b> License manager initialization failed. <b>Action:</b> Check adjacent log messages for more details.
011021	EMERG	lic_error_msg, lc_errstring(lm_job	<b>Cause:</b> There is a problem with your license. <b>Action:</b> Contact Support to obtain a new license.
011022	EMERG	lic_error_msg, lc_errstring(lm_job	<b>Cause:</b> There is a problem with your license. <b>Action:</b> Contact Support to obtain a new license.
011023	EMERG	lic_no_rest_suite, ""	<b>Cause:</b> There is a problem with your license. <b>Action:</b> Contact Support to obtain a new license.
011024	EMERG	lic_error_msg, lc_errstring(lm_job	<b>Cause:</b> There is a problem with your license. <b>Action:</b> Contact Support to obtain a new license.
011025	EMERG	lic_no_license, ""	<b>Cause:</b> LifeKeeper could not find valid license keys. <b>Action:</b> Ensure license keys are valid for the server and retry the operation.
011026	EMERG	lic_error_msg, lc_errstring(lm_job	<b>Cause:</b> There is an unknown problem with your license. <b>Action:</b> Contact Support to obtain a new license.
011027	EMERG	lic_no_license, ""	<b>Cause:</b> There is a problem with your license. <b>Action:</b> Contact Support to obtain a new license.
011028	ERROR	lang_error_msg	<b>Cause:</b> There is a problem with your license. <b>Action:</b> Contact Support to obtain a new license.

Code	Severity	Message	Cause/Action
011029	FATAL	can't set reply system	<p><b>Cause:</b> A message failed to be sent.</p> <p><b>Action:</b> Check adjacent log messages for more details. This may be a temporary error.</p>
011030	FATAL	can't set reply mailbox	<p><b>Cause:</b> A message failed to be sent.</p> <p><b>Action:</b> Check adjacent log messages for more details. This may be a temporary error.</p>
011031	ERROR	Failure reading output of '%s' on behalf of %s	<p><b>Cause:</b> A system error has occurred while accessing temporary file /tmp/OUT.{pid}.</p> <p><b>Action:</b> Determine why /tmp/OUT.{pid} is not accessible.</p>
011032	ERROR	Failure reading output of '%s'	<p><b>Cause:</b> A system error has occurred while accessing temporary file /tmp/ERR.{pid}.</p> <p><b>Action:</b> Determine why /tmp/ERR.{pid} is not accessible.</p>
011033	ERROR	event \"%s,%s\" already posted for resource with id \"%s\"	<p><b>Cause:</b> This message is for information only.</p>
011034	ERROR	no resource has id of \"%s\"	<p><b>Cause:</b> LifeKeeper could not find the {id} resource.</p> <p><b>Action:</b> Verify the parameters and retry the "sendevent" operation.</p>
011044	ERROR	flagcleanup:fopen(%s	<p><b>Cause:</b> A system error has occurred while reading /opt/LifeKeeper/config/flg.</p> <p><b>Action:</b> Determine why /opt/LifeKeeper/config/flg is not readable.</p>

Code	Severity	Message	Cause/Action
011045	ERROR	flagcleanup:fopen(%s	<p><b>Cause:</b> A system error has occurred while writing /opt/LifeKeeper/config/flg.</p> <p><b>Action:</b> Determine why /opt/LifeKeeper/config/flg is not writable.</p>
011046	ERROR	flagcleanup:fputs(%s	<p><b>Cause:</b> A system error has occurred while writing /opt/LifeKeeper/config/flg.</p> <p><b>Action:</b> Determine why /opt/LifeKeeper/config/flg is not writable.</p>
011047	ERROR	flagcleanup:rename(%s,%s	<p><b>Cause:</b> A system error has occurred while renaming /opt/LifeKeeper/config/.flg to /opt/LifeKeeper/config/flg.</p> <p><b>Action:</b> Determine why /opt/LifeKeeper/config/flg was not able to be renamed.</p>
011048	ERROR	flagcleanup:chmod(%s	<p><b>Cause:</b> A system error has occurred while changing permissions in /opt/LifeKeeper/config/flg.</p> <p><b>Action:</b> Determine why LifeKeeper could not change permissions in /opt/LifeKeeper/config/flg.</p>
011049	ERROR	License check failed with error code %d	<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011051	ERROR	lcdinit: clearing Disk Reserve file failed	<p><b>Cause:</b> A system error has occurred while writing /opt/LifeKeeper/subsys/scsi/resources/disk/disk.reserve.</p> <p><b>Action:</b> Determine why /opt/LifeKeeper/subsys/scsi/resources/disk/disk.reserve is not writable.</p>

Code	Severity	Message	Cause/Action
011052	FATAL	malloc() failed	<p><b>Cause:</b> The system could not allocate memory for LifeKeeper.</p> <p><b>Action:</b> Increase the process limit for the data segment.</p>
011053	FATAL	lcm_is_unavail	<p><b>Cause:</b> A system error has occurred while writing /tmp/LK_IS_UNAVAIL.</p> <p><b>Action:</b> Determine why /tmp/LK_IS_UNAVAIL is not writable.</p>
011054	FATAL	lk_is_unavail	<p><b>Cause:</b> A system error has occurred while writing /opt/LifeKeeper/config/LK_IS_ON.</p> <p><b>Action:</b> Determine why /opt/LifeKeeper/config/LK_IS_ON is not writable.</p>
011055	FATAL	usr_alarm_config_LK_IS_ON	<p><b>Cause:</b> A system error has occurred while writing /tmp/LCM_IS_UNAVAI.</p> <p><b>Action:</b> Determine why /tmp/LCM_IS_UNAVAI is not writable.</p>
011056	ERROR	License check failed with error code %d	<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011057	ERROR	lcdremote: unknown command type %d('%c')\n	<p><b>Cause:</b> A message failed to be received.</p> <p><b>Action:</b> Check adjacent log messages for more details. This may be a temporary error, but if this error continues and servers cannot communicate, verify the network configuration on the servers.</p>



Code	Severity	Message	Cause/Action
011059	FATAL	Could not write to: %s	<p><b>Cause:</b> A system error has occurred while accessing /opt/LifeKeeper/config/LK_START_TIME.</p> <p><b>Action:</b> Determine why /opt/LifeKeeper/config/LK_START_TIME is not accessible.</p>
011060	FATAL	received NULL message	<p><b>Cause:</b> A message failed to be received.</p> <p><b>Action:</b> Check adjacent log messages for more details. This may be a temporary error, but if this error continues and servers cannot communicate, verify the network configuration on the servers.</p>
011061	ERROR	unknown data type %d('%c') on machine \"%s\"\\n	<p><b>Cause:</b> A message failed to be received.</p> <p><b>Action:</b> Check adjacent log messages for more details. This may be a temporary error, but if this error continues and servers cannot communicate, verify the network configuration on the servers.</p>
011062	WARN	LifeKeeper shutdown in progress. Unable to perform fail-over recovery processing for %s\\n	<p><b>Cause:</b> LifeKeeper was unable to fail over the given resource during shutdown.</p> <p><b>Action:</b> Switch over the resource tree to other server manually.</p>
011063	WARN	LifeKeeper resource initialization in progress. Unable to perform failover recovery processing for %s\\n	<p><b>Cause:</b> LifeKeeper was unable to fail over the given resource during start up.</p> <p><b>Action:</b> Switch over the resource tree manually after LifeKeeper starts up.</p>
011068	ERROR	ERROR on command %s	<p><b>Cause:</b> An error occurred while running the "rlslocks" command.</p> <p><b>Action:</b> Check adjacent messages for more details.</p>

Code	Severity	Message	Cause/Action
011070	ERROR	ERROR on command %s	<p><b>Cause:</b> An error occurred while running the "getlocks" command.</p> <p><b>Action:</b> Check adjacent log messages for more details.</p>
011081	FATAL	Failed to ask ksh to run: %s	<p><b>Cause:</b> A system error has occurred while invoking ksh.</p> <p><b>Action:</b> Make sure the pdksh (v8.0 and earlier) or the steeleye-pdksh (v81 and later) package is installed.</p>
011082	ERROR	Failed to remove: %s	<p><b>Cause:</b> A system error has occurred while removing /tmp/LCM_IS_UNAVAIL.</p> <p><b>Action:</b> Determine why /tmp/LCM_IS_UNAVAIL is not removable.</p>
011083	ERROR	Failed to remove: %s	<p><b>Cause:</b> A system error has occurred while trying to unlink /tmp/LK_IS_UNAVAIL.</p> <p><b>Action:</b> Determine why /tmp/LK_IS_UNAVAIL is not removable.</p>
011084	FATAL	Failed to generate an IPC key based on: %s	<p><b>Cause:</b> A system error has occurred while accessing /opt/LifeKeeper.</p> <p><b>Action:</b> Determine why /opt/LifeKeeper is not accessible.</p>
011085	ERROR	semget(%s,%c) failed	<p><b>Cause:</b> A system error has occurred while removing a semaphore.</p> <p><b>Action:</b> Try to remove the semaphore manually.</p>
011086	ERROR	shmget(%s,%c) failed	<p><b>Cause:</b> A system error has occurred while removing a shared memory segment.</p> <p><b>Action:</b> Try to remove the shared memory segment manually.</p>

Code	Severity	Message	Cause/Action
011087	ERROR	semctl(IPC_RMID) failed	<p><b>Cause:</b> A system error has occurred while removing a semaphore.</p> <p><b>Action:</b> Try to remove the semaphore manually.</p>
011088	ERROR	shmctl(IPC_RMID) failed	<p><b>Cause:</b> A system error has occurred while removing a shared memory segment.</p> <p><b>Action:</b> Try to remove the shared memory segment manually.</p>
011089	FATAL	Execution of lcdstatus on remote system <%s> failed\n	<p><b>Cause:</b> The remote {node} is down, inaccessible via the network or some other system problem occurred on the remote node.</p> <p><b>Action:</b> Bring the remote node back online, or check adjacent messages for additional information, or check the logs on the remote node for additional information.</p>
011091	WARN		<p><b>Cause:</b> This will not occur under normal circumstances.</p>
011092	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
011093	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
011094	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
011095	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>

Code	Severity	Message	Cause/Action
011096	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
011097	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011098	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011099	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011100	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011101	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011102	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011103	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011104	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011105	FATAL		<p><b>Cause:</b> There is a problem with your license.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>

Code	Severity	Message	Cause/Action
011111	ERROR	action \"%s\" on resource with tag \"%s\" has failed	<b>Cause:</b> The {action} for resource {tag} has failed. <b>Action:</b> See adjacent error messages for further details.
011112	ERROR		<b>Cause:</b> LifeKeeper could not find the network device. <b>Action:</b> Check your LifeKeeper configuration.
011117	ERROR	sysremote: system \"%s\" not found on \"%s\"	<b>Cause:</b> An invalid system name was provided. <b>Action:</b> Recheck the system name and rerun the command.
011129	ERROR	Failure during run of '%s' on behalf of %s	<b>Cause:</b> Command execution failed. <b>Action:</b> See message details to determine the problem.
011130	ERROR	%s	<b>Cause:</b> The command {command} produced unexpected output. <b>Action:</b> Action should be determined by the content of adjacent error messages.
011131	EMERG	demo_update_msg	<b>Cause:</b> There is a problem with your demo license. <b>Action:</b> Contact Support to obtain a new license.
011132	EMERG	demo_tamper_msg	<b>Cause:</b> You have a demo license and clock tampering has been detected. <b>Action:</b> Contact Support to obtain a new license.
011133	EMERG	demo_tamper_msg	<b>Cause:</b> You have a demo license and clock tampering has been detected. <b>Action:</b> Contact Support to obtain a new license.
011134	EMERG	demo_expire_msg	<b>Cause:</b> The demo license for this product has expired. <b>Action:</b> Contact Support to obtain a new license.

Code	Severity	Message	Cause/Action
011135	EMERG	demo_tamper_msg	<p><b>Cause:</b> You have a demo license and clock tampering has been detected.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011136	EMERG	buf	<p><b>Cause:</b> You are running a demo license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011138	EMERG	buf	<p><b>Cause:</b> You are running a demo license.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011142	WARN	LifeKeeper Recovery Kit %s license key NOT FOUND	<p><b>Cause:</b> An Application Recovery Kit license for {kit} was not found.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011150	ERROR	COMMAND OUTPUT: %s	<p><b>Cause:</b> The command "eventslcm" produced unexpected output.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
011151	EMERG	&localebuf[3]	<p><b>Cause:</b> This version of the LifeKeeper core package is restricted to being used within the territories of the People's Republic of China or Japan.</p>
011152	EMERG	Localized license failure	<p><b>Cause:</b> There was a mis-match between your locale and the locale for which the product license was created.</p> <p><b>Action:</b> Contact Support to obtain a new license which matches your locale.</p>

Code	Severity	Message	Cause/Action
011154	EMERG	Single Node flag check failed.	<p><b>Cause:</b> You have a license for LifeKeeper Single Server Protection but you do not have LifeKeeper Single Server Protection installed.</p> <p><b>Action:</b> Either install LifeKeeper Single Server Protection or obtain a license that matches the product you are running.</p>
011155	EMERG	lic_master_exp_msg, ""	<p><b>Cause:</b> Your license key for this product has expired.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011162	EMERG	lic_restricted_exp_msg, ""	<p><b>Cause:</b> Your license key for this product has expired.</p> <p><b>Action:</b> Contact Support to obtain a new license.</p>
011163	EMERG	Single Node license check failed	<p><b>Cause:</b> You have a license for LifeKeeper Single Server Protection but you do not have LifeKeeper Single Server Protection installed.</p> <p><b>Action:</b> Either install LifeKeeper Single Server Protection or obtain a license that matches the product you are running.</p>
011164	EMERG	demo_expire_msg, DEMO_UPGRADE_MSG	<p><b>Cause:</b> Your license key for this product has expired.</p> <p><b>Action:</b> Please contact Support to obtain a permanent license key for your product.</p>
015000	ERROR	COMMAND OUTPUT: /opt/LifeKeeper/sbin/steeleye-lighttpd	<p><b>Cause:</b> An error has occurred with the "steeleye-lighttpd" process. Specific details of the error are included in the actual log message.</p> <p><b>Action:</b> Correct the configuration and "steeleye-lighttpd" will automatically be restarted.</p>
103001	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The db2nodes.cfg does not contain any server names.</p> <p><b>Action:</b> Ensure the db2nodes.cfg is valid.</p>

Code	Severity	Message	Cause/Action
103002	ERROR	LifeKeeper was unable to get the version for the requested instance "%s"	<b>Cause:</b> "db2level" command did not return DB2 version. <b>Action:</b> Check your DB2 configuration.
103003	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<b>Cause:</b> The DB2 Application Recovery Kit was unable to find any nodes for the DB2 instance. <b>Action:</b> Check your DB2 configuration.
103004	ERROR	Unable to get the information for resource "%s"	<b>Cause:</b> Failed to get resource information. <b>Action:</b> Check your LifeKeeper configuration.
103005	ERROR	Unable to get the information for resource "%s"	<b>Cause:</b> Failed to get resource information. <b>Action:</b> Check your LifeKeeper configuration.
103006	ERROR	Unable to get the instance information for resource "%s"	<b>Cause:</b> Failed to get the instance information. <b>Action:</b> Check your LifeKeeper configuration.
103007	ERROR	Unable to get the instance home directory information for resource "%s"	<b>Cause:</b> Failed to get the instance home directory path. <b>Action:</b> Check your LifeKeeper configuration.
103008	ERROR	Unable to get the instance type information for resource "%s"	<b>Cause:</b> The DB2 Application Recovery Kit found invalid instance type. <b>Action:</b> Check your LifeKeeper configuration.
103009	ERROR	LifeKeeper has encountered an error while trying to get the database configuration parameters for database \"\$DB\"	<b>Cause:</b> There was an unexpected error running "db2 get db cfg for \$DB" command. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.



Code	Severity	Message	Cause/Action
103012	ERROR	LifeKeeper was unable to start the database server for instance "%s"	<p><b>Cause:</b> The requested startup of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "restore" operation.</p>
103013	ERROR	LifeKeeper was unable to start the database server for instance "%s"	<p><b>Cause:</b> The requested startup of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "restore" operation.</p>
103015	ERROR	An entry for the home directory "%s" of instance "%s" does not exist in "/etc/fstab"	<p><b>Cause:</b> The home directory of instance of Multiple Partition database should exist in "/etc/fstab".</p> <p><b>Action:</b> Ensure the home directory exists in "/etc/fstab".</p>
103016	ERROR	LifeKeeper was unable to mount the home directory for the DB2 instance "%s"	<p><b>Cause:</b> Failed to mount the home directory of instance of Multiple Partition database.</p> <p><b>Action:</b> Ensure the home directory is mounted and retry the operation.</p>
103017	ERROR	Unable to get the instance nodes information for resource "%s"	<p><b>Cause:</b> Failed to get the instance nodes.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
103018	ERROR	LifeKeeper was unable to start database partition server "%s" for instance "%s"	<p><b>Cause:</b> The requested startup of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "restore" operation.</p>
103020	ERROR	LifeKeeper was unable to stop the database server for instance "%s"	<p><b>Cause:</b> The requested shutdown of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "remove" operation.</p>

Code	Severity	Message	Cause/Action
103021	ERROR	LifeKeeper was unable to stop the database server for instance "%s"	<p><b>Cause:</b> The requested shutdown of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "remove" operation.</p>
103023	ERROR	Unable to get the instance nodes information for resource "%s"	<p><b>Cause:</b> Failed to get the instance nodes.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
103024	ERROR	LifeKeeper was unable to stop database partition server "%s" for instance "%s"	<p><b>Cause:</b> The requested shutdown of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "remove" operation.</p>
103026	ERROR	Unable to get the instance nodes information for resource "%s"	<p><b>Cause:</b> Failed to get the instance nodes.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
103027	FATAL	The argument for the DB2 instance is empty	<p><b>Cause:</b> Invalid parameters were specified for the create operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
103028	FATAL	Unable to determine the DB2 instance home directory	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance home directory.</p> <p><b>Action:</b> Ensure the instance owner name is same as the instance name and retry the operation.</p>
103029	FATAL	Unable to determine the DB2 instance type	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance type.</p> <p><b>Action:</b> Check your DB2 configuration.</p>

Code	Severity	Message	Cause/Action
103030	FATAL	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find any nodes for the DB2 instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103031	ERROR	The path "%s" is not on a shared filesystem	<p><b>Cause:</b> The instance home directory should be on a shared filesystem.</p> <p><b>Action:</b> Ensure the path is on shared filesystem and retry the create operation.</p>
103032	ERROR	LifeKeeper was unable to get the DB tablespace containers for instance "%s" or the log path for one of its databases	<p><b>Cause:</b> LifeKeeper could not determine the location of the database table space containers or verify that they are located in a path which is on a mounted filesystem.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "create" operation.</p>
103033	ERROR	The path "%s" is not on a shared filesystem	<p><b>Cause:</b> The path of database table space container should be on a shared filesystem.</p> <p><b>Action:</b> Ensure database table space container is on a shared filesystem and retry the operation.</p>
103034	ERROR	A DB2 Hierarchy already exists for instance "%s"	<p><b>Cause:</b> An attempt was made to protect the DB2 instance that is already under LifeKeeper protection.</p> <p><b>Action:</b> You must select a different DB2 instance for LifeKeeper protection.</p>
103035	ERROR	The file system resource "%s" is not in-service	<p><b>Cause:</b> The file system which the DB2 resource depends on should be in service.</p> <p><b>Action:</b> Ensure the file system resource is in service and retry the "create" operation.</p>

Code	Severity	Message	Cause/Action
103036	ERROR	Unable to create the hierarchy for raw device "%s"	<p><b>Cause:</b> LifeKeeper was unable to create the resource {raw device} .</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the "create" operation.</p>
103037	ERROR	A RAW hierarchy does not exist for the tag "%s"	<p><b>Cause:</b> LifeKeeper was unable to find the raw resource {tag} .</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
103038	ERROR	LifeKeeper was unable to create a dependency between the DB2 hierarchy "%s" and the Raw hierarchy "%s"	<p><b>Cause:</b> The requested dependency creation between the parent DB2 resource and the child Raw resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the "create" operation.</p>
103039	ERROR	LifeKeeper could not disable the automatic startup feature of DB2 instance "%s"	<p><b>Cause:</b> An unexpected error occurred while attempting to update the DB2 setting.</p> <p><b>Action:</b> The DB2AUTOSTART will need to be updated manually to turn off the automatic startup of the instance at system boot.</p>
103040	ERROR	DB2 version "%s" is not installed on server "%s"	<p><b>Cause:</b> LifeKeeper could not find DB2 installed location.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103041	ERROR	The instance owner "%s" does not exist on target server "%s"	<p><b>Cause:</b> An attempt to retrieve the DB2 instance owner from template server during a "canextend" or "extend" operation failed.</p> <p><b>Action:</b> Verify the DB2 instance owner exists on the specified server. If the user does not exist, it should be created with the same uid and gid on all servers in the cluster.</p>

Code	Severity	Message	Cause/Action
103042	ERROR	The instance owner "%s" uids are different on target server "%s" and template server "%s"	<p><b>Cause:</b> The user id on the target server {target server} for the DB2 instance owner {user} does not match the value of the user {user} on the template server {template server}.</p> <p><b>Action:</b> The user ids for the DB2 instance owner {user} must match on all servers in the cluster. The user id mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103043	ERROR	The instance owner "%s" gids are different on target server "%s" and template server "%s"	<p><b>Cause:</b> The group id on the target server {target server} for the DB2 instance owner {user} does not match the value of the user {user} on the template server {template server}.</p> <p><b>Action:</b> The group ids for the DB2 instance owner {user} must match on all servers in the cluster. The group id mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103044	ERROR	The instance owner "%s" home directories are different on target server "%s" and template server "%s"	<p><b>Cause:</b> The home directory location of the user {user} on the target server {target server} does not match the DB2 instance owner's home directory on the template server {template server}.</p> <p><b>Action:</b> The home directory location of the DB2 instance owner {user} must match on all servers in the cluster. The location mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103045	ERROR	LifeKeeper was unable to get the DB2 "SVCENAME" parameter for the DB2 instance	<p><b>Cause:</b> There was an unexpected error running "db2 get dbm cfg" command.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103046	ERROR	Unable to get the value of the DB2 "SVCENAME" parameter for the DB2 instance %s.	<p><b>Cause:</b> The DB2 "SVCENAME" parameter is set to null.</p> <p><b>Action:</b> Check your DB2 configuration.</p>

Code	Severity	Message	Cause/Action
103047	ERROR	LifeKeeper was unable to get the contents of the "/etc/services" file on the server "%s"	<p><b>Cause:</b> "/etc/services" on the template server does not contain the service names for the DB2 instance.</p> <p><b>Action:</b> The service names in "/etc/services" for the DB2 instance must match on all servers in the cluster. The service names mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103048	ERROR	LifeKeeper was unable to get the contents of the "/etc/services" file on the server "%s"	<p><b>Cause:</b> "/etc/services" on the target server does not contain the service names for the DB2 instance.</p> <p><b>Action:</b> The service names in "/etc/services" for the DB2 instance must match on all servers in the cluster. The service names mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103049	ERROR	The "/etc/services" entries for the instance "%s" are different on target server "%s" and template server "%s"	<p><b>Cause:</b> The "/etc/services" entries for the instance are mismatched.</p> <p><b>Action:</b> The service names in "/etc/services" for the DB2 instance must match on all servers in the cluster. The service names mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103050	ERROR	The home directory "%s" for instance "%s" is not mounted on server "%s"	<p><b>Cause:</b> LifeKeeper could not find db2nodes.cfg for Multiple Partition instance.</p> <p><b>Action:</b> Ensure the home directory is mounted and retry the operation.</p>
103051	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> Failed to get resource information from the template server.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>

Code	Severity	Message	Cause/Action
103052	ERROR	LifeKeeper was unable to add instance "%s" and/or its variables to the DB2 registry	<p><b>Cause:</b> There was an unexpected error running "db2iset" command.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
103054	ERROR	Unable to determine the DB2 instance type	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance type.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103055	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find any nodes for the DB2 instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103060	ERROR	Unable to determine the DB2 instance home directory	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance home directory.</p> <p><b>Action:</b> Ensure the instance owner name is same as the instance name and retry the operation.</p>
103061	ERROR	Unable to determine the DB2 instance type	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance type.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103062	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find the node for the DB2 instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103063	ERROR	Unable to determine the DB2 install path	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find DB2 for the instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>

Code	Severity	Message	Cause/Action
103065	ERROR	Invalid input provided for "%s" utility operation, characters are not allowed.	<b>Cause:</b> Invalid parameters were specified for the "nodes" command. <b>Action:</b> Verify the parameters and retry the operation.
103066	ERROR	Unable to get the information for resource "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag}. <b>Action:</b> Verify the parameters and retry the operation.
103067	ERROR	The DB2 instance "%s" is not a EEE or Multiple Partition instance	<b>Cause:</b> The resource {tag} is single partition instance. <b>Action:</b> Verify the parameters and retry the operation.
103069	ERROR	Node "%s" is already protected by this hierarchy	<b>Cause:</b> Invalid parameters were specified for the "nodes" command. <b>Action:</b> Verify the parameters and retry the operation.
103070	ERROR	Node number "%s" is the last remaining node protected by resource "%s". Deleting all nodes is not allowed.	<b>Cause:</b> Invalid parameters were specified for the "nodes" command. <b>Action:</b> Verify the parameters and retry the operation.
103071	ERROR	LifeKeeper is unable to get the equivalent instance for resource "%s"	<b>Cause:</b> There was an unexpected error running "nodes" command. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
103072	ERROR	Unable to set NodesInfo for resource "%s" on "%s"	<b>Cause:</b> There was an unexpected error running "nodes" command. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.



Code	Severity	Message	Cause/Action
103073	ERROR	Unable to set NodesInfo for resource "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "nodes" command.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
103076	ERROR	Unable to determine the DB2 instance type	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance type.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103077	ERROR	Unable to determine the DB2 instance home directory	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance home directory.</p> <p><b>Action:</b> Ensure the instance owner name is same as the instance name and retry the operation.</p>
103078	ERROR	The database server is not running for instance "%s"	<p><b>Cause:</b> A process check for the DB2 instance did not find any processes running.</p> <p><b>Action:</b> The DB2 instance must be started.</p>
103079	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find any nodes for the DB2 instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103080	ERROR	One or more of the database partition servers for instance "%s" is down	<p><b>Cause:</b> All database partition servers should be running.</p> <p><b>Action:</b> Ensure all database partition servers are running and retry the operation.</p>
103082	ERROR	Failed to create flag "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create a flag for controlling DB2 local recovery processing.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>

Code	Severity	Message	Cause/Action
103083	ERROR	Failed to remove flag "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to remove a flag for controlling DB2 local recovery processing.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
103084	ERROR	Unable to determine the DB2 instance \"\${Instance}\" home directory	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance home directory.</p> <p><b>Action:</b> Ensure the instance owner name is same as the instance name and retry the operation.</p>
104002	FATAL	\$msg	<p><b>Cause:</b> This message indicates an internal software error.</p> <p><b>Action:</b> The stack trace indicates the source of the error.</p>
104003	FATAL	\$self->Val('Tag') . " is not an SDR resource"	<p><b>Cause:</b> A data replication action was attempted on a non data replication resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
104010	ERROR	\$self->{'md'}: bitmap merge failed, \$action	<p><b>Cause:</b> The bitmap merge operation has failed.</p> <p><b>Action:</b> The target server may have the mirror and/or protected filesystem mounted, or the bitmap file may be missing on the target. Check the target server.</p>
104022	ERROR	\$argv[1]: mdadm failed (\$ret	<p><b>Cause:</b> The "mdadm" command has failed to add a device into the mirror.</p> <p><b>Action:</b> This is usually a temporary condition.</p>
104023	ERROR	\$_	<p><b>Cause:</b> The message contains the output of the "mdadm" command.</p>

Code	Severity	Message	Cause/Action
104025	ERROR	failed to spawn monitor	<p><b>Cause:</b> The system failed to start the 'mdadm -F' monitor process. This should not happen under normal circumstances.</p> <p><b>Action:</b> Reboot the system to ensure that any potential conflicts are resolved.</p>
104026	ERROR	cannot create \$md	<p><b>Cause:</b> The mirror device could not be created.</p> <p><b>Action:</b> Ensure the device is not already in use and that all other parameters for the mirror creation are correct.</p>
104027	ERROR	\$_	<p><b>Cause:</b> This message contains the "mdadm" command output.</p>
104035	ERROR	Too many failures. Aborting resync of \$md	<p><b>Cause:</b> The device was busy for an abnormally long period of time.</p> <p><b>Action:</b> Reboot the system to be sure that the device is no longer busy.</p>
104036	ERROR	Failed to start nbd-server on \$target (error \$port	<p><b>Cause:</b> The nbd-server process could not be started on the target server.</p> <p><b>Action:</b> Ensure that the target disk device is available and that its Device ID has not changed.</p>
104037	ERROR	Failed to start compression (error \$port	<p><b>Cause:</b> The system was unable to start the 'balance' tunnel process or there was a network problem.</p> <p><b>Action:</b> Ensure that the network is operating properly and that TCP ports in the range 10000-10512 are opened and unused. Ensure that the software is installed properly on all systems.</p>

Code	Severity	Message	Cause/Action
104038	ERROR	Failed to start nbd-client on \$source (error \$ret	<p><b>Cause:</b> The nbd-client process has failed to start on the source server.</p> <p><b>Action:</b> Look up the reported errno value and try to resolve the problem reported. For example, an errno value of 110 means "Connection timed out", which may indicate a network or firewall problem.</p>
104039	ERROR	Failed to add \$nbd to \$md on \$source	<p><b>Cause:</b> This is usually a temporary condition.</p> <p><b>Action:</b> If this error persists, reboot the system to resolve any potential conflicts.</p>
104045	ERROR	failed to stop \$self->{'md'}	<p><b>Cause:</b> The mirror device could not be stopped.</p> <p><b>Action:</b> Ensure that the device is not busy or mounted. Try running "mdadm --stop" manually to stop the device.</p>
104048	WARN	failed to kill \$proc, pid \$pid	<p><b>Cause:</b> The process could not be signalled. This may indicate that the process has already died.</p> <p><b>Action:</b> Ensure that the process in question is no longer running. If it is, then reboot the system to clear up the unkillable process.</p>
104050	ERROR	Setting \$name on \$dest failed: \$ret. Please try again.	<p><b>Cause:</b> The system failed to set a 'mirrorinfo' file setting.</p> <p><b>Action:</b> Check the network and systems and retry the mirror setting operation.</p>
104052	FATAL	Specified existing mount point "%s" is not mounted	<p><b>Cause:</b> The mount point became unmounted.</p> <p><b>Action:</b> Ensure that the mount point is mounted and retry the operation.</p>

Code	Severity	Message	Cause/Action
104055	ERROR	Failed to set up temporary \$type access to data for \$self->{'tag'}. Error: \$ret	<p><b>Cause:</b> The filesystem or device was not available on the target server. The mirrored data will not be available on the target server until the mirror is paused and resumed again.</p> <p><b>Action:</b> Reboot the target server to resolve any potential conflicts.</p>
104057	ERROR	Failed to undo temporary access for \$self->{'tag'} on \$self->{'sys'}. Error: \$ret. Please verify that \$fsid is not mounted on server \$self->{'sys'}.	<p><b>Cause:</b> The filesystem could not be unmounted on the target server.</p> <p><b>Action:</b> Ensure that the filesystem and device are not busy on the target server. Reboot the target server to resolve any potential conflicts.</p>
104062	FATAL	Cannot find a device with unique ID "%s"	<p><b>Cause:</b> The target disk could not be identified.</p> <p><b>Action:</b> Ensure that the appropriate storage recovery kits are installed on the target server. Ensure that the Device ID of the target disk has not changed.</p>
104066	FATAL	Cannot get the hardware ID of device "%s"	<p><b>Cause:</b> A unique ID could not be found for the target disk device.</p> <p><b>Action:</b> Ensure that the appropriate storage recovery kits are installed on the target server. Ensure that the Device ID of the target disk has not changed.</p>
104067	FATAL	Asynchronous writes cannot be enabled without a bitmap file	<p><b>Cause:</b> An attempt was made to create a mirror with invalid parameters.</p> <p><b>Action:</b> A bitmap file parameter must be specified or synchronous writes must be specified.</p>
104068	FATAL	Failed to extend dependent resource %s to system %s. Error %s	<p><b>Cause:</b> The hierarchy extend operation failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
104070	FATAL	Unable to extend the mirror "%s" to system "%s"	<p><b>Cause:</b> The hierarchy extend operation failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
104071	ERROR	Failed to restore target device resources on \$target->{sys'}: \$err	<p><b>Cause:</b> The in-service operation has failed on the target server.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
104073	EMERG	WARNING: A temporary communication failure has occurred between systems %s and %s. In order to avoid data corruption, data resynchronization will not occur. MANUAL INTERVENTION IS REQUIRED. In order to initiate data resynchronization, you should: 1) Take one of the following resources out of service (this resource will become the mirror target): %s on %s or %s on %s. 2) Take the other resource out of service (this resource will become the mirror source). 3) Run %s/bitmap -d %s on the system that will become mirror source. 4) Bring the mirror in service on the source system. A full resync will occur.	<p><b>Cause:</b> A temporary communication failure (split-brain scenario) has occurred between the source and target servers.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
104074	FATAL	Cannot get the hardware ID of device "%s"	<p><b>Cause:</b> There is no storage recovery kit that recognizes the underlying disk device that you are attempting to use for the mirror.</p> <p><b>Action:</b> Make sure the appropriate storage recovery kits are installed. If necessary, place your device name in the /opt/LifeKeeper/subsys/scsi/resources/DEVNAME/device_pattern file.</p>

Code	Severity	Message	Cause/Action
104081	FATAL	Cannot make the %s filesystem on "%s" (%d)	<p><b>Cause:</b> The "mkfs" command failed.</p> <p><b>Action:</b> Ensure that the disk device is writable and free of errors and that the filesystem tools for the selected filesystem are installed.</p>
104082	FATAL	%s	<p><b>Cause:</b> This message contains the output of the "mkfs" command.</p>
104083	FATAL	Cannot create filesys hierarchy "%s"	<p><b>Cause:</b> The resource creation failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
104086	ERROR	The "%s_data_corrupt" flag is set in "%s/sub-sys/scsi/resources/netraid/" on system "%s". To avoid data corruption, LifeKeeper will not restore the resource	<p><b>Cause:</b> The data corrupt flag file has been set as a precaution to prevent accidental data corruption. The mirror cannot be restored on this server until the file is removed.</p> <p><b>Action:</b> If you are sure that the data is valid on the server in question, you can either: 1) remove the file and restore the mirror, or 2) force the mirror online using the LifeKeeper GUI or 'mirror_action force' command.</p>
104092	ERROR	Mirror target resource movement to system %s : status %s	<p><b>Cause:</b> The hierarchy switchover operation has failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
104099	ERROR	Unable to unextend the mirror for resource "%s" from system "%s"	<p><b>Cause:</b> The hierarchy unextend operation failed.</p> <p><b>Action:</b> Reboot the target server to resolve any potential conflicts and retry the operation.</p>

Code	Severity	Message	Cause/Action
104106	ERROR	remote 'bitmap -m' command failed on \$target->{'sys'}: \$ranges	<p><b>Cause:</b> The bitmap merge command failed on the target server. This may be caused by one of two things: 1) The bitmap file may be missing or corrupted, or 2) the mirror (md) device may be active on the target.</p> <p><b>Action:</b> Make sure that the mirror and protected filesystem are not active on the target. If the target's bitmap file is missing, pause and resume the mirror to recreate the bitmap file.</p>
104107	ERROR	Asynchronous writes cannot be enabled without a bitmap file	<p><b>Cause:</b> Invalid parameters were specified for the mirror create operation.</p>
104108	ERROR	Local Partition not available	<p><b>Cause:</b> Invalid parameters were specified for the mirror create operation.</p>
104109	ERROR	Cannot get the hardware ID of device "%s"	<p><b>Cause:</b> A unique ID could not be determined for the disk device.</p> <p><b>Action:</b> Ensure that the appropriate storage recovery kits are installed on the server. Ensure that the Device ID of the disk has not changed.</p>
104111	FATAL	Insufficient input parameters for "%s" creation	<p><b>Cause:</b> Invalid parameters were specified for the mirror create operation.</p>
104112	FATAL	Insufficient input parameters for "%s" creation	<p><b>Cause:</b> Invalid parameters were specified for the mirror create operation.</p>
104113	FATAL	Insufficient input parameters for "%s" creation	<p><b>Cause:</b> Invalid parameters were specified for the mirror create operation.</p>
104114	FATAL	Insufficient input parameters for "%s" creation	<p><b>Cause:</b> Invalid parameters were specified for the mirror create operation.</p>
104115	FATAL	Insufficient input parameters for "%s" creation	<p><b>Cause:</b> Invalid parameters were specified for the mirror create operation.</p>



Code	Severity	Message	Cause/Action
104117	FATAL	Insufficient input parameters for "%s" creation	<b>Cause:</b> Invalid parameters were specified for the mirror create operation.
104118	FATAL	Cannot unmount existing Mount Point "%s"	<b>Cause:</b> The mount point is busy. <b>Action:</b> Make sure the filesystem is not busy. Stop any processes or applications that may be accessing the filesystem.
104119	FATAL	Invalid data replication resource type requested ("%s")	<b>Cause:</b> An invalid parameter was specified for the mirror create operation.
104124	EMERG	WARNING: A temporary communication failure has occurred between systems %s and %s. In order to avoid data corruption, data resynchronization will not occur. MANUAL INTERVENTION IS REQUIRED. In order to initiate data resynchronization, you should take one of the following resources out of service: %s on %s or %s on %s. The resource that is taken out of service will become the mirror target.	<b>Cause:</b> A temporary communication failure (split-brain scenario) has occurred between the source and target servers. <b>Action:</b> Perform the steps listed in the message text.
104125	ERROR	failed to start '\$cmd \$_[2] \$user_args' on '\$_[3]'	<b>Cause:</b> The specified command failed. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
104126	ERROR	\$_	<b>Cause:</b> This message contains the output of the command that was reported as failing in message 104125.
104129	WARN	The replication connection for mirror "%s" (resource: "%s") is down (reason: %s)	<b>Cause:</b> The replication connection for the mirror is down. <b>Action:</b> Check the network.

Code	Severity	Message	Cause/Action
104130	ERROR	Mirror resize failed on %s (%s). You must successfully complete this operation before using the mirror. Please try again.	<p><b>Cause:</b> The mirror resize operation has failed to update the mirror metadata on the listed system.</p> <p><b>Action:</b> You must successfully complete the resize before using the mirror. Re-run mirror_resize (possibly using -f to force the operation if necessary).</p>
104136	ERROR	Extend failed.	<p><b>Cause:</b> The hierarchy extend operation failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
104143	ERROR	Mirror resume was unsuccessful (\$ret	<p><b>Cause:</b> The mirror could not be established.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problems.</p>
104144	ERROR	Unable to stop the mirror access for \$self->{'md'} on system \$self->{'sys'}. Error: \$ret. Use the \"mdadm --stop \$self->{'md'}\" command to manually stop the mirror.	<p><b>Cause:</b> The mirror device created on the target node when the mirror was paused could not be stopped.</p> <p><b>Action:</b> Ensure that the device is not busy or mounted. Try running \"mdadm --stop\" manually to stop the device.</p>
104156	WARN	Resynchronization of \"%s\" is in PENDING state. Current sync_action is: \"%s\"	<p><b>Cause:</b> The resynchronization of the md device is detected in PENDING state.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by forcing a resynchronization. Check the logs for related errors. When successful assure that the PENDING state has been cleared in /proc/mdstat and the resynchronization is in progress or has been completed for the datarep resource.</p>
122005	ERROR	Unable to \"%s\" on \"%s\"	<p><b>Cause:</b> There was an unexpected error running \"getlocks\".</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
122007	ERROR	Unable to "%s" on "%s"	<b>Cause:</b> There was an unexpected error running "rlocks". <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
122009	ERROR	The path %s is not a valid file.	<b>Cause:</b> There is no listener.ora file. <b>Action:</b> Ensure the file exists and retry the operation.
122010	ERROR	The listener user does not exist on the server %s.	<b>Cause:</b> "Stat" command could not get user id. <b>Action:</b> Retry the operation.
122011	ERROR	The listener user does not exist on the server %s.	<b>Cause:</b> UID is not in passwd file. <b>Action:</b> Ensure the UID exists in passwd file and retry the operation.
122012	ERROR	The listener user does not exist on the server %s.	<b>Cause:</b> User name is not in passwd file. <b>Action:</b> Ensure the user name exists in passwd file; retry the operation.
122023	ERROR	The %s command failed (%d	<b>Cause:</b> This message contains the return code of the "lsnrctl" command. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
122024	ERROR	\$line	<b>Cause:</b> The message contains the output of the "lsnrctl" command. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
122039	ERROR	Usage error	<b>Cause:</b> Invalid parameters were specified for the restore operation. <b>Action:</b> Verify the parameters and retry the operation.

Code	Severity	Message	Cause/Action
122040	ERROR	Script \$cmd has hung on the restore of \"\$opt_t\". Forcibly terminating.	<p><b>Cause:</b> The listener restore script reached its timeout value.</p> <p><b>Action:</b> Ensure listener.ora is valid and that LSNR_START_TIME (default 35 seconds) in /etc/default/LifeKeeper is set to a value greater than or equal to the time needed to start the listener.</p>
122041	ERROR	END failed %s of \"%s\" on server \"%s\" due to a \"%s\" signal	<p><b>Cause:</b> LifeKeeper was unable to restore the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122045	ERROR	Error getting resource information for resource \"%s\" on server \"%s\"	<p><b>Cause:</b> Failed to get resource information.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122046	ERROR	Usage error	<p><b>Cause:</b> Invalid parameters were specified for the restore operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122049	ERROR	The script \$cmd has hung on remove of \"\$opt_t\". Forcibly terminating.	<p><b>Cause:</b> The listener remove script reached its timeout value.</p> <p><b>Action:</b> Ensure listener.ora is valid and that LSNR_STOP_TIME (default 35 seconds) in /etc/default/LifeKeeper is set to a value greater than or equal to the time needed to stop the listener.</p>
122051	ERROR	Error getting resource information for resource \"%s\" on server \"%s\"	<p><b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>

Code	Severity	Message	Cause/Action
122055	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> LifeKeeper was unable to quickCheck the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122057	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122064	WARN	The %s level is set to %s a %s will not occur.	<p><b>Cause:</b> The minimal Listener protection level is Start and Monitor.</p> <p><b>Action:</b> Start the listener manually.</p>
122066	ERROR	Script has hung checking \"%\$tag\". Forcibly terminating.	<p><b>Cause:</b> The listener quickCheck script reached its timeout value.</p> <p><b>Action:</b> Ensure listener.ora is valid and that LSNR_STATUS_TIME (default 15 seconds) in /etc/default/LifeKeeper is set to a value greater than or equal to the time needed to check the listener.</p>
122067	ERROR	Usage error	<p><b>Cause:</b> Invalid parameters were specified for the quickCheck operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122069	ERROR	Usage error	<p><b>Cause:</b> Invalid parameters were specified for the delete operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122072	ERROR	%s: resource "%s" not found on local server	<p><b>Cause:</b> Invalid parameters were specified for the recover operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>

Code	Severity	Message	Cause/Action
122074	WARN	The local recovery attempt has failed but %s level is set to %s preventing a failover to another node in the cluster. With %s recovery set all local recovery failures will exit successfully to prevent resource failovers.	<b>Cause:</b> The optional listener recovery level is set to local recovery only. <b>Action:</b> Switch over the resource tree manually.
122078	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<b>Cause:</b> LifeKeeper was unable to recover the resource {resource} on {server}. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
122082	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122083	ERROR	\$cmd has hung checking \"\$tag\". Forcibly terminating	<b>Cause:</b> The recover script was stopped by signal. <b>Action:</b> Ensure listener.ora is valid.
122084	ERROR	Cannot extend resource "%s" to server "%s"	<b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}. <b>Action:</b> Verify the parameters and retry the operation.
122085	ERROR	Usage: %s %s	<b>Cause:</b> Invalid parameters were specified for the canextend operation. <b>Action:</b> Verify the parameters and retry the operation.
122086	ERROR	The values specified for the target and the template servers are the same. Please specify the correct values for the target and template servers.	<b>Cause:</b> The values specified for the target and the template servers are the same. <b>Action:</b> Perform the steps listed in the message text.

Code	Severity	Message	Cause/Action
122087	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122088	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> Failed to get listener user name from resource information. <b>Action:</b> Ensure the resource info field is valid then retry the operation.
122089	ERROR	The listener user %s does not exist on the server %s.	<b>Cause:</b> User name is not in passwd file. <b>Action:</b> Ensure the user name exists in passwd file and retry the operation.
122090	ERROR	The id for user %s is not the same on template server %s and target server %s.	<b>Cause:</b> User ID should be same on both servers. <b>Action:</b> Trim user ID to the same.
122091	ERROR	The group id for user %s is not the same on template server %s and target server %s.	<b>Cause:</b> Group ID should be same on both servers. <b>Action:</b> Trim group ID to the same.
122092	ERROR	Cannot access canextend script "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to run pre-extend checks because it was unable to find the "canextend" script on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122097	ERROR	Usage: %s %s	<b>Cause:</b> Invalid arguments were specified for the "configActions" operation. <b>Action:</b> Verify the arguments and retry the operation.
122098	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}. <b>Action:</b> Check your LifeKeeper configuration.

Code	Severity	Message	Cause/Action
122099	ERROR	Unable to update the resource %s to change the %s to %s on %s.	<p><b>Cause:</b> LifeKeeper failed to put information into the info field.</p> <p><b>Action:</b> Restart LifeKeeper and retry the operation.</p>
122100	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122101	ERROR	Unable to update the resource %s to change the %s to %s on %s.	<p><b>Cause:</b> LifeKeeper failed to put information to info field on {server}.</p> <p><b>Action:</b> Restart LifeKeeper on {server} and retry the operation.</p>
122103	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid parameters were specified for the create operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122124	ERROR	END failed hierarchy "%s" of resource "%s" on server "%s" with return value of %d	<p><b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122126	ERROR	Unable to "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "rlslocks".</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122127	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>



Code	Severity	Message	Cause/Action
122129	ERROR	Unable to "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "getlocks."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122131	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122133	ERROR	Unable to create a file system resource hierarchy for the file system %s.	<p><b>Cause:</b> There was an unexpected error running "filesyshier."</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
122135	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122140	ERROR	Resource "%s" is not ISP on server "%s" Manually bring the resource in service and retry the operation	<p><b>Cause:</b> IP resource {tag} which the listener resource depends on should be ISP.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
122141	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122144	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid parameters were specified for the "create_ins" operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>

Code	Severity	Message	Cause/Action
122145	ERROR	An error has occurred in utility %s on server %s. View the LifeKeeper logs for details and retry the operation.	<p><b>Cause:</b> There was an unexpected error running "app_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122146	ERROR	An error has occurred in utility %s on server %s. View the LifeKeeper logs for details and retry the operation.	<p><b>Cause:</b> There was an unexpected error running "typ_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122147	ERROR	An error has occurred in utility %s on server %s. View the LifeKeeper logs for details and retry the operation.	<p><b>Cause:</b> There was an unexpected error running "newtag."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122148	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122149	ERROR	An error has occurred in utility %s on server %s. View the LifeKeeper logs for details and retry the operation.	<p><b>Cause:</b> There was an unexpected error running "ins_setstate."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122150	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122151	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid arguments were specified for the "depstoextend" operation.</p> <p><b>Action:</b> Verify the arguments and retry the operation.</p>

Code	Severity	Message	Cause/Action
122152	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid parameters were specified for the "extend" operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122153	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122154	ERROR	Cannot extend resource "%s" to server "%s"	<p><b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}.</p>
122155	ERROR	Resource with either matching tag "%s" or id "%s" already exists on server "%s" for App "%s" and Type "%s"	<p><b>Cause:</b> During the Listener resource extension, a resource instance was found using the same {tag} and/or {id} but with a different resource application and type.</p> <p><b>Action:</b> Resource IDs must be unique. The resource instance with the ID matching the Oracle Listener resource instance must be removed.</p>
122156	ERROR	Cannot access extend script "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to extend the resource hierarchy because it was unable to find the script EXTEND on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122157	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid arguments were specified for the "getConfiglps" operation.</p> <p><b>Action:</b> Verify the arguments and retry the operation.</p>
122158	ERROR	The file %s is not a valid listener file. The file does not contain any listener definitions.	<p><b>Cause:</b> Failed to find any listener definitions.</p> <p><b>Action:</b> Ensure listener definition is in the listener.ora and retry the operation.</p>

Code	Severity	Message	Cause/Action
122159	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid arguments were specified for the "getSidListeners" operation.</p> <p><b>Action:</b> Verify the arguments and retry the operation.</p>
122160	ERROR	The file %s is not a valid listener file. The file does not contain any listener definitions.	<p><b>Cause:</b> Failed to find any listener definitions.</p> <p><b>Action:</b> Ensure listener definition is in the listener.ora and retry the operation.</p>
122161	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid arguments were specified for the "lsn-display" operation.</p> <p><b>Action:</b> Verify the arguments and retry the operation.</p>
122162	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122163	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid parameters were specified for the updateHelper operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122164	ERROR	END failed hierarchy "%s" of resource "%s" on server "%s" with return value of %d	<p><b>Cause:</b> LifeKeeper was unable to update the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122166	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid parameters were specified for the "updateHelper" operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>

Code	Severity	Message	Cause/Action
122170	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122171	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122172	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid arguments were specified for the "updIPDeps" operation.</p> <p><b>Action:</b> Verify the arguments and retry the operation.</p>
122173	ERROR	END failed hierarchy "%s" of resource "%s" on server "%s" with return value of %d	<p><b>Cause:</b> LifeKeeper was unable to update the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122175	ERROR	Unable to "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "rlslocks."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122177	ERROR	Unable to "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "getlocks."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122180	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
122181	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122183	ERROR	The path %s is not a valid file.	<p><b>Cause:</b> There is no listener.ora file.</p> <p><b>Action:</b> Ensure the file exists and retry the operation.</p>
122185	ERROR	The file %s is not a valid listener file. The file does not contain any listener definitions.	<p><b>Cause:</b> LifeKeeper failed to find any valid listener definitions.</p> <p><b>Action:</b> Ensure there are valid listener definitions in the listener.ora and retry the operation.</p>
122186	ERROR	The value specified for %s cannot be empty. Please specify a value for this field.	<p><b>Cause:</b> The config and/or executable {path} field is empty.</p> <p><b>Action:</b> Input a non-empty value for {path} and retry the operation.</p>
122187	ERROR	The path %s is not a valid file or directory.	<p><b>Cause:</b> The defined {path} is invalid.</p> <p><b>Action:</b> Ensure the {path} exists and retry the operation.</p>
122188	ERROR	The path %s is not a valid file or directory.	<p><b>Cause:</b> There is no {path}.</p> <p><b>Action:</b> Ensure the {path} exists and retry the operation.</p>
122189	ERROR	The value specified for %s cannot be empty. Please specify a value for this field.	<p><b>Cause:</b> The config and/or executable Path field is empty.</p> <p><b>Action:</b> Input path for the field.</p>
122190	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid arguments were specified for the "valid_rpath" operation.</p> <p><b>Action:</b> Verify the arguments and retry the operation.</p>

Code	Severity	Message	Cause/Action
122191	ERROR	The values specified for the target and the template servers are the same.	<p><b>Cause:</b> Invalid argument of valid_rpath.</p> <p><b>Action:</b> Ensure arguments and retry the operation.</p>
122192	ERROR	Unable to find the configuration file "oratab" in its default locations, /etc/oratab or %s on "%s"	<p><b>Cause:</b> There is no oratab file in /etc/oratab or {path}.</p> <p><b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.</p>
122193	ERROR	Unable to find the configuration file "oratab" in its default locations, /etc/oratab or %s on "%s"	<p><b>Cause:</b> There is no oratab file in /etc/oratab or {path}.</p> <p><b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.</p>
122194	ERROR	Unable to find the configuration file "oratab" in its default locations, /etc/oratab or %s on "%s"	<p><b>Cause:</b> There is no oratab file in /etc/oratab or {path}.</p> <p><b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.</p>
122195	ERROR	Unable to find the configuration file "oratab" in its default locations, /etc/oratab or %s on "%s"	<p><b>Cause:</b> There is no oratab file in /etc/oratab or {path}.</p> <p><b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.</p>
122196	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> LifeKeeper was unable to remove the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
122197	ERROR	Unable to find the configuration file \"oratab\" in its default locations, /etc/oratab or \$listener::oraTab on \"\$me\"	<p><b>Cause:</b> There is no oratab file in /etc/oratab or {path}.</p> <p><b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.</p>
122501	ERROR	DB instance \"%s\" is already protected on \"%s\".	<p><b>Cause:</b> An attempt was made to protect an Oracle database instance {sid} that is already under LifeKeeper protection on {server}.</p> <p><b>Action:</b> You must select a different database instance {sid} for LifeKeeper protection.</p>
122502	ERROR	Failed to create object instance for Oracle on \"%s\".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122503	ERROR	Unable to locate the oratab file \"%s\" on \"%s\".	<p><b>Cause:</b> The oratab file was not found at the default or alternate locations on {server}.</p> <p><b>Action:</b> Verify the oratab file exists and has proper permissions for the Oracle user. A valid oratab file is required to complete the "create" operation.</p>
122504	ERROR	Unable to determine Oracle user for \"%s\" on \"%s\".	<p><b>Cause:</b> The Oracle Application Recovery Kit was unable to determine the ownership of the Oracle database installation binaries.</p> <p><b>Action:</b> The owner of the Oracle binaries must be a valid non-root user on {server}. Correct the permissions and ownership of the Oracle database installation and retry the operation.</p>



Code	Severity	Message	Cause/Action
122505	ERROR	The Oracle database "%s" is not running or no open connections are available on "%s".	<p><b>Cause:</b> The database instance {sid} was not running or connections to the database were not available via the credentials provided.</p> <p><b>Action:</b> The database instance {sid} must be started on {server} and the proper credentials must be provided for the completion of the "create" operation.</p>
122506	ERROR	Unable to determine Oracle dbspaces and logfiles for "%s" on "%s".	<p><b>Cause:</b> A query to determine the location of required tablespaces, logfiles and related database files failed. This may have been caused by an internal database error.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>
122507	ERROR	Unknown chunk type found for "%s" on "%s".	<p><b>Cause:</b> The specified tablespace, logfile or other required database file is not one of the LifeKeeper supported file or character device types.</p> <p><b>Action:</b> The specified file {database_file} must reference an existing character device or file. Consult the Oracle installation documentation to recreate the specified file {database_file} as a supported file or character device type.</p>

Code	Severity	Message	Cause/Action
122508	ERROR	DB Chunk "%s" for "%s" on "%s" does not reside on a shared file system.	<p><b>Cause:</b> The specified tablespace, logfile or other required database file {database_file} does not reside on a file system that is shared with other systems in the cluster.</p> <p><b>Action:</b> Use the LifeKeeper UI or "lcdstatus (1M)" to verify that communication paths have been properly created. Use "rpm" to verify that the necessary Application Recovery Kits for storage protection have been installed. Verify that the file is, in fact, not on shared storage, and if not, move it to a shared storage device.</p>
122510	ERROR	File system create failed for "%s" on "%s". Reason	<p><b>Cause:</b> LifeKeeper was unable to create the resource {filesystem} on the specified server {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the "create" operation.</p>
122511	ERROR	%s	<p><b>Cause:</b> The message contains the output of the "filesyshier" command.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
122513	ERROR	Dependency creation between Oracle database "%s (%s)" and the dependent resource "%s" on "%s" failed. Reason	<p><b>Cause:</b> LifeKeeper was unable to create a dependency between the database resource {tag} and the necessary child resource {childtag}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Once any problems have been corrected, it may be possible to create the dependency between {tag} and {childtag} manually.</p>

Code	Severity	Message	Cause/Action
122514	ERROR	Unable to "%s" on "%s" during resource create.	<p><b>Cause:</b> The Oracle Application Recovery Kit was unable to release the administrative lock using the "rlslocks" command.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
122516	ERROR	Raw device resource created failed for "%s" on "%s". Reason	<p><b>Cause:</b> LifeKeeper was unable to create the resource {raw device} on the specified server {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the "create" operation.</p>
122519	ERROR	In-service attempted failed for tag "%s" on "%s".	<p><b>Cause:</b> The "perform_action" command for {tag} on {server} failed to start the database {sid}. The in-service operation has failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the "create" operation.</p>
122521	ERROR	Create of app "%s" on "%s" failed with return code of "%d".	<p><b>Cause:</b> There was an error running the command "app_create" to create the internal application type.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122522	ERROR	Create of typ "%s" for app "%s" on "%s" failed with return code of "%d".	<p><b>Cause:</b> There was an error running the command "typ_create" to create the internal resource type.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
122524	ERROR	Setting "resstate" for resource "%s" on "%s" failed with return code of "%d".	<p><b>Cause:</b> There was an error running the command "ins_setstate" to set the resource state to {state}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122525	ERROR	The values specified for the target and the template servers are the same: "%s".	<p><b>Cause:</b> The value specified for the target and template servers for the "extend" operation were the same.</p> <p><b>Action:</b> You must specify the correct parameter for the {target server} and {template server}. The {target server} is the server where the {tag} will be extended.</p>
122526	ERROR	Unable to locate the oratab file in "/etc" or in "%s" on "%s".	<p><b>Cause:</b> The oratab file was not found at the default or alternate locations on {server}.</p> <p><b>Action:</b> Verify the oratab file exists and has proper permissions for the Oracle user. A valid oratab file is required to complete the "extend" operation.</p>
122527	ERROR	Unable to retrieve the Oracle user on "%s".	<p><b>Cause:</b> An attempt to retrieve the Oracle user from {template server} during a "canextend" or "extend" operation failed.</p> <p><b>Action:</b> The owner of the Oracle binaries must be a valid user on {target server} and {template server}. Correct the permissions and ownership of the Oracle database installation and retry the operation.</p>

Code	Severity	Message	Cause/Action
122528	ERROR	The Oracle user and/or group information for user "%s" does not exist on the server "%s".	<p><b>Cause:</b> LifeKeeper is unable to find the Oracle user and/or group information for the Oracle user {user} on the server {server}.</p> <p><b>Action:</b> Verify the Oracle user {user} exists on the specified {server}. If the user {user} does not exist, it should be created with the same uid and gid on all servers in the cluster.</p>
122529	ERROR	The id for user "%s" is not the same on template server "%s" and target server "%s".	<p><b>Cause:</b> The user id on the target server {target server} for the Oracle user {user} does not match the value of the user {user} on the template server {template server}.</p> <p><b>Action:</b> The user ids for the Oracle user {user} must match on all servers in the cluster. The user id mismatch should be corrected manually on all servers before retrying the "extend" operation.</p>
122530	ERROR	The group id for user "%s" is not the same on template server "%s" and target server "%s".	<p><b>Cause:</b> The group id on the target server {target server} for the Oracle user {user} does not match the value of the user {user} on the template server {template server}.</p> <p><b>Action:</b> The group ids for the Oracle user {user} must match on all servers in the cluster. The group id mismatch should be corrected manually on all servers before retrying the "extend" operation.</p>
122532	ERROR	No file system or raw devices found to extend for "%s" on "%s".	<p><b>Cause:</b> There were no dependent file system or raw device resources found for the Oracle resource {tag} on server {template server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>

Code	Severity	Message	Cause/Action
122533	WARN	A RAMDISK (%s) was detected in the ORACLE Database configuration for "%s" on "%s". LifeKeeper cannot protect RAMDISK. This RAMDISK resource will not be protected by LifeKeeper! ORACLE hierarchy creation will continue.	<p><b>Cause:</b> The specified tablespace, logfile or other database file {database_file} was detected as a ramdisk. No protection is available for this type of resource in the current LifeKeeper product.</p> <p><b>Action:</b> The ramdisk will not be protected. You must manually ensure that the required database file {database_file} will be available during all Oracle database operations.</p>
122534	ERROR	Failed to initialize object instance for Oracle sid "%s" on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122537	ERROR	Update of instance info field for "%s" on "%s" failed (%s).	<p><b>Cause:</b> There was an error while running the command "ins_setinfo" to update the internal resource information field.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122538	ERROR	Initial connect with query buffer to database "%s" on "%s" failed, testing output.	<p><b>Cause:</b> A connection attempt to the Oracle database {sid} to determine the database status has failed.</p> <p><b>Action:</b> The connection attempt failed with the specified credentials. Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>

Code	Severity	Message	Cause/Action
122542	ERROR	The "%s [ %s ]" attempt of the database "%s" appears to have failed on "%s".	<p><b>Cause:</b> The attempted Oracle action {action} using method {action_method} for the database instance {sid} failed on the server {server}.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>
122543	ERROR	All attempts to "%s" database "%s" on "%s" failed	<p><b>Cause:</b> All efforts to perform the action {action} on the Oracle database {sid} on server {server} have failed.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>
122544	ERROR	Update of "%s" sid "%s" on "%s" failed. Reason: "%s" "%s" failed: "%s".	<p><b>Cause:</b> An unexpected error occurred while attempting to update the oratab entry for the database {sid}. The error occurred while attempting to open the oratab file.</p> <p><b>Action:</b> The oratab file entry for {sid} will need to be updated manually to turn off the automatic start up of the database at system boot.</p>
122545	ERROR	Unable to locate the oratab file in "/etc" or in "%s" on "%s".	<p><b>Cause:</b> The oratab file was not found at the default or alternate locations on {server}.</p> <p><b>Action:</b> Verify the oratab file exists and has proper permissions for the oracle user. A valid oratab file is required to complete the "extend" operation.</p>

Code	Severity	Message	Cause/Action
122546	ERROR	Unable to open file "%s" on "%s" (%s).	<p><b>Cause:</b> The specified file {file} could not be opened or accessed on the server {server} due to the error {error}.</p> <p><b>Action:</b> Verify the existence and permissions on the specified file {file}. Check adjacent log messages for further details and related errors. You must correct any reported errors before retrying the operation.</p>
122547	ERROR	(cleanUpPids):Forcefully killing hung pid(s):pid(s)="%s"	<p><b>Cause:</b> The process {pid} failed to respond to the request to terminate gracefully. The process {pid} will be forcefully terminated.</p> <p><b>Action:</b> Use the command line to verify that the process {pid} has been terminated. Check the adjacent log messages for further details and related messages.</p>
122548	ERROR	Unable to locate the DB utility (%s/%s) on this host.	<p><b>Cause:</b> The Oracle binaries and required database utility {utility} located at {path/utility} were not found on this server {server}.</p> <p><b>Action:</b> Verify that the Oracle binaries and required software utilities are installed and properly configured on the server {server}. The Oracle binaries must be installed locally on each node or located on shared storage available to all nodes in the cluster.</p>
122549	ERROR	Oracle internal error or non-standard Oracle configuration detected. Oracle User and/or Group set to "root".	<p><b>Cause:</b> The detected ownership of the Oracle database installation resolves to the root user and/or root group. Ownership of the Oracle installation by root is a non-standard configuration.</p> <p><b>Action:</b> The owner of the Oracle binaries must be a valid non-root user on {server}. Correct the permissions and ownership of the Oracle database installation and retry the operation.</p>



Code	Severity	Message	Cause/Action
122550	ERROR	Initial inspection of "%s" failed, verifying failure or success of received output.	<p><b>Cause:</b> The previous Oracle query {query} or command {cmd} failed to return success.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>
122551	ERROR	Logon failed with "%s" for "%s" on "%s". Please check username/password and privileges.	<p><b>Cause:</b> The logon with the credentials {credentials} for the database instance {sid} on server {server} failed. An invalid user {user} or password was specified.</p> <p><b>Action:</b> Verify that the Oracle database user {user} and password {password} are indeed valid. In addition, the Oracle database user {user} must have sufficient privileges for the attempted action.</p>
122552	ERROR	%s	<p><b>Cause:</b> The message contains the output of the "sqlplus" command.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
122553	ERROR	Unable to open file "%s" on "%s" (%s).	<p><b>Cause:</b> The specified file {file} could not be opened or accessed on the server {server} due to the error {error}.</p> <p><b>Action:</b> Verify the existence and permissions on the specified file {file}. Check adjacent log messages for further details and related errors. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
122554	ERROR	The tag "%s" on "%s" is not an Oracle instance or it does not exist.	<p><b>Cause:</b> The specified tag {tag} on server {server} does not refer to an existing and valid Oracle resource instance.</p> <p><b>Action:</b> Use the UI or "lcdstatus (1M)" to verify the existence of the resource tag {tag}. The resource tag {tag} must be an Oracle resource instance to use the command "ora-display."</p>
122555	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to update the authorized user, password and database role for the Oracle resource instance.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122557	ERROR	Update of user and password failed for "%s" on "%s".	<p><b>Cause:</b> A request to update the user and password for the resource tag {tag} failed. The specified credentials failed the initial validation/connection attempt on server {server}.</p> <p><b>Action:</b> Verify the correct credentials {user/password} were specified for the attempted operation. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122559	ERROR	Update of user and password failed for "%s" on "%s".	<p><b>Cause:</b> The update of the user and password information for the resource tag {tag} on server {server} failed.</p> <p><b>Action:</b> Verify the correct credentials {user/password} were specified for the attempted operation. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
122562	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The required Oracle executable {exe} was not found on this server {server}.</p> <p><b>Action:</b> Verify that the Oracle binaries and required software utilities are installed and properly configured on the server {server}. The Oracle binaries must be installed locally on each node or located on shared storage available to all nodes in the cluster.</p>
122566	ERROR	Unable to find Oracle home for "%s" on "%s".	<p><b>Cause:</b> The Oracle home directory {Oracle home} does not appear to contain files necessary for the proper operation of the Oracle instance {sid}.</p> <p><b>Action:</b> Verify using the command line that the Oracle home directory {Oracle home} contains the Oracle binaries, a valid spfile{sid}.ora or init{sid}.ora file.</p>
122567	ERROR	Oracle SID mismatch. The instance SID "%s" does not match the SID "%s" specified for the command.	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected. The specified internal ID {id} does not match the expected SID {sid}.</p> <p><b>Action:</b> Verify the parameters are correct. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122568	ERROR	DB Processes are not running on "%s".	<p><b>Cause:</b> A process check for the Oracle instance did not find any processes running on server {server}.</p> <p><b>Action:</b> If local recovery is enabled, the Oracle instance will be restarted locally. Check adjacent log messages for further details and related messages.</p>

Code	Severity	Message	Cause/Action
122572	ERROR	Failed to create flag "%s" on "%s".	<p><b>Cause:</b> An unexpected error occurred attempting to create a flag for controlling Oracle local recovery processing causing a failover to the standby node.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
122574	ERROR	all attempts to shutdown the database %s failed on "%s".	<p><b>Cause:</b> The shutdown of the Oracle database failed during a local recovery process most likely caused because the maximum number of database connections has been reached.</p> <p><b>Action:</b> Check the Oracle logs for connection failures caused by the maximum number of available connections being reached, and if found, consider increasing the value. Additionally, set the tunable LK_ORA_NICE to 1 to prevent connection failures from causing a quickCheck failure followed by a local recovery attempt.</p>
122597	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected during pre-extend checking.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the pre-extend.</p>
122598	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being created while attempting to determine the validity of the Oracle home directory.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the "create."</p>

Code	Severity	Message	Cause/Action
122599	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to look up the Oracle user on the template system.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the extend.</p>
122600	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to display the resource properties.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the display of the resource properties.</p>
122601	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to check for valid database authorization.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the command.</p>
122603	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to perform health checks on the Oracle resource instance.</p> <p><b>Action:</b> Check that correct arguments were passed to the quickCheck command and also check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the restore.</p>

Code	Severity	Message	Cause/Action
122604	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to perform a local recovery on the Oracle resource instance.</p> <p><b>Action:</b> Check that correct arguments were passed to the "recover" command, and also check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the recover.</p>
122606	ERROR	The Oracle database "%s" is not running or no open connections are available on "%s".	<p><b>Cause:</b> The database instance {sid} was not running or connections to the database are not available via the credentials provided.</p> <p><b>Action:</b> The database instance {sid} must be started on {server} and the proper credentials must be provided for the completion of the selected operation.</p>
122607	ERROR	The Oracle database "%s" is not running or no open connections are available on "%s".	<p><b>Cause:</b> The database instance {sid} was not running or connections to the database are not available via the credentials provided.</p> <p><b>Action:</b> The database instance {sid} must be started on {server} and the proper credentials must be provided for the completion of the selected operation.</p>
122608	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> The "remove" operation failed to create the resource object instance required to take the Oracle resource Out of Service.</p> <p><b>Action:</b> Check that correct arguments were passed to the "remove" command and also check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the restore.</p>

Code	Severity	Message	Cause/Action
122609	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> The "restore" operation failed to create the resource object instance required to put the Oracle resource In Service.</p> <p><b>Action:</b> Check that correct arguments were passed to the "restore" command and also check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the "restore."</p>
122610	ERROR	Unable to "%s" on "%s" during resource create.	<p><b>Cause:</b> The Oracle Application Recovery Kit was unable to create the administrative lock using the "getlocks" command during resource creation.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create.</p>
122611	ERROR	%s	<p><b>Cause:</b> The requested dependency creation between the parent Oracle resource and the child File System resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create operation.</p>
122612	ERROR	%s	<p><b>Cause:</b> The requested dependency creation between the parent Oracle resource and the child Raw resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create operation.</p>

Code	Severity	Message	Cause/Action
122613	ERROR	%s	<p><b>Cause:</b> The requested dependency creation between the parent Oracle resource and the child Raw resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create operation.</p>
122614	ERROR	%s	<p><b>Cause:</b> The requested dependency creation between the parent Oracle resource and the child Listener resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create operation.</p>
122616	ERROR	%s	<p><b>Cause:</b> The requested start up or shutdown of the Oracle database failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the "restore" or "remove" operation.</p>
122618	ERROR	Dependency creation between Oracle database "%s (%s)" and the dependent resource "%s" on "%s" failed. Reason	<p><b>Cause:</b> LifeKeeper was unable to create a dependency between the database resource {tag} and the necessary child resource {childtag}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Once any problems have been corrected, it may be possible to create the dependency between {tag} and {childtag} manually.</p>



Code	Severity	Message	Cause/Action
122619	ERROR	Dependency creation between Oracle database "%s (%s)" and the dependent resource "%s" on "%s" failed. Reason	<p><b>Cause:</b> LifeKeeper was unable to create a dependency between the database resource {tag} and the necessary child resource {childtag}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Once any problems have been corrected, it may be possible to create the dependency between {tag} and {childtag} manually.</p>
122625	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The quickCheck process was unable to find the Oracle executable "sqlplus."</p> <p><b>Action:</b> Check the Oracle configuration and also check adjacent log messages for further details and related messages. Correct any reported problems.</p>
122626	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The remove process was unable to find the Oracle executable "sqlplus."</p> <p><b>Action:</b> Check the Oracle configuration and also check adjacent log messages for further details and related messages. Correct any reported problems.</p>
122627	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The restore process was unable to find the Oracle executable "sqlplus."</p> <p><b>Action:</b> Check the Oracle configuration and also check adjacent log messages for further details and related messages. Correct any reported problems.</p>
122628	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The recover process was unable to find the Oracle executable "sqlplus."</p> <p><b>Action:</b> Check the Oracle configuration and also check adjacent log messages for further details and related messages. Correct any reported problems.</p>

Code	Severity	Message	Cause/Action
122632	ERROR	Oracle SID mismatch. The instance SID "%s" does not match the SID "%s" specified for the command.	<p><b>Cause:</b> During a remove, the resource instance {sid} passed to the remove process does not match internal resource instance information for the {sid}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122633	ERROR	Oracle SID mismatch. The instance SID "%s" does not match the SID "%s" specified for the command.	<p><b>Cause:</b> During a restore, the resource instance {sid} passed to restore does not match internal resource instance information for the {sid}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122634	ERROR	Oracle SID mismatch. The instance SID "%s" does not match the SID "%s" specified for the command.	<p><b>Cause:</b> During resource recovery, the resource instance {sid} passed to recovery does not match internal resource instance information for the {sid}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122636	ERROR	END failed hierarchy "%s" of resource "%s" on server "%s" with return value of %d	<p><b>Cause:</b> The create of the Oracle resource hierarchy {tag} failed on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122638	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The create action for the Oracle database resource {tag} on server {server} failed. The signal {sig} was received by the create process.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
122640	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create the Oracle resource instance {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122641	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create the Oracle resource instance {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122642	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create the Oracle resource instance {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122643	ERROR	Cannot extend resource "%s" to server "%s"	<p><b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
122644	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to retrieve resource instance information for {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors and retry the extend.</p>
122645	ERROR	Cannot access canextend script "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to run pre-extend checks because it was unable to find the "canextend" script on {server} for a dependent child resource.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>

Code	Severity	Message	Cause/Action
122646	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to retrieve resource instance information for {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors and retry the extend.</p>
122647	ERROR	Cannot extend resource "%s" to server "%s"	<p><b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122648	ERROR	Resource with either matching tag "%s" or id "%s" already exists on server "%s" for App "%s" and Type "%s"	<p><b>Cause:</b> During the database resource extension, a resource instance was found using the same {tag} and/or {id} but with a different resource application and type.</p> <p><b>Action:</b> Resource IDs must be unique. The resource instance with the ID matching the Oracle resource instance must be removed.</p>
122649	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create the Oracle resource instance {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122650	ERROR	Cannot access extend script "%s" on server "%s"	<p><b>Cause:</b> The request to extend the database resource {resource} to {server} failed because it was unable to find the script {extend} on {server} for a dependent child resource.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>

Code	Severity	Message	Cause/Action
122651	ERROR	Cannot extend resource "%s" to server "%s"	<p><b>Cause:</b> The request to extend the database resource {resource} to {server} failed because of an error attempting to extend a dependent child resource.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
122654	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The health check for the database {sid} was terminated because the quickCheck process received a signal. This is most likely caused by the quickCheck process requiring more time to complete than was allotted.</p> <p><b>Action:</b> The health check time for an Oracle resource is controlled by the tunable value ORACLE_QUICKCHECK_TIMEOUT. Set it to a value greater than 45 seconds to allow more time for the health check process to complete.</p>
122655	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The request to take database {sid} "Out of Service" was terminated because the remove process received a signal. This is most likely caused by the remove process requiring more time to complete than was allotted.</p> <p><b>Action:</b> The remove time for an Oracle resource is controlled by the tunable value ORACLE_REMOVE_TIMEOUT. Set the tunable to a value greater than 240 seconds to allow more time for the remove process to complete.</p>

Code	Severity	Message	Cause/Action
122659	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The request to place database {sid} "In Service" was terminated because the restore process received a signal. This is most likely caused by the restore process requiring more time to complete than was allotted.</p> <p><b>Action:</b> The restore time for an Oracle resource is controlled by the tunable value ORACLE_RESTORE_TIMEOUT. Set the tunable to a value greater than 240 seconds to allow more time for the restore process to complete.</p>
122663	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The recovery of the failed database was terminated because the recovery process received a signal. This is most likely caused by the recovery process requiring more time to complete than was allotted.</p> <p><b>Action:</b> The recovery time for an Oracle resource is controlled by the tunable values ORACLE_RESTORE_TIMEOUT and ORACLE_REMOVE_TIMEOUT. Set one or both of these to a value greater than 240 seconds to allow more time for a recovery to complete.</p>
122670	ERROR	Update of "%s" sid "%s" on "%s" failed. Reason: "%s" "%s" failed: "%s".	<p><b>Cause:</b> An unexpected error occurred while attempting to update the oratab entry for the database {sid}. The error occurred while attempting to open the temporary file used in the update process.</p> <p><b>Action:</b> The oratab file entry for {sid} will need to be updated manually to turn off the automatic start up of the database at system boot.</p>

Code	Severity	Message	Cause/Action
122671	ERROR	Update of "%s" sid "%s" on "%s" failed. Reason: "%s" "%s" failed: "%s".	<p><b>Cause:</b> An unexpected error occurred while attempting to update the oratab entry for the database {sid}. The error occurred while attempting to close the temporary file used in the update process.</p> <p><b>Action:</b> The oratab file entry for {sid} will need to be updated manually to turn off the automatic start up of the database at system boot.</p>
122672	ERROR	Update of "%s" sid "%s" on "%s" failed. Reason: "%s" "%s" failed: "%s".	<p><b>Cause:</b> An unexpected error occurred while attempting to update the oratab entry for the database {sid}. The error occurred while attempting to rename the temporary file back to oratab.</p> <p><b>Action:</b> The oratab file entry for {sid} will need to be updated manually to turn off the automatic start up of the database at system boot.</p>
122673	ERROR	Unable to log messages queued while running as oracle user %s on %s. Reason: \$!	<p><b>Cause:</b> An unexpected error {reason} occurred while attempting to add messages to the log file. These messages were generated while running as the Oracle user.</p> <p><b>Action:</b> Review the reason for the failure and take corrective action.</p>
122674	ERROR	Unable to open %s Reason: %s.	<p><b>Cause:</b> An unexpected error occurred while attempting to open a connection to the Oracle database and run the database {cmd}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Additionally, check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct any reported problems.</p>

Code	Severity	Message	Cause/Action
123006	FATAL	Unknown version %s of IP address	<p><b>Cause:</b> The IP address does not appear to be valid for either IPv4 or IPv6.</p> <p><b>Action:</b> Provide a valid IP address.</p>
123008	ERROR	No pinglist found for %s.	<p><b>Cause:</b> Problem while opening the pinglist for this IP address.</p> <p><b>Action:</b> Make sure you have provided a pinglist for this IP address.</p>
123009	ERROR	List ping test failed for virtual IP %s	<p><b>Cause:</b> No response was received from any of the addresses in the ping list.</p> <p><b>Action:</b> Check network connectivity of this node and the systems on which the IPs in the ping list reside.</p>
123013	ERROR	Link check failed for virtual IP %s on interface %s.	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present on the physical layer connection.</p> <p><b>Action:</b> Check the physical connections for the interface and bring the physical layer link up.</p>
123015	ERROR	Link check failed for virtual IP %s on interface %s.	<p><b>Cause:</b> The requested interface is a bonded interface, and one of the slaves is showing 'NO-CARRIER' indicating that no link is present on the physical layer connection.</p> <p><b>Action:</b> Check the physical connections for the slave interface and bring the physical layer link up.</p>
123024	ERROR	IP address seems to still exist somewhere else.	<p><b>Cause:</b> The IP address appears to be in use elsewhere on the network.</p> <p><b>Action:</b> Either select a different IP address to use or locate and disable the current use of this IP address.</p>



Code	Severity	Message	Cause/Action
123027	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The quickCheck of a virtual IP ended due to a timeout.</p> <p><b>Action:</b> Correct the condition or provide a more appropriate value for IP_QUICKCHECK_TIMEOUT in /etc/default/LifeKeeper.</p>
123037	ERROR	must specify machine name containing primary hierarchy	<p><b>Cause:</b> Not enough arguments were provided to crelPhier.</p> <p><b>Action:</b> Supply all of the needed arguments to crelPhier.</p>
123038	ERROR	must specify IP resource name	<p><b>Cause:</b> Not enough arguments were passed to crelPhier.</p> <p><b>Action:</b> Supply all of the needed arguments to crelPhier.</p>
123039	ERROR	must specify primary IP Resource tag	<p><b>Cause:</b> The argument specifying the primary IP Resource tag was missing from the "crelPhier" command.</p> <p><b>Action:</b> Supply all of the needed arguments.</p>
123042	ERROR	An unknown error has occurred in utility validmask on machine %s.	<p><b>Cause:</b> There was an unexpected error running the "validmask" utility.</p> <p><b>Action:</b> Check adjacent log messages for additional details.</p>
123045	ERROR	An unknown error has occurred in utility getlocks.	<p><b>Cause:</b> There was an unexpected error running the "getlocks" utility.</p> <p><b>Action:</b> Check adjacent log messages for additional details.</p>
123053	ERROR	Cannot resolve hostname %s	<p><b>Cause:</b> A hostname was provided for the IP address, but the system was unable to resolve the name to an IP address.</p> <p><b>Action:</b> Check the correctness of the hostname and verify that name resolution (DNS or /etc/hosts) is working correctly and returns the IP for the hostname.</p>

Code	Severity	Message	Cause/Action
123055	ERROR	An unknown error has occurred in utility %s on machine %s.	<p><b>Cause:</b> There was a failure while creating the IP resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
123056	ERROR	create ip hierarchy failure: perform_action failed	<p><b>Cause:</b> Unexpected error trying to restore the IP address during creation.</p> <p><b>Action:</b> Check adjacent log messages for additional details.</p>
123059	ERROR	Resource already exists on machine %s	<p><b>Cause:</b> Attempted to create an IP address that already exists.</p> <p><b>Action:</b> Reuse the existing resource or manually remove the IP address if it exists or use a different IP address.</p>
123060	ERROR	ins_create failed on machine %s	<p><b>Cause:</b> An unexpected failure occurred while creating an IP resource.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
123064	ERROR	An unknown error has occurred in utility %s on machine %s.	<p><b>Cause:</b> There was a failure while creating a dependency for the IP resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
123066	ERROR	An error occurred during creation of LifeKeeper application=comm on %s.	<p><b>Cause:</b> A failure occurred while calling "app_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
123068	ERROR	An error occurred during creation of LifeKeeper resource type=ip on %s.	<p><b>Cause:</b> A failure occurred while calling "typ_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
123091	ERROR	the link for interface %s is down	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present on the physical layer connection.</p> <p><b>Action:</b> Check the physical connections for the interface and bring the physical layer link up.</p>
123093	ERROR	the ping list check failed	<p><b>Cause:</b> No response was received from any of the addresses in the ping list.</p> <p><b>Action:</b> Check network connectivity of this node and the systems on which the IPs in the ping list reside.</p>
123095	ERROR	broadcast ping failed	<p><b>Cause:</b> No replies were received from a broadcast ping.</p> <p><b>Action:</b> Verify that at least one host on the subnet will respond to broadcast pings. Verify that virtual IP is on the correct network interface. Consider using a pinglist instead of a broadcast ping.</p>
123096	ERROR	\$msg	<p><b>Cause:</b> The broadcast ping used to determine the viability of the virtual IP failed.</p> <p><b>Action:</b> Please ensure that the ping list for this resource is properly configured in the properties panel or that broadcast ping checking is disabled by adding NOBCASTPING=1 to the /etc/default/LifeKeeper configuration file.</p>
123097	ERROR	exec_list_ping(): broadcast ping failed.	<p><b>Cause:</b> The broadcast ping used to determine the viability of the virtual IP failed.</p> <p><b>Action:</b> Ensure that the ping list for this resource is properly configured in the properties panel or that broadcast ping checking is disabled by adding NOBCASTPING=1 to the /etc/default/LifeKeeper configuration file.</p>

Code	Severity	Message	Cause/Action
124004	FATAL	resource tag name not specified	<p><b>Cause:</b> Invalid arguments were specified for the "quickCheck" operation.</p> <p><b>Action:</b> Ensure that the correct arguments are passed.</p>
124005	FATAL	resource id not specified	<p><b>Cause:</b> Invalid arguments were specified for the "quickCheck" operation.</p> <p><b>Action:</b> Ensure that the correct arguments are passed.</p>
124007	FATAL	Failed to get resource information	<p><b>Cause:</b> The filesystem resource's info field does not contain the correct information.</p> <p><b>Action:</b> Put the correct information in the resource's info field or restore the system from a recent "lkbackup" to restore the original info field.</p>
124008	ERROR	getId failed	<p><b>Cause:</b> The filesystem resource could not find the underlying disk device.</p> <p><b>Action:</b> Check adjacent log messages for further details. Verify that the resource hierarchy is valid and that all required storage kits are installed.</p>
124009	ERROR	LifeKeeper protected filesystem is in service but quick-Check detects the following error	<p><b>Cause:</b> The filesystem kit has found something wrong with the resource.</p> <p><b>Action:</b> Check the messages immediately following this one for more details.</p>
124010	ERROR	"\$id" is not mounted	<p><b>Cause:</b> The filesystem resource is no longer mounted.</p> <p><b>Action:</b> No action is required. Allow local recovery to remount the resource.</p>

Code	Severity	Message	Cause/Action
124011	ERROR	\"\$id\" is mounted but with the incorrect mount options (current mount option list: \$mntopts, expected mount option list: \$infopts)	<p><b>Cause:</b> The filesystem resource is mounted incorrectly.</p> <p><b>Action:</b> No action is required. Allow local recovery to remount the resource.</p>
124012	ERROR	\"\$id\" is mounted but on the wrong device (current mount device: \$tmpdev, expected mount device: \$dev)	<p><b>Cause:</b> The filesystem resource has the wrong device mounted.</p> <p><b>Action:</b> No action is required. Allow local recovery to remount the resource.</p>
124015	ERROR	LifeKeeper protected filesystem \"\$tag\" (\$id) is \$percent% full (\$blocksfree free blocks).	<p><b>Cause:</b> The filesystem is getting full.</p> <p><b>Action:</b> Remove or migrate data from the filesystem.</p>
124016	WARN	LifeKeeper protected filesystem \"\$tag\" (\$id) is \$percent% full (\$blocksfree free blocks).	<p><b>Cause:</b> The filesystem is getting full.</p> <p><b>Action:</b> Remove or migrate data from the filesystem.</p>
124020	FATAL	cannot find device information for filesystem \$id	<p><b>Cause:</b> The filesystem resource could not find the underlying disk device.</p> <p><b>Action:</b> Check adjacent log messages for further details. Verify that the resource hierarchy is valid and that all required storage kits are installed.</p>
124029	ERROR	Failed to find child resource.	<p><b>Cause:</b> The filesystem resource could not determine its underlying disk resource.</p> <p><b>Action:</b> Ensure that the resource hierarchy is correct.</p>

Code	Severity	Message	Cause/Action
124032	FATAL	Script has hung. Exiting.	<p><b>Cause:</b> Processes had files open on a mounted filesystem that needed to be unmounted. Killing those processes has taken too long.</p> <p><b>Action:</b> If this error continues, try to temporarily stop all software that may be using the mount point to allow it to be unmounted. If the filesystem still cannot be unmounted, contact Support.</p>
124042	ERROR	file system \$fsname failed unmount; will try again	<p><b>Cause:</b> Processes had files open on a mounted filesystem that needed to be unmounted. It can take multiple attempts to clear those processes.</p> <p><b>Action:</b> No action is required. Allow the process to continue.</p>
124046	ERROR	file system \$fsname failed unmount	<p><b>Cause:</b> A filesystem could not be unmounted.</p> <p><b>Action:</b> If this error continues, try to temporarily stop all software that may be using the mount point to allow it to be unmounted. If the filesystem still cannot be unmounted, contact Support.</p>
124049	ERROR	Local recovery of resource has failed (err=\$err	<p><b>Cause:</b> A filesystem resource has a problem that cannot be repaired locally.</p> <p><b>Action:</b> No action is required. Allow the resource to be failed over to another system.</p>
124103	ERROR	\$ERRMSG Script was terminated for unknown reason	<p><b>Cause:</b> This message should not occur under normal circumstances.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>

Code	Severity	Message	Cause/Action
124104	ERROR	\$ERRMSG Required template machine name is null	<p><b>Cause:</b> Invalid arguments were specified for the canextend operation.</p> <p><b>Action:</b> Ensure that the arguments are correct. If this error happens during normal operation, please contact Support.</p>
124105	ERROR	\$ERRMSG Required template resource tag name is null	<p><b>Cause:</b> Invalid arguments were specified for the canextend operation.</p> <p><b>Action:</b> Ensure that the arguments are correct. If this error happens during normal operation, please contact Support.</p>
124106	ERROR	\$ERRMSG Unable to access template resource \"\$TemplateTagName\"	<p><b>Cause:</b> The resource's underlying disk information cannot be determined.</p> <p><b>Action:</b> Ensure the hierarchy is correct on the template system before extending.</p>
124107	ERROR	\$ERRMSG Resource \"\$TemplateTagName\" must have one and only one device resource dependency	<p><b>Cause:</b> The resource has too many underlying devices in the hierarchy.</p> <p><b>Action:</b> Ensure the hierarchy is correct on the template system before extending.</p>
124108	ERROR	\$ERRMSG Unable to access template resource \"\$TemplateTagName\"	<p><b>Cause:</b> The resource cannot be found on the template system.</p> <p><b>Action:</b> Ensure the hierarchy is correct on the template system before extending.</p>
124109	ERROR	\$ERRMSG Can not access canextend for scsi/\$DeviceResType resources on machine \"\$TargetSysName\"	<p><b>Cause:</b> The target system is missing some required components.</p> <p><b>Action:</b> Ensure that the target system has all the correct kits installed and licensed.</p>

Code	Severity	Message	Cause/Action
124110	ERROR	\$ERRMSG Either filesystem \"\$TemplateLKId\" is not mounted on \"\$TemplateSysName\" or filesystem is not shareable with \"\$TargetSysName\"	<p><b>Cause:</b> The filesystem isn't in service on the template system or doesn't meet the requirements for extending to the target system.</p> <p><b>Action:</b> Make sure the resource is in service on the template system and review the product documentation regarding the requirements for extending filesystems.</p>
124111	ERROR	\$ERRMSG File system type \"{FSType}\" is not supported by the kernel currently running on \"{TargetSysName}\"	<p><b>Cause:</b> The filesystem's type cannot be mounted on the target system due to lack of kernel support.</p> <p><b>Action:</b> Ensure that the target system has all its kernel modules configured correctly before extending the resource.</p>
124112	ERROR	must specify machine name containing primary hierarchy	<p><b>Cause:</b> Invalid arguments were specified for the creFShier operation.</p> <p><b>Action:</b> If this error happens during normal operation, please contact Support.</p>
124113	ERROR	must specify primary ROOT tag	<p><b>Cause:</b> Invalid arguments were specified for the creFShier operation.</p> <p><b>Action:</b> If this error happens during normal operation, please contact Support.</p>
124114	ERROR	must specify primary mount point	<p><b>Cause:</b> Invalid arguments were specified for the creFShier operation.</p> <p><b>Action:</b> If this error happens during normal operation, please contact Support.</p>
124115	ERROR	must specify primary switchback type	<p><b>Cause:</b> Invalid arguments were specified for the creFShier operation.</p> <p><b>Action:</b> If this error happens during normal operation, please contact Support.</p>



Code	Severity	Message	Cause/Action
124118	ERROR	dep_remove failure on machine \"'\$PRIMACH'\" for parent \"'\$PRITAG'\" and child \"'\$DEVTAG'\"	<b>Cause:</b> Cleanup after a dependency creation failed. <b>Action:</b> Check adjacent log messages for further details.
124119	ERROR	ins_remove failure on machine \"'\$PRIMACH'\" for \"'\$PRITAG'\"	<b>Cause:</b> Cleanup after an instance creation failed. <b>Action:</b> Check adjacent log messages for further details.
124121	ERROR	ins_remove failure on machine \"'\$PRIMACH'\"	<b>Cause:</b> Cleanup after a resource creation failed. <b>Action:</b> Check adjacent log messages for further details.
124122	ERROR	\$ERRMSG Script was terminated for unknown reason	<b>Cause:</b> This message should not occur under normal circumstances. <b>Action:</b> Check adjacent log messages for further details.
124123	ERROR	\$ERRMSG Required template machine name is null	<b>Cause:</b> Invalid arguments were specified for the depstoextend operation. <b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.
124124	ERROR	\$ERRMSG Required template resource tag name is null	<b>Cause:</b> Invalid arguments were specified for the depstoextend operation. <b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.
124125	ERROR	\$ERRMSG Unable to access template resource \"'\$TemplateTagName'\"	<b>Cause:</b> The resource was unable to locate its underlying disk resource. <b>Action:</b> Ensure the hierarchy and all dependencies are correct before extending.

Code	Severity	Message	Cause/Action
124126	ERROR	unextmgr failure on machine \"'\$PRIMACH\"	<p><b>Cause:</b> The cleanup, after a failed resource extend operation, failed.</p> <p><b>Action:</b> Manually clean up any remaining resources and check adjacent log messages for further details.</p>
124128	ERROR	unextmgr failure on machine \"'\$PRIMACH\" for \"'\$PRITAG.\	<p><b>Cause:</b> The cleanup, after a failed resource extend operation, failed.</p> <p><b>Action:</b> Manually clean up any remaining resources and check adjacent log messages for further details.</p>
124129	ERROR	\$ERRMSG Script was terminated for unknown reason	<p><b>Cause:</b> This message should not occur under normal circumstances.</p> <p><b>Action:</b> Look for additional log messages for more details.</p>
124130	ERROR	\$ERRMSG Required template machine name is null	<p><b>Cause:</b> Invalid arguments were specified for the extend operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124131	ERROR	\$ERRMSG Required template resource tag name is null	<p><b>Cause:</b> Invalid arguments were specified for the extend operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124132	ERROR	\$ERRMSG Required target mount point is null	<p><b>Cause:</b> Invalid arguments were specified for the extend operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>

Code	Severity	Message	Cause/Action
124133	ERROR	\$ERRMSG Unable to access template resource \"\\$TemplateTagName\"	<p><b>Cause:</b> The tag being extended doesn't exist on the template system.</p> <p><b>Action:</b> Ensure that the hierarchy is correct on the template system before extending.</p>
124134	ERROR	\$ERRMSG Detected conflict in expected tag name \"\\$TargetTagName\" on target machine.	<p><b>Cause:</b> A resource already exists on the target system with the same tag as the resource being extended.</p> <p><b>Action:</b> Recreate one of the conflicting resources with a different tag.</p>
124135	ERROR	\$ERRMSG Resource \"\\$TemplateTagName\" does not have required device resource dependency or unable to access this resource on template machine.	<p><b>Cause:</b> The resource or its underlying disk resource cannot be found on the template system.</p> <p><b>Action:</b> Ensure that the hierarchy is correct on the template system before extending.</p>
124136	ERROR	\$ERRMSG Resource \"\\$TemplateTagName\" must have one and only one device resource dependency	<p><b>Cause:</b> The resource has multiple underlying devices in the hierarchy on the template system.</p> <p><b>Action:</b> Ensure the hierarchy is correct before extending and that the filesystem resource only depends on a single disk resource.</p>
124137	ERROR	\$ERRMSG Can not access extend for scsi/\$DeviceResType resources on machine \"\\$TargetSysName\"	<p><b>Cause:</b> The files required to support the given storage type aren't available on the target system.</p> <p><b>Action:</b> Ensure that the required kits are installed on the target system and licensed.</p>
124138	ERROR	\$ERRMSG Unable to access target device resource \"\\$DeviceTagName\" on machine \"\\$TargetSysName\"	<p><b>Cause:</b> The required underlying disk resource doesn't exist on the target system.</p> <p><b>Action:</b> Check adjacent log messages for further details and ensure that the target system is properly configured for hosting the resources being extended.</p>

Code	Severity	Message	Cause/Action
124139	ERROR	\$ERRMSG Unable to access template \"/etc/mtab\" file	<p><b>Cause:</b> The target system cannot read the template system's /etc/mtab file.</p> <p><b>Action:</b> Check adjacent log messages for further details. Ensure that the /etc/mtab file exists on the template system.</p>
124140	ERROR	\$ERRMSG Unable to find mount point entry \"\$TemplateLKId\" in template \"/etc/mtab\" file. Is template resource in-service?	<p><b>Cause:</b> The resource doesn't appear to be mounted on the template system.</p> <p><b>Action:</b> Make sure the resource is in service before extending.</p>
124141	ERROR	\$ERRMSG Unable to find mount point \"\$TemplateLKId\" mode on template machine	<p><b>Cause:</b> The details of the mount point on the template system cannot be determined.</p> <p><b>Action:</b> Ensure that the resource is in service and accessible on the template system before extending.</p>
124142	ERROR	\$ERRMSG Unable to create or access mount point \"\$TargetLKId\" on target machine	<p><b>Cause:</b> The mount point could not be created on the target system.</p> <p><b>Action:</b> Ensure that the mount point's parent directory exists and is accessible on the target system.</p>
124143	ERROR	\$ERRMSG Two or more conflicting entries found in /etc/fstab on \"\$TargetSysName\"	<p><b>Cause:</b> The device or mount point appears to be mounted more than once on the target system.</p> <p><b>Action:</b> Ensure that the mount point is not mounted on the target system before extending.</p>
124144	ERROR	\$ERRMSG Failed to create resource instance on \"\$TargetSysName\"	<p><b>Cause:</b> The resource creation on the target system failed.</p> <p><b>Action:</b> Check adjacent log messages for further details. Make sure to check the logs on the target server.</p>

Code	Severity	Message	Cause/Action
124145	ERROR	\$ERRMSG Failed to set resource instance state for \"TargetTagName\" on \"TargetSysName\	<p><b>Cause:</b> The source state could not be changed to OSU on the target system.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124146	ERROR	must specify machine name containing primary hierarchy	<p><b>Cause:</b> Invalid arguments were specified for the filesyshier operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124147	ERROR	must specify primary mount point	<p><b>Cause:</b> Invalid arguments were specified for the filesyshier operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124149	ERROR	create file system hierarchy failure	<p><b>Cause:</b> The process of finding the resource instance failed.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124150	ERROR	create file system hierarchy failure	<p><b>Cause:</b> The system failed to read the /etc/mstab file.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124151	ERROR	create file system hierarchy failure	<p><b>Cause:</b> The mount point could not be found in the /etc/mstab file.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124152	ERROR	create file system hierarchy failure	<p><b>Cause:</b> The underlying disk resource could not be found.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124153	ERROR	create file system hierarchy failure	<p><b>Cause:</b> Creating the filesystem resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>

Code	Severity	Message	Cause/Action
124154	ERROR	create file system hierarchy failure	<b>Cause:</b> The info field for the resource could not be updated. <b>Action:</b> Check adjacent log messages for further details.
124155	ERROR	create file system hierarchy failure	<b>Cause:</b> The switchback strategy could not be set on the resource. <b>Action:</b> Check adjacent log messages for further details.
124157	ERROR	create file system hierarchy failure \(\conflicting entries in /etc/fstab\)	<b>Cause:</b> The mount point could not be removed from the /etc/fstab file. <b>Action:</b> Check adjacent log messages for further details.
124160	ERROR	Unknown error in script filesysins, err=\$err	<b>Cause:</b> This message should not occur under normal circumstances. <b>Action:</b> Check adjacent log messages for further details.
124161	ERROR	create filesys instance - existid - failure	<b>Cause:</b> This message should not occur under normal circumstances. <b>Action:</b> Check adjacent log messages for further details.
124163	ERROR	create filesys instance - ins_list - failure	<b>Cause:</b> Checking for an existing resource failed. <b>Action:</b> Check adjacent log messages for further details.
124164	ERROR	create filesys instance - newtag - failure	<b>Cause:</b> The system failed to generate a suggested tag for the resource. <b>Action:</b> If this error happens during normal operation, contact Support.
124168	ERROR	create filesys instance - ins_create - failure	<b>Cause:</b> The filesystem resource could not be created. <b>Action:</b> Check adjacent log messages for further details.

Code	Severity	Message	Cause/Action
124169	ERROR	filesys instance - ins_setstate - failure	<p><b>Cause:</b> The new filesystem resource's state could not be initialized.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124173	ERROR	create fileys instance - dep_create - failure	<p><b>Cause:</b> The resource's dependency relationship with its underlying disk could not be created.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124174	ERROR	machine not specified	<p><b>Cause:</b> Invalid arguments were specified for the mmenu_mp operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124175	ERROR	mount point not specified	<p><b>Cause:</b> Invalid arguments were specified for the mmenu_mp operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124177	ERROR	unexpected multiple matches found	<p><b>Cause:</b> One or more systems show a filesystem or mount point used more than once.</p> <p><b>Action:</b> Verify filesystem devices and mount points and ensure that filesystems are only mounted once. Look for additional log messages for more details.</p>
124178	ERROR	machine name not specified	<p><b>Cause:</b> Invalid arguments were specified for the mmenump operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>

Code	Severity	Message	Cause/Action
124180	ERROR	must specify filesystem type	<p><b>Cause:</b> Invalid arguments were specified for the validfstype operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124181	ERROR	mount point not specified	<p><b>Cause:</b> Invalid arguments were specified for the validmp operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124182	ERROR	The mount point \$MP is not an absolute path	<p><b>Cause:</b> A mount point was specified that isn't an absolute path (doesn't start with a '/').</p> <p><b>Action:</b> Specify a mount point as an absolute path starting with a '/'.</p>
124183	ERROR	\$MP is already mounted on \$MACH	<p><b>Cause:</b> The requested mount point is already in use on the system.</p> <p><b>Action:</b> Specify a mount point that isn't in use or unmount it before retrying the operation.</p>
124184	ERROR	The mount point \$MP is already protected by LifeKeeper on \$MACH	<p><b>Cause:</b> The system is already protecting the specified mount point.</p> <p><b>Action:</b> Choose a different mount point that isn't already being protected.</p>
124185	ERROR	The mount point \$MP is not a directory on \$MACH	<p><b>Cause:</b> The mount point refers to a non-directory such as a regular file.</p> <p><b>Action:</b> Choose a mount point that refers to a directory.</p>



Code	Severity	Message	Cause/Action
124186	ERROR	The mount point directory \$MP is not empty on \$MACH	<p><b>Cause:</b> The specified mount point refers to a directory that isn't empty.</p> <p><b>Action:</b> Choose a mount point that is empty or remove the contents of the specified directory before retrying the operation.</p>
124187	ERROR	server name not specified	<p><b>Cause:</b> Invalid arguments were specified for the valuepmp operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124188	ERROR	There are no mount points on server \$MACH	<p><b>Cause:</b> There are no possible mount points for filesystem resource on the server.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124194	WARN	Please correct conflicting \"/etc/fstab\" entries on server \$UNAME for: \$FSDEV, \$FSNAME	<p><b>Cause:</b> After deleting a filesystem resource, some entries in /etc/fstab need to be manually cleaned up.</p> <p><b>Action:</b> Manually clean up the /etc/fstab file.</p>
124195	ERROR	getchildinfo found no \$OKAPP child for \$PTAG	<p><b>Cause:</b> The system could not find a child resource in the hierarchy.</p> <p><b>Action:</b> Check adjacent log messages for further details and ensure that the hierarchy is correct before retrying the operation.</p>
124196	ERROR	enablequotas - quotacheck may have failed for \$FS_NAME	<p><b>Cause:</b> The quota operation failed.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and in /var/log/messages.</p>

Code	Severity	Message	Cause/Action
124198	ERROR	enablequotas - quotaon failed to turn on quotas for \$FS_NAME, reason	<p><b>Cause:</b> The quota operation failed.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and /var/log/messages.</p>
124200	ERROR	The device node \$dev was not found or did not appear in the udev create time limit of \$delay seconds	<p><b>Cause:</b> A device node (/dev/...) was not created by udev. This may indicate an issue with the storage or the server's connection to the storage.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and in /var/log/messages.</p>
124201	WARN	Device \$device not found. Will retry wait to see if it appears.	<p><b>Cause:</b> This can happen under normal conditions while udev creates device node entries for storage. This message should not happen repeatedly.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and in /var/log/messages.</p>
124202	ERROR	Command \"\$commandwithargs\" failed. Retrying ....	<p><b>Cause:</b> The given command failed but may have failed temporarily. This failure may happen during normal operations but should not keep failing.</p> <p><b>Action:</b> Check adjacent log messages for further details if this message continues.</p>
124204	WARN	cannot make file system \$FSNAME mount point	<p><b>Cause:</b> The mount point directory could not be created.</p> <p><b>Action:</b> Ensure that the mount point can be created. This may be due to filesystem permissions, mount options, etc.</p>
124207	ERROR	\"fsck\"ing file system \$FSNAME failed, trying alternative superblock	<p><b>Cause:</b> This message indicates that the typical filesystem check failed. This message may be ok for ext2 filesystems or other filesystems where an alternative superblock location is used.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>

Code	Severity	Message	Cause/Action
124209	ERROR	\\"fsck\\"ing file system \$FSNAME with alternative superblock failed	<p><b>Cause:</b> This indicates that an ext2 filesystem (or other filesystem where an alternative superblock location is used) check failed with the alternative superblock location.</p> <p><b>Action:</b> Check adjacent log messages for further details and instructions on how to proceed.</p>
124210	WARN	POSSIBLE FILESYSTEM CORRUPTION ON \$FSNAME (\$FPNAME)	<p><b>Cause:</b> A filesystem was put in service or failed over when it was out of sync with its mirror source.</p> <p><b>Action:</b> Check adjacent log messages for further details and review the product documentation for information on how to bring the filesystem in service safely.</p>
124211	ERROR	Reason for fsck failure (\$retval): \$ret	<p><b>Cause:</b> This log message is part of a series of messages and gives the actual exit code from the fsck process.</p> <p><b>Action:</b> Check adjacent log messages for further details and instructions on how to proceed.</p>
124212	ERROR	\\"fsck\\" of file system \$FSNAME failed	<p><b>Cause:</b> The check of the filesystem failed. This is usually due to the filesystem having corruption.</p> <p><b>Action:</b> Check adjacent log messages for further details. Review the product documentation for instructions on how to handle possible filesystem corruption.</p>
124213	WARN	POSSIBLE FILESYSTEM CORRUPTION ON \$FSNAME (\$FPNAME)	<p><b>Cause:</b> The system or user tried to bring into service a filesystem that may be corrupted. This can happen if a filesystem is switched or failed over when it was out of sync with its mirror source.</p> <p><b>Action:</b> Check adjacent log messages for further details and review the product documentation for instructions on how to bring the resource into service safely.</p>

Code	Severity	Message	Cause/Action
124214	ERROR	Reason for fsck failure (\$retval)	<p><b>Cause:</b> This message should follow a previous log message about a filesystem check failure and gives the process exit code of the fsck process.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124218	ERROR	File system \$FSNAME was found to be already	<p><b>Cause:</b> This message is part of a series of messages.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124219	ERROR	mounted after initial mount attempt failed.	<p><b>Cause:</b> This message is part of a series of messages. This should not happen under normal circumstances but may not be fatal if the resource can be put in service.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and in /var/log/messages.</p>
124220	ERROR	File system \$FSNAME failed to mount.	<p><b>Cause:</b> The filesystem could not be mounted.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124221	WARN	Protected Filesystem \$ID is full	<p><b>Cause:</b> The filesystem is full.</p> <p><b>Action:</b> Remove unused data from the filesystem or migrate to a larger filesystem.</p>
124222	WARN	Dependent Applications may be affected <>	<p><b>Cause:</b> This indicates that an operation on a resource is likely to cause operation on other resources based on the resource hierarchy.</p> <p><b>Action:</b> Make sure it's acceptable for the indicated resources to be affected before continuing.</p>
124223	ERROR	Put \"\$t\" Out-Of-Service Failed By Signal	<p><b>Cause:</b> This message should not occur under normal circumstances.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>

Code	Severity	Message	Cause/Action
124227	ERROR	Put \"\$i\" Out-Of-Service Failed	<b>Cause:</b> The operation failed. <b>Action:</b> Check adjacent log messages for further details.
124230	ERROR	Put \"\$t\" In-Service Failed By Signal	<b>Cause:</b> This message should not occur under normal circumstances. <b>Action:</b> Check adjacent log messages for further details.
124231	ERROR	Put \"\$t\" In-Service Failed	<b>Cause:</b> The operation failed. <b>Action:</b> Check adjacent log messages for further details.
124234	ERROR	Put \"\$t\" In-Service Failed	<b>Cause:</b> The operation failed. <b>Action:</b> Check adjacent log messages for further details.
125102	ERROR	`printf 'Template resource \"%s\" on server \"%s\" does not exist' \$TemplateTagName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125103	ERROR	`printf '%s is not shareable with any machine.' \$DEV`	<b>Cause:</b> The device does not appear to be shared with any other systems. <b>Action:</b> Verify that the device is accessible from all servers in the cluster. Ensure that all relevant storage drivers and software are installed and configured properly.
125104	ERROR	`printf 'Failed to create disk hierarchy for \"%s\" on \"%s\" \$PRIMACH \$DEV`	<b>Cause:</b> The creation of a resource to protect a physical disk failed. <b>Action:</b> Check adjacent log messages for more details and try to resolve the reported problem.
125107	ERROR	`printf 'Template resource \"%s\" on server \"%s\" does not exist' \$TemplateTagName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125114	ERROR	`printf 'Template resource \"%s\" on server \"%s\" does not exist' \$TemplateTagName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.

Code	Severity	Message	Cause/Action
125120	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$TemplateTagName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125123	ERROR	`printf 'Cannot access depstoextend script "%s" on server "%s"' \$depstoextend \$TargetSysName`	<b>Cause:</b> LifeKeeper was unable to run pre-extend checks on the resource hierarchy because it was unable to find the script "DEPSTOEXTEND" on {server}. <b>Action:</b> Check your LifeKeeper configuration.
125126	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$ChildTag \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125129	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$TemplateTagName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125155	ERROR	SCSI \$DEV failed to lock.	<b>Cause:</b> There was a problem locking a SCSI device. <b>Action:</b> Check adjacent log messages for more details and try to resolve the reported problem.
125164	ERROR	SCSI \$INFO failed to unlock.	<b>Cause:</b> There was a problem unlocking a SCSI device. <b>Action:</b> Check adjacent log messages for more details and try to resolve the reported problem.
125181	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$TemplateTag \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
126105	ERROR	script not specified - \$PTH is a directory	<b>Cause:</b> The specified script path is a directory. <b>Action:</b> Correct the path of the script.
126110	ERROR	script \$PTH does not exist	<b>Cause:</b> The specified script path does not exist. <b>Action:</b> Correct the path of the script.

Code	Severity	Message	Cause/Action
126115	ERROR	script \$PTH is a zero length file	<p><b>Cause:</b> The specified script is an empty file.</p> <p><b>Action:</b> Correct the script's file path and check the contents inside the script.</p>
126117	ERROR	script \$PTH is not executable	<p><b>Cause:</b> The specified script is not executable.</p> <p><b>Action:</b> Correct the script's file path, check the contents inside the script file and make sure it has the proper execute permissions.</p>
126125	ERROR	required template machine name is null	<p><b>Cause:</b> The input template machine name is null.</p> <p><b>Action:</b> Correct the input template machine name.</p>
126130	ERROR	required template resource tag name is null	<p><b>Cause:</b> The input template resource {tag} is null.</p> <p><b>Action:</b> Correct the input template resource tag name.</p>
126135	ERROR	Unable to generate a new tag	<p><b>Cause:</b> Failed to generate a new tag as the same as the template tag name on the target node using the "newtag" script during the extension. The tag name is already existing.</p> <p><b>Action:</b> Avoid using duplicate tag name on the same node and check the log for detail.</p>
126140	ERROR	Unable to generate a new tag	<p><b>Cause:</b> Failed to generate a new tag as input target tag name on the target node using the "newtag" script during the extension. The tag name is already existing.</p> <p><b>Action:</b> Avoid using duplicate tag name on the same node and check log for detail.</p>

Code	Severity	Message	Cause/Action
126150	ERROR	unable to remote copy template \"\$_lscript\" script file	<p><b>Cause:</b> Failed to remote copy template script file. The cause may be due to the non-existence/availability of template script file on template node or any transaction failure during "lcdrpc" process.</p> <p><b>Action:</b> Check the existence/availability of template script and the connection to template node. Also check the logs for related errors and try to resolve the reported problem.</p>
126155	ERROR	failed to create resource instance on \"\${TargetSysName}	<p><b>Cause:</b> Failed to create resource instance using "ins_create".</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126160	ERROR	failed to set resource instance state for \"\${TargetTagName}\" on \"\${TargetSysName}	<p><b>Cause:</b> Failed to set resource instance state using "ins_setstate" during GenApp resource extension.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126170	ERROR	getlocks failure	<p><b>Cause:</b> Failed to get the administrative lock when creating a resource hierarchy.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126175	ERROR	instance create failed	<p><b>Cause:</b> Failed to create a GenApp instance using "appins".</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126180	ERROR	unable to set state to OSU	<p><b>Cause:</b> Failed to set resource instance state using "ins_setstate" during GenApp resource creation.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>



Code	Severity	Message	Cause/Action
126190	ERROR	resource restore has failed	<p><b>Cause:</b> Failed to restore GenApp resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126200	ERROR	create application hierarchy rlslocks failure	<p><b>Cause:</b> Failed to release lock after GenApp resource created.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126210	ERROR	copy \$ltype script \$lscript failure	<p><b>Cause:</b> Failed to copy user provided script to appropriate GenApp directory during resource creation.</p> <p><b>Action:</b> Check the existence/availability of user provided script and the GenApp directory as well. Also check the logs for related errors and try to resolve the reported problem.</p>
126215	ERROR	no \$ltype script specified	<p><b>Cause:</b> Missing user defined script during GenApp resource creation.</p> <p><b>Action:</b> Check the input action script and run resource creation again.</p>
126220	ERROR	no machine name specified	<p><b>Cause:</b> Missing specified machine name during GenApp resource creation. Failed to copy specified user script due to missing the input for machine name.</p> <p><b>Action:</b> Check the input for machine name and run resource creation again.</p>
126225	ERROR	no resource tag specified	<p><b>Cause:</b> Missing specified tag name during resource creation.</p> <p><b>Action:</b> Check the input for source tag name and run resource creation again.</p>

Code	Severity	Message	Cause/Action
126230	ERROR	\$ERRMSG Script was terminated for unknown reason	<p><b>Cause:</b> Failed to extend GenApp resource due to unknown reason.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126235	ERROR	\$ERRMSG Required template machine name is null	<p><b>Cause:</b> Missing the input for template machine name during GenApp resource extension.</p> <p><b>Action:</b> Check the input for template machine name and do the resource extension again.</p>
126240	ERROR	\$ERRMSG Required template resource tag name is null	<p><b>Cause:</b> Missing the input for template resource tag name during GenApp resource extension.</p> <p><b>Action:</b> Check the input for template resource tag name and do the resource extension again.</p>
126245	ERROR	\$ERRMSG Can not access extend for \$AppType/\$ResType resources on machine \"\$TargetSysName\	<p><b>Cause:</b> Failed to locate "extend" script during GenApp resource extension on target node.</p> <p><b>Action:</b> Check the existence/availability of "extend" script and do GenApp resource extension again.</p>
126250	ERROR	create application failure - ins_list failed	<p><b>Cause:</b> Failed when calling "ins_list" during GenApp resource creation.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126255	ERROR	create application failure - unable to generate a new tag	<p><b>Cause:</b> Failed to generate a new tag during the GenApp resource creation.</p> <p><b>Action:</b> Avoid using duplicate tag name on the same node. Also check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
126270	ERROR	create application failure - ins_create failed	<p><b>Cause:</b> Failed using "ins_create" to create GenApp instance.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126275	ERROR	create application failure - copy_actions failed	<p><b>Cause:</b> Failed using "copy_actions" to copy user specified template script file.</p> <p><b>Action:</b> Check the existence/availability of template script. Also check the logs for related errors and try to resolve the reported problem.</p>
126290	ERROR	Unable to obtain tag for resource with id \$ID	<p><b>Cause:</b> Failed to fetch GenApp resource tag name by input ID during recovery.</p> <p><b>Action:</b> Check the correctness of input ID and existence/availability of GenApp resource in LCD. Also check the logs for related errors and try to resolve the reported problem.</p>
126300	ERROR	generic application recover script for \$TAG was not found or was not executable	<p><b>Cause:</b> Failed to locate the user defined script for GenApp resource during recovery.</p> <p><b>Action:</b> Check the existence/availability of the user defined script and do the GenApp recovery process again.</p>
126310	ERROR	-t flag not specified	<p><b>Cause:</b> Missing the input for resource tag name during GenApp resource restore.</p> <p><b>Action:</b> Check the input for resource tag name and do resource restore again.</p>
126315	ERROR	-i flag not specified	<p><b>Cause:</b> Missing the input for resource internal id during GenApp resource restore.</p> <p><b>Action:</b> Check the input for resource internal id and do resource restore again.</p>

Code	Severity	Message	Cause/Action
126335	ERROR	restore script \"\$LCDAS/\$APP_RESTOREDIR/\$TAG\" was not found or is not executable	<p><b>Cause:</b> Failed to locate the user defined script for GenApp resource during restore.</p> <p><b>Action:</b> Check the existence/availability of the user defined script and do the GenApp restore process again.</p>
126340	ERROR	-t flag not specified	<p><b>Cause:</b> Missing the input for resource tag name during GenApp resource remove.</p> <p><b>Action:</b> Check the input for resource tag name and do resource remove again.</p>
126345	ERROR	-i flag not specified	<p><b>Cause:</b> Missing the input for resource internal id during GenApp resource remove.</p> <p><b>Action:</b> Check the input for resource internal id and do resource remove again.</p>
126365	ERROR	remove script \"\$LCDAS/\$APP_REMOVEDIR/\$TAG\" was not found or was not executable	<p><b>Cause:</b> Failed to locate the user defined script for GenApp resource during remove.</p> <p><b>Action:</b> Check the existence/availability of the user defined script and do the GenApp remove process again.</p>
126375	ERROR	Script has hung checking \"\$tag\". Forcibly terminating.	<p><b>Cause:</b> The "quickCheck" Script will be forcibly terminated for GenApp resource with tag name {tag} due to a waiting time over the user defined timeout.</p> <p><b>Action:</b> Check the GenApp resource performance and restart quickChecking. Also check the logs for related errors and try to resolve the reported problem.</p>
126380	ERROR	Usage error: no tag specified	<p><b>Cause:</b> Missing the input for resource tag name during GenApp resource quickCheck.</p> <p><b>Action:</b> Check the input for resource tag name and retry resource quickCheck.</p>

Code	Severity	Message	Cause/Action
126385	ERROR	Internal error: ins_list failed on \$tag.	<p><b>Cause:</b> Failed using "ins_list" to fetch the GenApp resource information by input tag name during the quickCheck process.</p> <p><b>Action:</b> Correct the input tag name and do the quickCheck process again. Also check the logs for related errors and try to resolve the reported problem.</p>
126390	FATAL	Failed to fork process to execute \$userscript: \$!	<p><b>Cause:</b> Failed to fork process to execute user defined "quickCheck" script during the GenApp resource "quickCheck" process.</p> <p><b>Action:</b> Check the existency/availability of the user defined "quickCheck" script and do the "quickCheck" process again.</p>
126391	ERROR	quickCheck has failed for \"\$tag!\". Starting recovery.	<p><b>Cause:</b> The GenApp resource with tag name {tag} is determined to be failed by using the user defined health monitoring script - "quickCheck" and the recovery process will be initiated.</p> <p><b>Action:</b> Check the performance of the GenApp resource when local recovery finished. Also check the logs for related errors and try to resolve the reported problem.</p>
126400	ERROR	-t flag not specified	<p><b>Cause:</b> Missing the input for resource tag name during GenApp resource deletion process.</p> <p><b>Action:</b> Check the input for resource tag name and do resource deletion process again.</p>
126405	ERROR	-i flag not specified	<p><b>Cause:</b> Missing the input for resource internal id during GenApp resource deletion process.</p> <p><b>Action:</b> Check the input for resource internal id and do resource deletion process again.</p>

Code	Severity	Message	Cause/Action
128005	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The quickCheck of {resource} on {server} failed due to an operating system signal {signal}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128008	ERROR	Usage: quickCheck -t <tag name> -i <id>	<p><b>Cause:</b> Incorrect arguments have been supplied to the dmmp device quickCheck command preventing it from running.</p> <p><b>Action:</b> Make sure all software components are properly installed and at the correct version. Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource to be quickChecked.</p>
128010	ERROR	quickCheck for "%s" failed checks of underlying paths, initiate recovery. retry count=%s.	<p><b>Cause:</b> The dmmp kit failed to quickCheck a device after {count} times of retries. A recovery of the protected dmmp resource will be executed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128021	ERROR	unable to find device for uuid "%s".	<p><b>Cause:</b> The device could not be found by unique id during a restore operation.</p> <p><b>Action:</b> Verify that the resource is configured properly. Rerun the command and supply the correct device id that identifies the dmmp device resource to be restored.</p>

Code	Severity	Message	Cause/Action
128025	ERROR	Device "%s" failed to unlock.	<p><b>Cause:</b> A non working {device} was detected and could not be unlocked during the restore operation.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128026	ERROR	Device "%s" failed to lock.	<p><b>Cause:</b> The {device} could not be locked during the restore.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128031	ERROR	unable to find device for uuid "%s".	<p><b>Cause:</b> The device could not be found by unique id during the remove operation.</p> <p><b>Action:</b> Verify that the resource is configured properly. Rerun the command and supply the correct device id that identifies the dmmp device resource to be removed.</p>
128034	ERROR	Device "%s" failed to unlock.	<p><b>Cause:</b> The {device} could not be unlocked during the remove.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128036	ERROR	unable to load existing information for device with uuid "%s".	<p><b>Cause:</b> The device information could not be loaded by unique id.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct device id that identifies the dmmp device resource.</p>

Code	Severity	Message	Cause/Action
128037	ERROR	unable to load existing information for device "%s".	<p><b>Cause:</b> The device information could not be loaded by name.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct device name that identifies the dmmp device resource.</p>
128038	ERROR	unable to load existing information for device, no dev or uuid defined.	<p><b>Cause:</b> The device information could not be loaded since neither a unique device id nor name of the device were defined.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct device id or name that identifies the dmmp device resource.</p>
128041	ERROR	unable to load existing information for device with uuid "%s".	<p><b>Cause:</b> The device information could not be loaded by unique id.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct device id that identifies the dmmp device resource.</p>
128057	ERROR	All paths are failed on "%s".	<p><b>Cause:</b> LifeKeeper detected all paths listed to the protected dmmp device are in the failed state.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128058	ERROR	could not determine registrations for "%s"! All paths failed.	<p><b>Cause:</b> LifeKeeper could not determine registrations for protected dmmp {device}. All paths to the dmmp {device} are in the failed state.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>



Code	Severity	Message	Cause/Action
128059	WARN	path "%s" no longer configured for "%s", remove from path list.	<p><b>Cause:</b> LifeKeeper detected listed {path} to protected {device} is not valid anymore and will remove it from the path list.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128060	WARN	registration failed on path "%s" for "%s".	<p><b>Cause:</b> LifeKeeper failed the registration on {path} for protected dmmp {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128062	ERROR	all paths failed for "%s".	<p><b>Cause:</b> LifeKeeper failed to verify a valid path to protected dmmp {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128072	ERROR	The daemon "%s" does not appear to be running and could not be restarted. Path failures may not be correctly handled without this daemon.	<p><b>Cause:</b> LifeKeeper failed to verify dmmp daemon is running and could not restart it.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128078	ERROR	"%s" resource type is not installed on "%s".	<p><b>Cause:</b> The Device Mapper Multipath Recovery Kit for dmmp device support is not installed on the system.</p> <p><b>Action:</b> Install the steeleye-ikDMMP Device Mapper Multipath Recovery Kit rpm on the system.</p>

Code	Severity	Message	Cause/Action
128083	ERROR	This script must be executed on "%s".	<p><b>Cause:</b> An incorrect system name has been supplied as an argument to the devicehier script used to create the dmmp device resource.</p> <p><b>Action:</b> Make sure the cluster nodes and comm-paths are properly configured. Supply the correct system name to the devicehier script. The name must match the name of the system on which the command is run.</p>
128084	ERROR	The device %s is not active.	<p><b>Cause:</b> LifeKeeper failed to find the specified {device} as a valid device on the system during resource creation.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource to be created.</p>
128086	ERROR	Failed to create "%s" hierarchy.	<p><b>Cause:</b> LifeKeeper failed to create resource hierarchy for {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128088	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper failed to create the resource with {tagname} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
128090	ERROR	Failed to create dependency "%s"-"%s" on system "%s".	<p><b>Cause:</b> LifeKeeper failed to create dependency {resource tag name} - {resource tag name} on {system} during creation.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128091	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper failed to create {resource} on {system}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128101	ERROR	"%s" constructor requires a valid argument.	<p><b>Cause:</b> LifeKeeper failed to create an object for the dmmp resource during construction.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource.</p>
128102	ERROR	Invalid tag "%s".	<p><b>Cause:</b> A resource instance could not be found for the given tag name.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource.</p>
128111	ERROR	Failed to get registrations for "%s": %s. Verify the storage supports persistent reservations.	<p><b>Cause:</b> LifeKeeper failed to get the registrations of {device} with the message, "bad field in Persistent reservation in cdb".</p> <p><b>Action:</b> Verify if the storage supports persistent reservations. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
128112	ERROR	Failed to get registrations for "%s": %s. Verify the storage supports persistent reservations.	<p><b>Cause:</b> LifeKeeper failed to get the registrations of {device} with the message, "illegal request".</p> <p><b>Action:</b> Verify if the storage supports persistent reservations. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128136	ERROR	A previous quickCheck with PID "%s" running for device "%s" has been terminated.	<p><b>Cause:</b> LifeKeeper detected that a previous quickCheck operation is still running during the dmmp resource restore operation. It has been terminated by LifeKeeper.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128137	ERROR	SCSI reservation conflict on %s during LifeKeeper resource initialization. Manual intervention required.	<p><b>Cause:</b> LifeKeeper detected a SCSI reservation conflict on {device} during dmmp resource restore.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Manual intervention and fix of the reservation conflict on {device} is required.</p>
128138	ERROR	unable to clear registrations on %s.	<p><b>Cause:</b> LifeKeeper failed to clear all the registrations on {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128140	WARN	registration failed on path %s for %s.	<p><b>Cause:</b> LifeKeeper failed to make the registration on {path} for {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
128143	ERROR	reserve failed (%d) on %s.	<p><b>Cause:</b> LifeKeeper failed to make reservation for {resource} on {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128145	ERROR	The server ID "%s" returned by "%s" is not valid.	<p><b>Cause:</b> LifeKeeper failed to generate a valid host {ID}.</p> <p><b>Action:</b> The ID used to register a device is made up of 1 to 12 Hex digits that uniquely identifies the server in the cluster. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128146	ERROR	device failure on %s. SYSTEM HALTED.	<p><b>Cause:</b> LifeKeeper detected failure on {device} and will reboot the server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128148	ERROR	device failure on %s. SYSTEM HALTED DISABLED.	<p><b>Cause:</b> LifeKeeper detected a failure on {device}. The reboot was skipped due to LifeKeeper configuration.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Turn on the configuration "SCSIHALT" to make the reboot available for any detected device failure.</p>
128149	ERROR	device failure or SCSI Error on %s. SENDEVENT DISABLED.	<p><b>Cause:</b> LifeKeeper detected a failure on {device}. The event generation was skipped due to LifeKeeper configuration.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Turn on the configuration "SCSIEVENT" to make the sendevent available for any detected device failure.</p>

Code	Severity	Message	Cause/Action
128150	ERROR	%s does not have EXCLUSIVE access to %s, halt system.	<p><b>Cause:</b> LifeKeeper detected a reservation conflict for {device} on {server} and will reboot the server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128151	ERROR	%s does not have EXCLUSIVE access to %s, halt system DISABLED.	<p><b>Cause:</b> LifeKeeper detected a reservation conflict for {device} on {server}. The reboot was skipped due to LifeKeeper configuration.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Turn on the configuration "RESERVATIONCONFLICT" to make the reboot available for any detected reservation conflicts.</p>
128154	WARN	unable to flush buffers on %s.	<p><b>Cause:</b> LifeKeeper failed to flush the buffers for {device} during dmmp resource remove.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128157	WARN	%s utility not found, limited healthcheck for %s.	<p><b>Cause:</b> LifeKeeper failed to find "dd" utility for the health check of {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128160	ERROR	%s failed to read %s.	<p><b>Cause:</b> LifeKeeper failed a disk I/O test for {device} when using {utility}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
128163	ERROR	Registration ID "%s" for "%s" is not valid.	<p><b>Cause:</b> LifeKeeper failed to generate a valid registration {ID} for {device}.</p> <p><b>Action:</b> The ID used to register a device is made up of 4 Hex digits derived from the path to the device. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128170	ERROR	Usage: canextend <Template system name> <Template tag name>	
128500	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the dmmp device restore command preventing it from running.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource to be restored.</p>
128504	ERROR	"%s" resource type is not installed on "%s".	<p><b>Cause:</b> The Device Mapper Multipath Recovery Kit for dmmp device support is not installed on the system.</p> <p><b>Action:</b> Install the steeleye-ikDMMP Device Mapper Multipath Recovery Kit rpm on the system.</p>
128506	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the dmmp device devShared command preventing it from running.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: &lt;Template Resource System Name&gt; and &lt;Template Resource Tag&gt; that identifies the dmmp device resource to be created.</p>

Code	Severity	Message	Cause/Action
128507	FATAL	This script must be executed on "%s".	<p><b>Cause:</b> An incorrect system name has been supplied as an argument to the devicehier script used to create the dmmp device resource.</p> <p><b>Action:</b> Supply the correct system name to the devicehier script. The name must match the name of the system on which the command is run.</p>
128511	ERROR	Failed to get the ID for the device "%s". Hierarchy create failed.	<p><b>Cause:</b> The devicehier script used to create the dmmp device resource was unable to determine the SCSI ID for the supplied device.</p> <p><b>Action:</b> Check that the supplied device path exists and that is for a supported SCSI storage array.</p>
128512	ERROR	Failed to get the disk ID for the device "%s". Hierarchy create failed.	<p><b>Cause:</b> The devicehier script used to create the dmmp disk resource was unable to determine the SCSI ID for the supplied disk.</p> <p><b>Action:</b> Check that the supplied device path exists and that is for a supported SCSI storage array.</p>
128513	ERROR	Failed to create the underlying resource for device "%s". Hierarchy create failed.	<p><b>Cause:</b> The creation of the underlying dmmp disk resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128515	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> The creation of the dmmp device resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>



Code	Severity	Message	Cause/Action
128517	ERROR	Failed to create dependency "%s"-"%s" on system "%s".	<p><b>Cause:</b> The parent child dependency creation between the dmmp device and dmmp disk resources failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128519	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> The attempt to bring the newly created dmmp device resource in service has failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128521	ERROR	Either TEMPLATESYS or TEMPLATETAG argument missing	<p><b>Cause:</b> Incorrect arguments have been supplied to the extend command for the dmmp device resource.</p> <p><b>Action:</b> Rerun the dmmp device resource extend and supply the correct template system and tag names.</p>
128540	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the dmmp device getId command used to retrieve the SCSI ID.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -i &lt;device path&gt; or -b &lt;device ID&gt;.</p>
128541	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the command used to delete the dmmp device resource.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -t &lt;dmmp device resource tag&gt;.</p>
128543	ERROR	device node \"\$dev\" does not exist.	<p><b>Cause:</b> The device node required for restoring the dmmp device resource does not exist. The allocated wait time in restore for udev device creation has been exceed.</p> <p><b>Action:</b> Rerun the dmmp device resource restore once udev has created the device.</p>

Code	Severity	Message	Cause/Action
128544	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the remove command used to take the dmmp device resource out of service.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -t &lt;dmmp device resource tag&gt;.</p>
129100	FATAL	Failed to load instance from LifeKeeper.	<p><b>Cause:</b> An invalid resource tag or ID was specified.</p> <p><b>Action:</b> Check that the tag or ID is valid and re-run the command.</p>
129103	FATAL	No resource matches tag \"\$self->{tag}\".	<p><b>Cause:</b> An invalid resource tag was specified.</p> <p><b>Action:</b> Check the tag and re-run the command.</p>
129104	FATAL	An error occurred setting LifeKeeper resource information	<b>Cause:</b> An internal error has occurred in LifeKeeper.
129108	ERROR	Missing parameter \"\$param\" in ec2 resource object	<b>Cause:</b> This is an internal error.
129110	ERROR	Could not get the Elastic Network Interface ID for \$dev	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129111	ERROR	Failed to get Allocation ID of Elastic IP \"\$elasticip\".	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129112	ERROR	Cannot find curl executable. Please verify that the steeleye-curl package is installed.	<b>Cause:</b> Install the steeleye-curl package, if it is not installed.
129113	ERROR	Failed to get my instance ID.	<p><b>Cause:</b> The EC2 instance metadata access failed.</p> <p><b>Action:</b> Check the Amazon console and retry the operation.</p>

Code	Severity	Message	Cause/Action
129114	ERROR	Failed to get ENI ID.	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129115	ERROR	Failed to associate Elastic IP, retrying \$i/\$MAX_RETRY	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129116	ERROR	Failed to associate Elastic IP \"\$self->{'EIP'}\" on \"\$self->{'DEV'}\".	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129117	ERROR	Failed to disassociate Elastic IP, retrying \$i/\$MAX_RETRY	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129118	WARN	\$self->{'EIP'} is not associated with any instance.	<p><b>Cause:</b> The Elastic IP is not associated with any instance.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by calling the EC2 API to associate the Elastic IP. Check adjacent log messages for more details.</p>
129119	WARN	\$self->{'EIP'} is associated with another instance.	<p><b>Cause:</b> The Elastic IP is associated with another instance.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by calling the EC2 API to associate the Elastic IP. Check adjacent log messages for more details.</p>

Code	Severity	Message	Cause/Action
129120	ERROR	Failed to recover Elastic IP.	<p><b>Cause:</b> The EC2 API call failed to associate the Elastic IP.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129121	ERROR	Recovery process ended but Elastic IP is not associated with this instance. Please check AWS console.	<p><b>Cause:</b> The EC2 API call failed to associate the Elastic IP.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129122	ERROR	Error creating resource \"\$target_tag\" with return code of \"\$err\".	<p><b>Cause:</b> LifeKeeper was unable to create the resource instance on the server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129123	ERROR	Failed to get ENI ID.	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129124	WARN	\$self->{'EIP'} is associated with another network interface.	<p><b>Cause:</b> The Elastic IP is associated with the proper instance, but the wrong ENI.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by calling the EC2 API to associate the Elastic IP. Check adjacent log messages for more details.</p>
129125	ERROR	Link check failed for interface \"\$dev\".	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present.</p> <p><b>Action:</b> Check the network interface and bring the link up.</p>
129126	ERROR	Link check failed for interface \"\$dev\". Reason: down slave.	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present.</p> <p><b>Action:</b> Check the network interface and bring the link up.</p>

Code	Severity	Message	Cause/Action
129129	WARN	The link for network interface '\\$self->{'DEV'}' is down. Attempting to bring the link up.	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by bringing the link up and associating the Elastic IP with the interface. Check adjacent log messages for more details.</p>
129137	ERROR	The link for network interface '\\$self->{'DEV'}' is still down.	<p><b>Cause:</b> LifeKeeper could not bring the link up.</p> <p><b>Action:</b> Ensure the interface is enabled and up. Check adjacent log messages for more details.</p>
129139	WARN	The link for network interface '\\$self->{'DEV'}' is down.	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present.</p> <p><b>Action:</b> Check the network interface and bring the link up.</p>
129140	ERROR	Could not get ENI ID for \$self->{IP}.	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129141	ERROR	Could not update route table, retrying \$i/\$MAX_RETRY (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129142	ERROR	Failed to update route table	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>

Code	Severity	Message	Cause/Action
129143	ERROR	You must have exactly one IP address resource as the parent of the RouteTable EC2 resource. Please reconfigure your resource hierarchy.	<p><b>Cause:</b> The Route Table EC2 resource must have one and only one IP resource as a parent.</p> <p><b>Action:</b> Repair the resource hierarchy as necessary.</p>
129144	ERROR	\$func called with invalid timeout: \$timeout	<p><b>Cause:</b> An invalid timeout value was specified in the /etc/default/LifeKeeper file.</p> <p><b>Action:</b> Verify all EC2_*_TIMEOUT settings are valid in /etc/default/LifeKeeper.</p>
129145	ERROR	\$func action timed out after \$timeout seconds	<p><b>Cause:</b> The action did not complete within the timeout period.</p> <p><b>Action:</b> Consider increasing the EC2_*_TIMEOUT value for the given action (in /etc/default/LifeKeeper).</p>
129146	ERROR	failed to run \$func with timeout: \$@	<p><b>Cause:</b> This is an internal error.</p>
129148	ERROR	Amazon ec2-describe-route-tables call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129150	ERROR	Elastic IP \"\$elasticIp\" is associated with another instance.	<p><b>Cause:</b> The Elastic IP is not associated with the proper instance.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by calling the EC2 API to associate the Elastic IP. Check adjacent log messages for more details.</p>
129151	ERROR	Could not get the Association ID for Elastic IP \"\$elasticIp\".	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>

Code	Severity	Message	Cause/Action
129152	ERROR	Failed to disassociate Elastic IP \"\$self->{'EIP'}\" on \"\$self->{'DEV'}\".	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129153	ERROR	Failed to disassociate Elastic IP \"\$elasticIp\", (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129154	ERROR	Amazon ec2-describe-addresses call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129155	ERROR	Amazon ec2-describe-addresses call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129156	ERROR	curl call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 instance metadata access failed.</p> <p><b>Action:</b> Check the Amazon console and retry the operation.</p>
129157	ERROR	curl call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 instance metadata access failed.</p> <p><b>Action:</b> Check the Amazon console and retry the operation.</p>
129158	ERROR	curl call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 instance metadata access failed.</p> <p><b>Action:</b> Check the Amazon console and retry the operation.</p>

Code	Severity	Message	Cause/Action
129159	ERROR	Amazon ec2-associate-address call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129160	ERROR	Amazon ec2-describe-addresses call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129161	ERROR	Error deleting resource \"\$otherTag\" on \"\$otherSys\" with return code of \"\$err\".	<p><b>Cause:</b> LifeKeeper was unable to delete the resource instance on the server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129403	ERROR	END failed create of \$TAG due to a \$sig signal	<p><b>Cause:</b> The create process was interrupted by a signal.</p>
129409	ERROR	The IP resource \$IP_RES is not \"\$ISP\".	<p><b>Cause:</b> The IP resource is not in service.</p> <p><b>Action:</b> Bring the resource in service and retry the operation.</p>
129410	ERROR	Could not find IP resource \$IP_RES	<p><b>Cause:</b> Ensure that the IP resource exists and retry the operation.</p>
129412	ERROR	EC2 resource \$ID is already protected	<p><b>Cause:</b> A resource with the specified ID already exists.</p> <p><b>Action:</b> Make sure to clean up any remnants of an old resource before re-creating a new resource.</p>
129413	ERROR	Failed to encrypt AWS_SECRET_KEY	<p><b>Cause:</b> Ensure that the AWS_ACCESS_KEY and AWS_SECRET_KEY have been entered correctly.</p>



Code	Severity	Message	Cause/Action
129416	ERROR	Error creating resource \" <code>\$TAG</code> \" with return code of \" <code>\$!-cderror</code> \".	<p><b>Cause:</b> LifeKeeper was unable to create the resource instance.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129418	ERROR	Dependency creation between \" <code>\$IP_RES</code> \" and \" <code>\$TAG</code> \" failed with return code of \" <code>\$!cderror</code> \".	<p><b>Cause:</b> LifeKeeper was unable to create the resource dependency.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129420	ERROR	In-service failed for tag \" <code>\$TAG</code> \".	<p><b>Cause:</b> LifeKeeper could not bring the resource instance into service.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129800	ERROR	canextend checks failed for \" <code>\$self-&gt;{tag}</code> \" (err= <code>\$ret</code> )	<p><b>Cause:</b> The pre-extend checks failed for the target server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>

## DataKeeper Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
104002	FATAL	\$msg	<p><b>Cause:</b> This message indicates an internal software error.</p> <p><b>Action:</b> The stack trace indicates the source of the error.</p>
104003	FATAL	\$self->Val('Tag') . " is not an SDR resource"	<p><b>Cause:</b> A data replication action was attempted on a non data replication resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
104010	ERROR	\$self->{'md'}: bitmap merge failed, \$action	<p><b>Cause:</b> The bitmap merge operation has failed.</p> <p><b>Action:</b> The target server may have the mirror and/or protected filesystem mounted, or the bitmap file may be missing on the target. Check the target server.</p>
104022	ERROR	\$argv[1]: mdadm failed (\$ret	<p><b>Cause:</b> The "mdadm" command has failed to add a device into the mirror.</p> <p><b>Action:</b> This is usually a temporary condition.</p>
104023	ERROR	\$_	<p><b>Cause:</b> The message contains the output of the "mdadm" command.</p>
104025	ERROR	failed to spawn monitor	<p><b>Cause:</b> The system failed to start the 'mdadm -F' monitor process. This should not happen under normal circumstances.</p> <p><b>Action:</b> Reboot the system to ensure that any potential conflicts are resolved.</p>

Code	Severity	Message	Cause/Action
104026	ERROR	cannot create \$md	<p><b>Cause:</b> The mirror device could not be created.</p> <p><b>Action:</b> Ensure the device is not already in use and that all other parameters for the mirror creation are correct.</p>
104027	ERROR	\$_	<p><b>Cause:</b> This message contains the "mdadm" command output.</p>
104035	ERROR	Too many failures. Aborting resync of \$md	<p><b>Cause:</b> The device was busy for an abnormally long period of time.</p> <p><b>Action:</b> Reboot the system to be sure that the device is no longer busy.</p>
104036	ERROR	Failed to start nbd-server on \$target (error \$port	<p><b>Cause:</b> The nbd-server process could not be started on the target server.</p> <p><b>Action:</b> Ensure that the target disk device is available and that its Device ID has not changed.</p>
104037	ERROR	Failed to start compression (error \$port	<p><b>Cause:</b> The system was unable to start the 'balance' tunnel process or there was a network problem.</p> <p><b>Action:</b> Ensure that the network is operating properly and that TCP ports in the range 10000-10512 are opened and unused. Ensure that the software is installed properly on all systems.</p>
104038	ERROR	Failed to start nbd-client on \$source (error \$ret	<p><b>Cause:</b> The nbd-client process has failed to start on the source server.</p> <p><b>Action:</b> Look up the reported errno value and try to resolve the problem reported. For example, an errno value of 110 means "Connection timed out", which may indicate a network or firewall problem.</p>

Code	Severity	Message	Cause/Action
104039	ERROR	Failed to add \$nbd to \$md on \$source	<p><b>Cause:</b> This is usually a temporary condition.</p> <p><b>Action:</b> If this error persists, reboot the system to resolve any potential conflicts.</p>
104045	ERROR	failed to stop \$self->{'md'}	<p><b>Cause:</b> The mirror device could not be stopped.</p> <p><b>Action:</b> Ensure that the device is not busy or mounted. Try running "mdadm --stop" manually to stop the device.</p>
104048	WARN	failed to kill \$proc, pid \$pid	<p><b>Cause:</b> The process could not be signalled. This may indicate that the process has already died.</p> <p><b>Action:</b> Ensure that the process in question is no longer running. If it is, then reboot the system to clear up the unkillable process.</p>
104050	ERROR	Setting \$name on \$dest failed: \$ret. Please try again.	<p><b>Cause:</b> The system failed to set a 'mirrorinfo' file setting.</p> <p><b>Action:</b> Check the network and systems and retry the mirror setting operation.</p>
104052	FATAL	Specified existing mount point "%s" is not mounted	<p><b>Cause:</b> The mount point became unmounted.</p> <p><b>Action:</b> Ensure that the mount point is mounted and retry the operation.</p>
104055	ERROR	Failed to set up temporary \$type access to data for \$self->{'tag'}. Error: \$ret	<p><b>Cause:</b> The filesystem or device was not available on the target server. The mirrored data will not be available on the target server until the mirror is paused and resumed again.</p> <p><b>Action:</b> Reboot the target server to resolve any potential conflicts.</p>

Code	Severity	Message	Cause/Action
104057	ERROR	Failed to undo temporary access for \$self->{'tag'} on \$self->{'sys'}. Error: \$ret. Please verify that \$fsid is not mounted on server \$self->{'sys'}.	<p><b>Cause:</b> The filesystem could not be unmounted on the target server.</p> <p><b>Action:</b> Ensure that the filesystem and device are not busy on the target server. Reboot the target server to resolve any potential conflicts.</p>
104062	FATAL	Cannot find a device with unique ID "%s"	<p><b>Cause:</b> The target disk could not be identified.</p> <p><b>Action:</b> Ensure that the appropriate storage recovery kits are installed on the target server. Ensure that the Device ID of the target disk has not changed.</p>
104066	FATAL	Cannot get the hardware ID of device "%s"	<p><b>Cause:</b> A unique ID could not be found for the target disk device.</p> <p><b>Action:</b> Ensure that the appropriate storage recovery kits are installed on the target server. Ensure that the Device ID of the target disk has not changed.</p>
104067	FATAL	Asynchronous writes cannot be enabled without a bitmap file	<p><b>Cause:</b> An attempt was made to create a mirror with invalid parameters.</p> <p><b>Action:</b> A bitmap file parameter must be specified or synchronous writes must be specified.</p>
104068	FATAL	Failed to extend dependent resource %s to system %s. Error %s	<p><b>Cause:</b> The hierarchy extend operation failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
104070	FATAL	Unable to extend the mirror "%s" to system "%s"	<p><b>Cause:</b> The hierarchy extend operation failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
104071	ERROR	Failed to restore target device resources on \$target->{sys'}: \$err	<p><b>Cause:</b> The in-service operation has failed on the target server.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
104073	EMERG	WARNING: A temporary communication failure has occurred between systems %s and %s. In order to avoid data corruption, data resynchronization will not occur. MANUAL INTERVENTION IS REQUIRED. In order to initiate data resynchronization, you should: 1) Take one of the following resources out of service (this resource will become the mirror target): %s on %s or %s on %s. 2) Take the other resource out of service (this resource will become the mirror source). 3) Run %s/bitmap -d %s on the system that will become mirror source. 4) Bring the mirror in service on the source system. A full resync will occur.	<p><b>Cause:</b> A temporary communication failure (split-brain scenario) has occurred between the source and target servers.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
104074	FATAL	Cannot get the hardware ID of device "%s"	<p><b>Cause:</b> There is no storage recovery kit that recognizes the underlying disk device that you are attempting to use for the mirror.</p> <p><b>Action:</b> Make sure the appropriate storage recovery kits are installed. If necessary, place your device name in the /opt/LifeKeeper/subsys/scsi/resources/DEVNAME/device_ pattern file.</p>
104081	FATAL	Cannot make the %s filesystem on "%s" (%d)	<p><b>Cause:</b> The "mkfs" command failed.</p> <p><b>Action:</b> Ensure that the disk device is writable and free of errors and that the filesystem tools for the selected filesystem are installed.</p>

Code	Severity	Message	Cause/Action
104082	FATAL	%s	<b>Cause:</b> This message contains the output of the "mkfs" command.
104083	FATAL	Cannot create filesystem hierarchy "%s"	<b>Cause:</b> The resource creation failed. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
104086	ERROR	The "%s_data_corrupt" flag is set in "%s/sub-sys/scsi/resources/netraid/" on system "%s". To avoid data corruption, LifeKeeper will not restore the resource	<b>Cause:</b> The data corrupt flag file has been set as a precaution to prevent accidental data corruption. The mirror cannot be restored on this server until the file is removed. <b>Action:</b> If you are sure that the data is valid on the server in question, you can either: 1) remove the file and restore the mirror, or 2) force the mirror online using the LifeKeeper GUI or 'mirror_action force' command.
104092	ERROR	Mirror target resource movement to system %s : status %s	<b>Cause:</b> The hierarchy switchover operation has failed. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
104099	ERROR	Unable to unextend the mirror for resource "%s" from system "%s"	<b>Cause:</b> The hierarchy unextend operation failed. <b>Action:</b> Reboot the target server to resolve any potential conflicts and retry the operation.
104106	ERROR	remote 'bitmap -m' command failed on \$target->{'sys'}: \$ranges	<b>Cause:</b> The bitmap merge command failed on the target server. This may be caused by one of two things: 1) The bitmap file may be missing or corrupted, or 2) the mirror (md) device may be active on the target. <b>Action:</b> Make sure that the mirror and protected filesystem are not active on the target. If the target's bitmap file is missing, pause and resume the mirror to recreate the bitmap file.

Code	Severity	Message	Cause/Action
104107	ERROR	Asynchronous writes cannot be enabled without a bitmap file	<b>Cause:</b> Invalid parameters were specified for the mirror create operation.
104108	ERROR	Local Partition not available	<b>Cause:</b> Invalid parameters were specified for the mirror create operation.
104109	ERROR	Cannot get the hardware ID of device "%s"	<b>Cause:</b> A unique ID could not be determined for the disk device. <b>Action:</b> Ensure that the appropriate storage recovery kits are installed on the server. Ensure that the Device ID of the disk has not changed.
104111	FATAL	Insufficient input parameters for "%s" creation	<b>Cause:</b> Invalid parameters were specified for the mirror create operation.
104112	FATAL	Insufficient input parameters for "%s" creation	<b>Cause:</b> Invalid parameters were specified for the mirror create operation.
104113	FATAL	Insufficient input parameters for "%s" creation	<b>Cause:</b> Invalid parameters were specified for the mirror create operation.
104114	FATAL	Insufficient input parameters for "%s" creation	<b>Cause:</b> Invalid parameters were specified for the mirror create operation.
104115	FATAL	Insufficient input parameters for "%s" creation	<b>Cause:</b> Invalid parameters were specified for the mirror create operation.
104117	FATAL	Insufficient input parameters for "%s" creation	<b>Cause:</b> Invalid parameters were specified for the mirror create operation.
104118	FATAL	Cannot unmount existing Mount Point "%s"	<b>Cause:</b> The mount point is busy. <b>Action:</b> Make sure the filesystem is not busy. Stop any processes or applications that may be accessing the filesystem.



Code	Severity	Message	Cause/Action
104119	FATAL	Invalid data replication resource type requested ("%s"	<b>Cause:</b> An invalid parameter was specified for the mirror create operation.
104124	EMERG	WARNING: A temporary communication failure has occurred between systems %s and %s. In order to avoid data corruption, data resynchronization will not occur. MANUAL INTERVENTION IS REQUIRED. In order to initiate data resynchronization, you should take one of the following resources out of service: %s on %s or %s on %s. The resource that is taken out of service will become the mirror target.	<b>Cause:</b> A temporary communication failure (split-brain scenario) has occurred between the source and target servers. <b>Action:</b> Perform the steps listed in the message text.
104125	ERROR	failed to start '\$cmd \$_[2] \$user_args' on '\$_[3]'	<b>Cause:</b> The specified command failed. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
104126	ERROR	\$_	<b>Cause:</b> This message contains the output of the command that was reported as failing in message 104125.
104129	WARN		<b>Cause:</b> The replication connection for the mirror is down. <b>Action:</b> Check the network.
104130	ERROR	Mirror resize failed on %s (%s). You must successfully complete this operation before using the mirror. Please try again.	<b>Cause:</b> The mirror resize operation has failed to update the mirror metadata on the listed system. <b>Action:</b> You must successfully complete the resize before using the mirror. Re-run mirror_resize (possibly using -f to force the operation if necessary).
104136	ERROR	Extend failed.	<b>Cause:</b> The hierarchy extend operation failed. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.

Code	Severity	Message	Cause/Action
104143	ERROR	Mirror resume was unsuccessful (\$ret	<p><b>Cause:</b> The mirror could not be established.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problems.</p>
104144	ERROR	Unable to stop the mirror access for \$self->{'md'} on system \$self->{'sys'}. Error: \$ret. Use the "\mdadm --stop \$self->{'md'}\" command to manually stop the mirror.	<p><b>Cause:</b> The mirror device created on the target node when the mirror was paused could not be stopped.</p> <p><b>Action:</b> Ensure that the device is not busy or mounted. Try running "mdadm --stop" manually to stop the device.</p>
104156	WARN	Resynchronization of "%s" is in PENDING state. Current sync_action is: "%s"	<p><b>Cause:</b> The resynchronization of the md device is detected in PENDING state.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by forcing a resynchronization. Check the logs for related errors. When successful assure that the PENDING state has been cleared in /proc/mdstat and the resynchronization is in progress or has been completed for the datarep resource.</p>
104157	WARN	/etc/sysconfig/raid-check update failed. Please %s "\m-d%d\" to SKIP_DEVS.	

## DB2 Kit Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
103001	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The db2nodes.cfg does not contain any server names.</p> <p><b>Action:</b> Ensure the db2nodes.cfg is valid.</p>

Code	Severity	Message	Cause/Action
103002	ERROR	LifeKeeper was unable to get the version for the requested instance "%s"	<b>Cause:</b> "db2level" command did not return DB2 version. <b>Action:</b> Check your DB2 configuration.
103003	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<b>Cause:</b> The DB2 Application Recovery Kit was unable to find any nodes for the DB2 instance. <b>Action:</b> Check your DB2 configuration.
103004	ERROR	Unable to get the information for resource "%s"	<b>Cause:</b> Failed to get resource information. <b>Action:</b> Check your LifeKeeper configuration.
103005	ERROR	Unable to get the information for resource "%s"	<b>Cause:</b> Failed to get resource information. <b>Action:</b> Check your LifeKeeper configuration.
103006	ERROR	Unable to get the instance information for resource "%s"	<b>Cause:</b> Failed to get the instance information. <b>Action:</b> Check your LifeKeeper configuration.
103007	ERROR	Unable to get the instance home directory information for resource "%s"	<b>Cause:</b> Failed to get the instance home directory path. <b>Action:</b> Check your LifeKeeper configuration.
103008	ERROR	Unable to get the instance type information for resource "%s"	<b>Cause:</b> The DB2 Application Recovery Kit found invalid instance type. <b>Action:</b> Check your LifeKeeper configuration.
103009	ERROR	LifeKeeper has encountered an error while trying to get the database configuration parameters for database \"\$DB\"	<b>Cause:</b> There was an unexpected error running "db2 get db cfg for \$DB" command. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.

Code	Severity	Message	Cause/Action
103012	ERROR	LifeKeeper was unable to start the database server for instance "%s"	<p><b>Cause:</b> The requested startup of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "restore" operation.</p>
103013	ERROR	LifeKeeper was unable to start the database server for instance "%s"	<p><b>Cause:</b> The requested startup of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "restore" operation.</p>
103015	ERROR	An entry for the home directory "%s" of instance "%s" does not exist in "/etc/fstab"	<p><b>Cause:</b> The home directory of instance of Multiple Partition database should exist in "/etc/fstab".</p> <p><b>Action:</b> Ensure the home directory exists in "/etc/fstab".</p>
103016	ERROR	LifeKeeper was unable to mount the home directory for the DB2 instance "%s"	<p><b>Cause:</b> Failed to mount the home directory of instance of Multiple Partition database.</p> <p><b>Action:</b> Ensure the home directory is mounted and retry the operation.</p>
103017	ERROR	Unable to get the instance nodes information for resource "%s"	<p><b>Cause:</b> Failed to get the instance nodes.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
103018	ERROR	LifeKeeper was unable to start database partition server "%s" for instance "%s"	<p><b>Cause:</b> The requested startup of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "restore" operation.</p>

Code	Severity	Message	Cause/Action
103020	ERROR	LifeKeeper was unable to stop the database server for instance "%s"	<p><b>Cause:</b> The requested shutdown of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "remove" operation.</p>
103021	ERROR	LifeKeeper was unable to stop the database server for instance "%s"	<p><b>Cause:</b> The requested shutdown of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "remove" operation.</p>
103023	ERROR	Unable to get the instance nodes information for resource "%s"	<p><b>Cause:</b> Failed to get the instance nodes.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
103024	ERROR	LifeKeeper was unable to stop database partition server "%s" for instance "%s"	<p><b>Cause:</b> The requested shutdown of the DB2 instance failed.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "remove" operation.</p>
103026	ERROR	Unable to get the instance nodes information for resource "%s"	<p><b>Cause:</b> Failed to get the instance nodes.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
103027	FATAL	The argument for the DB2 instance is empty	<p><b>Cause:</b> Invalid parameters were specified for the create operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>

Code	Severity	Message	Cause/Action
103028	FATAL	Unable to determine the DB2 instance home directory	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance home directory.</p> <p><b>Action:</b> Ensure the instance owner name is same as the instance name and retry the operation.</p>
103029	FATAL	Unable to determine the DB2 instance type	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance type.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103030	FATAL	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find any nodes for the DB2 instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103031	ERROR	The path "%s" is not on a shared filesystem	<p><b>Cause:</b> The instance home directory should be on a shared filesystem.</p> <p><b>Action:</b> Ensure the path is on shared filesystem and retry the create operation.</p>
103032	ERROR	LifeKeeper was unable to get the DB tablespace containers for instance "%s" or the log path for one of its databases	<p><b>Cause:</b> LifeKeeper could not determine the location of the database table space containers or verify that they are located in a path which is on a mounted filesystem.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem. Correct any reported errors before retrying the "create" operation.</p>
103033	ERROR	The path "%s" is not on a shared filesystem	<p><b>Cause:</b> The path of database table space container should be on a shared filesystem.</p> <p><b>Action:</b> Ensure database table space container is on a shared filesystem and retry the operation.</p>

Code	Severity	Message	Cause/Action
103034	ERROR	A DB2 Hierarchy already exists for instance "%s"	<p><b>Cause:</b> An attempt was made to protect the DB2 instance that is already under LifeKeeper protection.</p> <p><b>Action:</b> You must select a different DB2 instance for LifeKeeper protection.</p>
103035	ERROR	The file system resource "%s" is not in-service	<p><b>Cause:</b> The file system which the DB2 resource depends on should be in service.</p> <p><b>Action:</b> Ensure the file system resource is in service and retry the "create" operation.</p>
103036	ERROR	Unable to create the hierarchy for raw device "%s"	<p><b>Cause:</b> LifeKeeper was unable to create the resource {raw device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the "create" operation.</p>
103037	ERROR	A RAW hierarchy does not exist for the tag "%s"	<p><b>Cause:</b> LifeKeeper was unable to find the raw resource {tag}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
103038	ERROR	LifeKeeper was unable to create a dependency between the DB2 hierarchy "%s" and the Raw hierarchy "%s"	<p><b>Cause:</b> The requested dependency creation between the parent DB2 resource and the child Raw resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the "create" operation.</p>
103039	ERROR	LifeKeeper could not disable the automatic startup feature of DB2 instance "%s"	<p><b>Cause:</b> An unexpected error occurred while attempting to update the DB2 setting.</p> <p><b>Action:</b> The DB2AUTOSTART will need to be updated manually to turn off the automatic startup of the instance at system boot.</p>

Code	Severity	Message	Cause/Action
103040	ERROR	DB2 version "%s" is not installed on server "%s"	<p><b>Cause:</b> LifeKeeper could not find DB2 installed location.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103041	ERROR	The instance owner "%s" does not exist on target server "%s"	<p><b>Cause:</b> An attempt to retrieve the DB2 instance owner from template server during a "canextend" or "extend" operation failed.</p> <p><b>Action:</b> Verify the DB2 instance owner exists on the specified server. If the user does not exist, it should be created with the same uid and gid on all servers in the cluster.</p>
103042	ERROR	The instance owner "%s" uids are different on target server "%s" and template server "%s"	<p><b>Cause:</b> The user id on the target server {target server} for the DB2 instance owner {user} does not match the value of the user {user} on the template server {template server}.</p> <p><b>Action:</b> The user ids for the DB2 instance owner {user} must match on all servers in the cluster. The user id mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103043	ERROR	The instance owner "%s" gids are different on target server "%s" and template server "%s"	<p><b>Cause:</b> The group id on the target server {target server} for the DB2 instance owner {user} does not match the value of the user {user} on the template server {template server}.</p> <p><b>Action:</b> The group ids for the DB2 instance owner {user} must match on all servers in the cluster. The group id mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>



Code	Severity	Message	Cause/Action
103044	ERROR	The instance owner "%s" home directories are different on target server "%s" and template server "%s"	<p><b>Cause:</b> The home directory location of the user {user} on the target server {target server} does not match the DB2 instance owner's home directory on the template server {template server}.</p> <p><b>Action:</b> The home directory location of the DB2 instance owner {user} must match on all servers in the cluster. The location mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103045	ERROR	LifeKeeper was unable to get the DB2 "SVCENAME" parameter for the DB2 instance	<p><b>Cause:</b> There was an unexpected error running "db2 get dbm cfg" command.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103046	ERROR	Unable to get the value of the DB2 "SVCENAME" parameter for the DB2 instance %s.	<p><b>Cause:</b> The DB2 "SVCENAME" parameter is set to null.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103047	ERROR	LifeKeeper was unable to get the contents of the "/etc/services" file on the server "%s"	<p><b>Cause:</b> "/etc/services" on the template server does not contain the service names for the DB2 instance.</p> <p><b>Action:</b> The service names in "/etc/services" for the DB2 instance must match on all servers in the cluster. The service names mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103048	ERROR	LifeKeeper was unable to get the contents of the "/etc/services" file on the server "%s"	<p><b>Cause:</b> "/etc/services" on the target server does not contain the service names for the DB2 instance.</p> <p><b>Action:</b> The service names in "/etc/services" for the DB2 instance must match on all servers in the cluster. The service names mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>

Code	Severity	Message	Cause/Action
103049	ERROR	The "/etc/services" entries for the instance "%s" are different on target server "%s" and template server "%s"	<p><b>Cause:</b> The "/etc/services" entries for the instance are mismatched.</p> <p><b>Action:</b> The service names in "/etc/services" for the DB2 instance must match on all servers in the cluster. The service names mismatch should be corrected manually on all servers before retrying the "canextend" operation.</p>
103050	ERROR	The home directory "%s" for instance "%s" is not mounted on server "%s"	<p><b>Cause:</b> LifeKeeper could not find db2nodes.cfg for Multiple Partition instance.</p> <p><b>Action:</b> Ensure the home directory is mounted and retry the operation.</p>
103051	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> Failed to get resource information from the template server.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
103052	ERROR	LifeKeeper was unable to add instance "%s" and/or its variables to the DB2 registry	<p><b>Cause:</b> There was an unexpected error running "db2iset" command.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
103054	ERROR	Unable to determine the DB2 instance type	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance type.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103055	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find any nodes for the DB2 instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>

Code	Severity	Message	Cause/Action
103060	ERROR	Unable to determine the DB2 instance home directory	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance home directory.</p> <p><b>Action:</b> Ensure the instance owner name is same as the instance name and retry the operation.</p>
103061	ERROR	Unable to determine the DB2 instance type	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance type.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103062	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find the node for the DB2 instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103063	ERROR	Unable to determine the DB2 install path	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find DB2 for the instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103065	ERROR	Invalid input provided for "%s" utility operation, characters are not allowed.	<p><b>Cause:</b> Invalid parameters were specified for the "nodes" command.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
103066	ERROR	Unable to get the information for resource "%s"	<p><b>Cause:</b> LifeKeeper was unable to find the resource {tag}.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
103067	ERROR	The DB2 instance "%s" is not a EEE or Multiple Partition instance	<p><b>Cause:</b> The resource {tag} is single partition instance.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
103069	ERROR	Node "%s" is already protected by this hierarchy	<p><b>Cause:</b> Invalid parameters were specified for the "nodes" command.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>

Code	Severity	Message	Cause/Action
103070	ERROR	Node number "%s" is the last remaining node protected by resource "%s". Deleting all nodes is not allowed.	<p><b>Cause:</b> Invalid parameters were specified for the "nodes" command.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
103071	ERROR	LifeKeeper is unable to get the equivalent instance for resource "%s"	<p><b>Cause:</b> There was an unexpected error running "nodes" command.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
103072	ERROR	Unable to set NodesInfo for resource "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "nodes" command.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
103073	ERROR	Unable to set NodesInfo for resource "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "nodes" command.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
103076	ERROR	Unable to determine the DB2 instance type	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance type.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103077	ERROR	Unable to determine the DB2 instance home directory	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance home directory.</p> <p><b>Action:</b> Ensure the instance owner name is same as the instance name and retry the operation.</p>
103078	ERROR	The database server is not running for instance "%s"	<p><b>Cause:</b> A process check for the DB2 instance did not find any processes running.</p> <p><b>Action:</b> The DB2 instance must be started.</p>

Code	Severity	Message	Cause/Action
103079	ERROR	LifeKeeper has detected an error while trying to determine the node number(s) of the DB partition server(s) for the instance	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to find any nodes for the DB2 instance.</p> <p><b>Action:</b> Check your DB2 configuration.</p>
103080	ERROR	One or more of the database partition servers for instance "%s" is down	<p><b>Cause:</b> All database partition servers should be running.</p> <p><b>Action:</b> Ensure all database partition servers are running and retry the operation.</p>
103082	ERROR	Failed to create flag "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create a flag for controlling DB2 local recovery processing.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
103083	ERROR	Failed to remove flag "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to remove a flag for controlling DB2 local recovery processing.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
103084	ERROR	Unable to determine the DB2 instance \"%Instance\" home directory	<p><b>Cause:</b> The DB2 Application Recovery Kit was unable to determine the DB2 instance home directory.</p> <p><b>Action:</b> Ensure the instance owner name is same as the instance name and retry the operation.</p>

## DMMP Kit Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
128005	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The quickCheck of {resource} on {server} failed due to an operating system signal {signal}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128008	ERROR	Usage: quickCheck -t <tag name> -i <id>	<p><b>Cause:</b> Incorrect arguments have been supplied to the dmmp device quickCheck command preventing it from running.</p> <p><b>Action:</b> Make sure all software components are properly installed and at the correct version. Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource to be quickChecked.</p>
128010	ERROR	quickCheck for "%s" failed checks of underlying paths, initiate recovery. retry count=%s.	<p><b>Cause:</b> The dmmp kit failed to quickCheck a device after {count} times of retries. A recovery of the protected dmmp resource will be executed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128021	ERROR	unable to find device for uuid "%s".	<p><b>Cause:</b> The device could not be found by unique id during a restore operation.</p> <p><b>Action:</b> Verify that the resource is configured properly. Rerun the command and supply the correct device id that identifies the dmmp device resource to be restored.</p>

Code	Severity	Message	Cause/Action
128025	ERROR	Device "%s" failed to unlock.	<p><b>Cause:</b> A non working {device} was detected and could not be unlocked during the restore operation.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128026	ERROR	Device "%s" failed to lock.	<p><b>Cause:</b> The {device} could not be locked during the restore.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128031	ERROR	unable to find device for uuid "%s".	<p><b>Cause:</b> The device could not be found by unique id during the remove operation.</p> <p><b>Action:</b> Verify that the resource is configured properly. Rerun the command and supply the correct device id that identifies the dmmp device resource to be removed.</p>
128034	ERROR	Device "%s" failed to unlock.	<p><b>Cause:</b> The {device} could not be unlocked during the remove.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128036	ERROR	unable to load existing information for device with uuid "%s".	<p><b>Cause:</b> The device information could not be loaded by unique id.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct device id that identifies the dmmp device resource.</p>

Code	Severity	Message	Cause/Action
128037	ERROR	unable to load existing information for device "%s".	<p><b>Cause:</b> The device information could not be loaded by name.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct device name that identifies the dmmp device resource.</p>
128038	ERROR	unable to load existing information for device, no dev or uuid defined.	<p><b>Cause:</b> The device information could not be loaded since neither a unique device id nor name of the device were defined.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct device id or name that identifies the dmmp device resource.</p>
128041	ERROR	unable to load existing information for device with uuid "%s".	<p><b>Cause:</b> The device information could not be loaded by unique id.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct device id that identifies the dmmp device resource.</p>
128057	ERROR	All paths are failed on "%s".	<p><b>Cause:</b> LifeKeeper detected all paths listed to the protected dmmp device are in the failed state.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128058	ERROR	could not determine registrations for "%s"! All paths failed.	<p><b>Cause:</b> LifeKeeper could not determine registrations for protected dmmp {device}. All paths to the dmmp {device} are in the failed state.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>



Code	Severity	Message	Cause/Action
128059	WARN	path "%s" no longer configured for "%s", remove from path list.	<p><b>Cause:</b> LifeKeeper detected listed {path} to protected {device} is not valid anymore and will remove it from the path list.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128060	WARN	registration failed on path "%s" for "%s".	<p><b>Cause:</b> LifeKeeper failed the registration on {path} for protected dmmp {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128062	ERROR	all paths failed for "%s".	<p><b>Cause:</b> LifeKeeper failed to verify a valid path to protected dmmp {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128072	ERROR	The daemon "%s" does not appear to be running and could not be restarted. Path failures may not be correctly handled without this daemon.	<p><b>Cause:</b> LifeKeeper failed to verify dmmp daemon is running and could not restart it.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128078	ERROR	"%s" resource type is not installed on "%s".	<p><b>Cause:</b> The Device Mapper Multipath Recovery Kit for dmmp device support is not installed on the system.</p> <p><b>Action:</b> Install the steeleye-1kDMMP Device Mapper Multipath Recovery Kit rpm on the system.</p>

Code	Severity	Message	Cause/Action
128083	ERROR	This script must be executed on "%s".	<p><b>Cause:</b> An incorrect system name has been supplied as an argument to the devicehier script used to create the dmmp device resource.</p> <p><b>Action:</b> Make sure the cluster nodes and comm-paths are properly configured. Supply the correct system name to the devicehier script. The name must match the name of the system on which the command is run.</p>
128084	ERROR	The device %s is not active.	<p><b>Cause:</b> LifeKeeper failed to find the specified {device} as a valid device on the system during resource creation.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource to be created.</p>
128086	ERROR	Failed to create "%s" hierarchy.	<p><b>Cause:</b> LifeKeeper failed to create resource hierarchy for {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128088	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper failed to create the resource with {tagname} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
128090	ERROR	Failed to create dependency "%s"-"%s" on system "%s".	<p><b>Cause:</b> LifeKeeper failed to create dependency {resource tag name} - {resource tag name} on {system} during creation.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128091	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper failed to create {resource} on {system}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128101	ERROR	"%s" constructor requires a valid argument.	<p><b>Cause:</b> LifeKeeper failed to create an object for the dmmp resource during construction.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource.</p>
128102	ERROR	Invalid tag "%s".	<p><b>Cause:</b> A resource instance could not be found for the given tag name.</p> <p><b>Action:</b> Make sure the resource is configured properly. Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource.</p>

Code	Severity	Message	Cause/Action
128111	ERROR	Failed to get registrations for "%s": %s. Verify the storage supports persistent reservations.	<p><b>Cause:</b> LifeKeeper failed to get the registrations of {device} with the message, "bad field in Persistent reservation in cdb".</p> <p><b>Action:</b> Verify if the storage supports persistent reservations. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128112	ERROR	Failed to get registrations for "%s": %s. Verify the storage supports persistent reservations.	<p><b>Cause:</b> LifeKeeper failed to get the registrations of {device} with the message, "illegal request".</p> <p><b>Action:</b> Verify if the storage supports persistent reservations. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128136	ERROR	A previous quickCheck with PID "%s" running for device "%s" has been terminated.	<p><b>Cause:</b> LifeKeeper detected that a previous quickCheck operation is still running during the dmmp resource restore operation. It has been terminated by LifeKeeper.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128137	ERROR	SCSI reservation conflict on %s during LifeKeeper resource initialization. Manual intervention required.	<p><b>Cause:</b> LifeKeeper detected a SCSI reservation conflict on {device} during dmmp resource restore.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Manual intervention and fix of the reservation conflict on {device} is required.</p>

Code	Severity	Message	Cause/Action
128138	ERROR	unable to clear registrations on %s.	<p><b>Cause:</b> LifeKeeper failed to clear all the registrations on {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128140	WARN	registration failed on path %s for %s.	<p><b>Cause:</b> LifeKeeper failed to make the registration on {path} for {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128143	ERROR	reserve failed (%d) on %s.	<p><b>Cause:</b> LifeKeeper failed to make reservation for {resource} on {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128145	ERROR	The server ID "%s" returned by "%s" is not valid.	<p><b>Cause:</b> LifeKeeper failed to generate a valid host {ID}.</p> <p><b>Action:</b> The ID used to register a device is made up of 1 to 12 Hex digits that uniquely identifies the server in the cluster. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128146	ERROR	device failure on %s. SYSTEM HALTED.	<p><b>Cause:</b> LifeKeeper detected failure on {device} and will reboot the server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>

Code	Severity	Message	Cause/Action
128148	ERROR	device failure on %s. SYSTEM HALTED DISABLED.	<p><b>Cause:</b> LifeKeeper detected a failure on {device}. The reboot was skipped due to LifeKeeper configuration.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Turn on the configuration "SCSIHALT" to make the reboot available for any detected device failure.</p>
128149	ERROR	device failure or SCSI Error on %s. SENDEVENT DISABLED.	<p><b>Cause:</b> LifeKeeper detected a failure on {device}. The event generation was skipped due to LifeKeeper configuration.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Turn on the configuration "SCSIEVENT" to make the sendevent available for any detected device failure.</p>
128150	ERROR	%s does not have EXCLUSIVE access to %s, halt system.	<p><b>Cause:</b> LifeKeeper detected a reservation conflict for {device} on {server} and will reboot the server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
128151	ERROR	%s does not have EXCLUSIVE access to %s, halt system DISABLED.	<p><b>Cause:</b> LifeKeeper detected a reservation conflict for {device} on {server}. The reboot was skipped due to LifeKeeper configuration.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Turn on the configuration "RESERVATIONCONFLICT" to make the reboot available for any detected reservation conflicts.</p>

Code	Severity	Message	Cause/Action
128154	WARN	unable to flush buffers on %s.	<p><b>Cause:</b> LifeKeeper failed to flush the buffers for {device} during dmmp resource remove.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128157	WARN	%s utility not found, limited healthcheck for %s.	<p><b>Cause:</b> LifeKeeper failed to find "dd" utility for the health check of {device}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128160	ERROR	%s failed to read %s.	<p><b>Cause:</b> LifeKeeper failed a disk I/O test for {device} when using {utility}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128163	ERROR	Registration ID "%s" for "%s" is not valid.	<p><b>Cause:</b> LifeKeeper failed to generate a valid registration {ID} for {device}.</p> <p><b>Action:</b> The ID used to register a device is made up of 4 Hex digits derived from the path to the device. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128170	ERROR	Usage: canextend <Template system name> <Template tag name>	

Code	Severity	Message	Cause/Action
128500	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the dmmp device restore command preventing it from running.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -t &lt;Resource Tag&gt; and -i &lt;Resource ID&gt; that identifies the dmmp device resource to be restored.</p>
128504	ERROR	"%s" resource type is not installed on "%s".	<p><b>Cause:</b> The Device Mapper Multipath Recovery Kit for dmmp device support is not installed on the system.</p> <p><b>Action:</b> Install the steeleye-1kDMMP Device Mapper Multipath Recovery Kit rpm on the system.</p>
128506	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the dmmp device devShared command preventing it from running.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: &lt;Template Resource System Name&gt; and &lt;Template Resource Tag&gt; that identifies the dmmp device resource to be created.</p>
128507	FATAL	This script must be executed on "%s".	<p><b>Cause:</b> An incorrect system name has been supplied as an argument to the devicehier script used to create the dmmp device resource.</p> <p><b>Action:</b> Supply the correct system name to the devicehier script. The name must match the name of the system on which the command is run.</p>
128511	ERROR	Failed to get the ID for the device "%s". Hierarchy create failed.	<p><b>Cause:</b> The devicehier script used to create the dmmp device resource was unable to determine the SCSI ID for the supplied device.</p> <p><b>Action:</b> Check that the supplied device path exists and that is for a supported SCSI storage array.</p>



Code	Severity	Message	Cause/Action
128512	ERROR	Failed to get the disk ID for the device "%s". Hierarchy create failed.	<p><b>Cause:</b> The devicehier script used to create the dmmp disk resource was unable to determine the SCSI ID for the supplied disk.</p> <p><b>Action:</b> Check that the supplied device path exists and that is for a supported SCSI storage array.</p>
128513	ERROR	Failed to create the underlying resource for device "%s". Hierarchy create failed.	<p><b>Cause:</b> The creation of the underlying dmmp disk resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128515	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> The creation of the dmmp device resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128517	ERROR	Failed to create dependency "%s"-"%s" on system "%s".	<p><b>Cause:</b> The parent child dependency creation between the dmmp device and dmmp disk resources failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
128519	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> The attempt to bring the newly created dmmp device resource in service has failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
128521	ERROR	Either TEMPLATESYS or TEMPLATETAG argument missing	<p><b>Cause:</b> Incorrect arguments have been supplied to the extend command for the dmmp device resource.</p> <p><b>Action:</b> Rerun the dmmp device resource extend and supply the correct template system and tag names.</p>
128540	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the dmmp device getId command used to retrieve the SCSI ID.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -i &lt;device path&gt; or -b &lt;device ID&gt;.</p>
128541	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the command used to delete the dmmp device resource.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -t &lt;dmmp device resource tag&gt;.</p>
128543	ERROR	device node \"\$dev\" does not exist.	<p><b>Cause:</b> The device node required for restoring the dmmp device resource does not exist. The allocated wait time in restore for udev device creation has been exceeded.</p> <p><b>Action:</b> Rerun the dmmp device resource restore once udev has created the device.</p>
128544	ERROR	Usage error	<p><b>Cause:</b> Incorrect arguments have been supplied to the remove command used to take the dmmp device resource out of service.</p> <p><b>Action:</b> Rerun the command and supply the correct argument list: -t &lt;dmmp device resource tag&gt;.</p>

## EC2 Kit Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
129100	FATAL	Failed to load instance from LifeKeeper.	<b>Cause:</b> An invalid resource tag or ID was specified. <b>Action:</b> Check that the tag or ID is valid and re-run the command.
129103	FATAL	No resource matches tag \"\$self->{tag}\".	<b>Cause:</b> An invalid resource tag was specified. <b>Action:</b> Check the tag and re-run the command.
129104	FATAL	An error occurred setting LifeKeeper resource information	<b>Cause:</b> An internal error has occurred in LifeKeeper.
129108	ERROR	Missing parameter \"\$param\" in ec2 resource object	<b>Cause:</b> This is an internal error.
129110	ERROR	Could not get the Elastic Network Interface ID for \$dev	<b>Cause:</b> The EC2 API call failed, possibly due to a network issue. <b>Action:</b> Check the network and the Amazon console and retry the operation.
129111	ERROR	Failed to get Allocation ID of Elastic IP \"\$elasticIp\".	<b>Cause:</b> The EC2 API call failed, possibly due to a network issue. <b>Action:</b> Check the network and the Amazon console and retry the operation.
129112	ERROR	Cannot find curl executable. Please verify that the steeleye-curl package is installed.	<b>Cause:</b> Install the steeleye-curl package, if it is not installed.
129113	ERROR	Failed to get my instance ID.	<b>Cause:</b> The EC2 instance metadata access failed. <b>Action:</b> Check the Amazon console and retry the operation.
129114	ERROR	Failed to get ENI ID.	<b>Cause:</b> The EC2 API call failed, possibly due to a network issue. <b>Action:</b> Check the network and the Amazon console and retry the operation.

Code	Severity	Message	Cause/Action
129115	ERROR	Failed to associate Elastic IP, retrying \$i/\$MAX_RETRY	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129116	ERROR	Failed to associate Elastic IP \"\$self->{'EIP'}\" on \"\$self->{'DEV'}\".	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129117	ERROR	Failed to disassociate Elastic IP, retrying \$i/\$MAX_RETRY	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129118	WARN	\$self->{'EIP'} is not associated with any instance.	<p><b>Cause:</b> The Elastic IP is not associated with any instance.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by calling the EC2 API to associate the Elastic IP. Check adjacent log messages for more details.</p>
129119	WARN	\$self->{'EIP'} is associated with another instance.	<p><b>Cause:</b> The Elastic IP is associated with another instance.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by calling the EC2 API to associate the Elastic IP. Check adjacent log messages for more details.</p>
129120	ERROR	Failed to recover Elastic IP.	<p><b>Cause:</b> The EC2 API call failed to associate the Elastic IP.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>

Code	Severity	Message	Cause/Action
129121	ERROR	Recovery process ended but Elastic IP is not associated with this instance. Please check AWS console.	<p><b>Cause:</b> The EC2 API call failed to associate the Elastic IP.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129122	ERROR	Error creating resource \" <code>\$target_tag</code> \" with return code of \" <code>\$err</code> \".	<p><b>Cause:</b> LifeKeeper was unable to create the resource instance on the server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129123	ERROR	Failed to get ENI ID.	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129124	WARN	<code>\$self-&gt;{'EIP'}</code> is associated with another network interface.	<p><b>Cause:</b> The Elastic IP is associated with the proper instance, but the wrong ENI.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by calling the EC2 API to associate the Elastic IP. Check adjacent log messages for more details.</p>
129125	ERROR	Link check failed for interface ' <code>\$dev</code> '.	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present.</p> <p><b>Action:</b> Check the network interface and bring the link up.</p>
129126	ERROR	Link check failed for interface ' <code>\$dev</code> '. Reason: down slave.	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present.</p> <p><b>Action:</b> Check the network interface and bring the link up.</p>

Code	Severity	Message	Cause/Action
129129	WARN	The link for network interface '\\$self->{'DEV'}' is down. Attempting to bring the link up.	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by bringing the link up and associating the Elastic IP with the interface. Check adjacent log messages for more details.</p>
129137	ERROR	The link for network interface '\\$self->{'DEV'}' is still down.	<p><b>Cause:</b> LifeKeeper could not bring the link up.</p> <p><b>Action:</b> Ensure the interface is enabled and up. Check adjacent log messages for more details.</p>
129139	WARN	The link for network interface '\\$self->{'DEV'}' is down.	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present.</p> <p><b>Action:</b> Check the network interface and bring the link up.</p>
129140	ERROR	Could not get ENI ID for \$self->{IP}.	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129141	ERROR	Could not update route table, retrying \$i/\$MAX_RETRY (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129142	ERROR	Failed to update route table	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>

Code	Severity	Message	Cause/Action
129143	ERROR	You must have exactly one IP address resource as the parent of the RouteTable EC2 resource. Please reconfigure your resource hierarchy.	<p><b>Cause:</b> The Route Table EC2 resource must have one and only one IP resource as a parent.</p> <p><b>Action:</b> Repair the resource hierarchy as necessary.</p>
129144	ERROR	\$func called with invalid timeout: \$timeout	<p><b>Cause:</b> An invalid timeout value was specified in the /etc/default/LifeKeeper file.</p> <p><b>Action:</b> Verify all EC2_*_TIMEOUT settings are valid in /etc/default/LifeKeeper.</p>
129145	ERROR	\$func action timed out after \$timeout seconds	<p><b>Cause:</b> The action did not complete within the timeout period.</p> <p><b>Action:</b> Consider increasing the EC2_*_TIMEOUT value for the given action (in /etc/default/LifeKeeper).</p>
129146	ERROR	failed to run \$func with timeout: \$@	<p><b>Cause:</b> This is an internal error.</p>
129148	ERROR	Amazon ec2-describe-route-tables call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129150	ERROR	Elastic IP \"\$elasticIp\" is associated with another instance.	<p><b>Cause:</b> The Elastic IP is not associated with the proper instance.</p> <p><b>Action:</b> LifeKeeper will try to fix the issue by calling the EC2 API to associate the Elastic IP. Check adjacent log messages for more details.</p>
129151	ERROR	Could not get the Association ID for Elastic IP \"\$elasticIp\".	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>

Code	Severity	Message	Cause/Action
129152	ERROR	Failed to disassociate Elastic IP \"\$self->{'EIP'}\" on \"\$self->{'DEV'}\".	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129153	ERROR	Failed to disassociate Elastic IP \"\$elasticIp\", (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129154	ERROR	Amazon ec2-describe-addresses call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129155	ERROR	Amazon ec2-describe-addresses call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129156	ERROR	curl call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 instance metadata access failed.</p> <p><b>Action:</b> Check the Amazon console and retry the operation.</p>
129157	ERROR	curl call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 instance metadata access failed.</p> <p><b>Action:</b> Check the Amazon console and retry the operation.</p>
129158	ERROR	curl call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 instance metadata access failed.</p> <p><b>Action:</b> Check the Amazon console and retry the operation.</p>



Code	Severity	Message	Cause/Action
129159	ERROR	Amazon ec2-associate-address call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129160	ERROR	Amazon ec2-describe-addresses call failed (err=%s)(output=%s	<p><b>Cause:</b> The EC2 API call failed, possibly due to a network issue.</p> <p><b>Action:</b> Check the network and the Amazon console and retry the operation.</p>
129161	ERROR	Error deleting resource \"\$otherTag\" on \"\$otherSys\" with return code of \"\$err\".	<p><b>Cause:</b> LifeKeeper was unable to delete the resource instance on the server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129403	ERROR	END failed create of \$TAG due to a \$sig signal	<p><b>Cause:</b> The create process was interrupted by a signal.</p>
129409	ERROR	The IP resource \$IP_RES is not \"\$ISP\".	<p><b>Cause:</b> The IP resource is not in service.</p> <p><b>Action:</b> Bring the resource in service and retry the operation.</p>
129410	ERROR	Could not find IP resource \$IP_RES	<p><b>Cause:</b> Ensure that the IP resource exists and retry the operation.</p>
129412	ERROR	EC2 resource \$ID is already protected	<p><b>Cause:</b> A resource with the specified ID already exists.</p> <p><b>Action:</b> Make sure to clean up any remnants of an old resource before re-creating a new resource.</p>
129413	ERROR	Failed to encrypt AWS_SECRET_KEY	<p><b>Cause:</b> Ensure that the AWS_ACCESS_KEY and AWS_SECRET_KEY have been entered correctly.</p>

Code	Severity	Message	Cause/Action
129416	ERROR	Error creating resource \" <code>\$TAG</code> \" with return code of \" <code>\$!-cderror</code> \".	<p><b>Cause:</b> LifeKeeper was unable to create the resource instance.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129418	ERROR	Dependency creation between \" <code>\$IP_RES</code> \" and \" <code>\$TAG</code> \" failed with return code of \" <code>\$!cderror</code> \".	<p><b>Cause:</b> LifeKeeper was unable to create the resource dependency.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129420	ERROR	In-service failed for tag \" <code>\$TAG</code> \".	<p><b>Cause:</b> LifeKeeper could not bring the resource instance into service.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
129800	ERROR	canextend checks failed for \" <code>\$self-&gt;{tag}</code> \" (err= <code>\$ret</code> )	<p><b>Cause:</b> The pre-extend checks failed for the target server.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>

## File System Kit Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
124004	FATAL	resource tag name not specified	<p><b>Cause:</b> Invalid arguments were specified for the "quickCheck" operation.</p> <p><b>Action:</b> Ensure that the correct arguments are passed.</p>
124005	FATAL	resource id not specified	<p><b>Cause:</b> Invalid arguments were specified for the "quickCheck" operation.</p> <p><b>Action:</b> Ensure that the correct arguments are passed.</p>
124007	FATAL	Failed to get resource information	<p><b>Cause:</b> The filesystem resource's info field does not contain the correct information.</p> <p><b>Action:</b> Put the correct information in the resource's info field or restore the system from a recent "lkbackup" to restore the original info field.</p>
124008	ERROR	getId failed	<p><b>Cause:</b> The filesystem resource could not find the underlying disk device.</p> <p><b>Action:</b> Check adjacent log messages for further details. Verify that the resource hierarchy is valid and that all required storage kits are installed.</p>
124009	ERROR	LifeKeeper protected filesystem is in service but quick-Check detects the following error	<p><b>Cause:</b> The filesystem kit has found something wrong with the resource.</p> <p><b>Action:</b> Check the messages immediately following this one for more details.</p>

Code	Severity	Message	Cause/Action
124010	ERROR	\"\$id\" is not mounted	<b>Cause:</b> The filesystem resource is no longer mounted. <b>Action:</b> No action is required. Allow local recovery to remount the resource.
124011	ERROR	\"\$id\" is mounted but with the incorrect mount options (current mount option list: \$mntopts, expected mount option list: \$infopts)	<b>Cause:</b> The filesystem resource is mounted incorrectly. <b>Action:</b> No action is required. Allow local recovery to remount the resource.
124012	ERROR	\"\$id\" is mounted but on the wrong device (current mount device: \$tmpdev, expected mount device: \$dev)	<b>Cause:</b> The filesystem resource has the wrong device mounted. <b>Action:</b> No action is required. Allow local recovery to remount the resource.
124015	ERROR	LifeKeeper protected filesystem \"\$tag\" (\$id) is \$percent% full (\$blocksfree free blocks).	<b>Cause:</b> The filesystem is getting full. <b>Action:</b> Remove or migrate data from the filesystem.
124016	WARN	LifeKeeper protected filesystem \"\$tag\" (\$id) is \$percent%% full (\$blocksfree free blocks).	<b>Cause:</b> The filesystem is getting full. <b>Action:</b> Remove or migrate data from the filesystem.
124020	FATAL	cannot find device information for filesystem \$id	<b>Cause:</b> The filesystem resource could not find the underlying disk device. <b>Action:</b> Check adjacent log messages for further details. Verify that the resource hierarchy is valid and that all required storage kits are installed.
124029	ERROR	Failed to find child resource.	<b>Cause:</b> The filesystem resource could not determine its underlying disk resource. <b>Action:</b> Ensure that the resource hierarchy is correct.

Code	Severity	Message	Cause/Action
124032	FATAL	Script has hung. Exiting.	<p><b>Cause:</b> Processes had files open on a mounted filesystem that needed to be unmounted. Killing those processes has taken too long.</p> <p><b>Action:</b> If this error continues, try to temporarily stop all software that may be using the mount point to allow it to be unmounted. If the filesystem still cannot be unmounted, contact Support.</p>
124042	ERROR	file system \$fsname failed unmount; will try again	<p><b>Cause:</b> Processes had files open on a mounted filesystem that needed to be unmounted. It can take multiple attempts to clear those processes.</p> <p><b>Action:</b> No action is required. Allow the process to continue.</p>
124046	ERROR	file system \$fsname failed unmount	<p><b>Cause:</b> A filesystem could not be unmounted.</p> <p><b>Action:</b> If this error continues, try to temporarily stop all software that may be using the mount point to allow it to be unmounted. If the filesystem still cannot be unmounted, contact Support.</p>
124049	ERROR	Local recovery of resource has failed (err=\$err	<p><b>Cause:</b> A filesystem resource has a problem that cannot be repaired locally.</p> <p><b>Action:</b> No action is required. Allow the resource to be failed over to another system.</p>
124103	ERROR	\$ERRMSG Script was terminated for unknown reason	<p><b>Cause:</b> This message should not occur under normal circumstances.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>

Code	Severity	Message	Cause/Action
124104	ERROR	\$ERRMSG Required template machine name is null	<p><b>Cause:</b> Invalid arguments were specified for the canextend operation.</p> <p><b>Action:</b> Ensure that the arguments are correct. If this error happens during normal operation, please contact Support.</p>
124105	ERROR	\$ERRMSG Required template resource tag name is null	<p><b>Cause:</b> Invalid arguments were specified for the canextend operation.</p> <p><b>Action:</b> Ensure that the arguments are correct. If this error happens during normal operation, please contact Support.</p>
124106	ERROR	\$ERRMSG Unable to access template resource \"\$TemplateTagName\	<p><b>Cause:</b> The resource's underlying disk information cannot be determined.</p> <p><b>Action:</b> Ensure the hierarchy is correct on the template system before extending.</p>
124107	ERROR	\$ERRMSG Resource \"\$TemplateTagName\" must have one and only one device resource dependency	<p><b>Cause:</b> The resource has too many underlying devices in the hierarchy.</p> <p><b>Action:</b> Ensure the hierarchy is correct on the template system before extending.</p>
124108	ERROR	\$ERRMSG Unable to access template resource \"\$TemplateTagName\	<p><b>Cause:</b> The resource cannot be found on the template system.</p> <p><b>Action:</b> Ensure the hierarchy is correct on the template system before extending.</p>
124109	ERROR	\$ERRMSG Can not access canextend for scsi/\$DeviceResType resources on machine \"\$TargetSysName\	<p><b>Cause:</b> The target system is missing some required components.</p> <p><b>Action:</b> Ensure that the target system has all the correct kits installed and licensed.</p>

Code	Severity	Message	Cause/Action
124110	ERROR	\$ERRMSG Either filesystem \"\$TemplateLKId\" is not mounted on \"\$TemplateSysName\" or filesystem is not shareable with \"\$TargetSysName\"	<p><b>Cause:</b> The filesystem isn't in service on the template system or doesn't meet the requirements for extending to the target system.</p> <p><b>Action:</b> Make sure the resource is in service on the template system and review the product documentation regarding the requirements for extending filesystems.</p>
124111	ERROR	\$ERRMSG File system type \"{FSType}\" is not supported by the kernel currently running on \"{TargetSysName}\"	<p><b>Cause:</b> The filesystem's type cannot be mounted on the target system due to lack of kernel support.</p> <p><b>Action:</b> Ensure that the target system has all its kernel modules configured correctly before extending the resource.</p>
124112	ERROR	must specify machine name containing primary hierarchy	<p><b>Cause:</b> Invalid arguments were specified for the creFShier operation.</p> <p><b>Action:</b> If this error happens during normal operation, please contact Support.</p>
124113	ERROR	must specify primary ROOT tag	<p><b>Cause:</b> Invalid arguments were specified for the creFShier operation.</p> <p><b>Action:</b> If this error happens during normal operation, please contact Support.</p>
124114	ERROR	must specify primary mount point	<p><b>Cause:</b> Invalid arguments were specified for the creFShier operation.</p> <p><b>Action:</b> If this error happens during normal operation, please contact Support.</p>
124115	ERROR	must specify primary switchback type	<p><b>Cause:</b> Invalid arguments were specified for the creFShier operation.</p> <p><b>Action:</b> If this error happens during normal operation, please contact Support.</p>

Code	Severity	Message	Cause/Action
124118	ERROR	dep_remove failure on machine \"'\$PRIMACH'\" for parent \"'\$PRITAG'\" and child \"'\$DEVTAG'\".	<b>Cause:</b> Cleanup after a dependency creation failed. <b>Action:</b> Check adjacent log messages for further details.
124119	ERROR	ins_remove failure on machine \"'\$PRIMACH'\" for \"'\$PRITAG'\".	<b>Cause:</b> Cleanup after an instance creation failed. <b>Action:</b> Check adjacent log messages for further details.
124121	ERROR	ins_remove failure on machine \"'\$PRIMACH'\".	<b>Cause:</b> Cleanup after a resource creation failed. <b>Action:</b> Check adjacent log messages for further details.
124122	ERROR	\$ERRMSG Script was terminated for unknown reason	<b>Cause:</b> This message should not occur under normal circumstances. <b>Action:</b> Check adjacent log messages for further details.
124123	ERROR	\$ERRMSG Required template machine name is null	<b>Cause:</b> Invalid arguments were specified for the depstoextend operation. <b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.
124124	ERROR	\$ERRMSG Required template resource tag name is null	<b>Cause:</b> Invalid arguments were specified for the depstoextend operation. <b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.
124125	ERROR	\$ERRMSG Unable to access template resource \"'\$TemplateTagName'\".	<b>Cause:</b> The resource was unable to locate its underlying disk resource. <b>Action:</b> Ensure the hierarchy and all dependencies are correct before extending.



Code	Severity	Message	Cause/Action
124126	ERROR	unextmgr failure on machine \"'\$PRIMACH\"	<p><b>Cause:</b> The cleanup, after a failed resource extend operation, failed.</p> <p><b>Action:</b> Manually clean up any remaining resources and check adjacent log messages for further details.</p>
124128	ERROR	unextmgr failure on machine \"'\$PRIMACH\" for \"'\$PRITAG.\"	<p><b>Cause:</b> The cleanup, after a failed resource extend operation, failed.</p> <p><b>Action:</b> Manually clean up any remaining resources and check adjacent log messages for further details.</p>
124129	ERROR	\$ERRMSG Script was terminated for unknown reason	<p><b>Cause:</b> This message should not occur under normal circumstances.</p> <p><b>Action:</b> Look for additional log messages for more details.</p>
124130	ERROR	\$ERRMSG Required template machine name is null	<p><b>Cause:</b> Invalid arguments were specified for the extend operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124131	ERROR	\$ERRMSG Required template resource tag name is null	<p><b>Cause:</b> Invalid arguments were specified for the extend operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124132	ERROR	\$ERRMSG Required target mount point is null	<p><b>Cause:</b> Invalid arguments were specified for the extend operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>

Code	Severity	Message	Cause/Action
124133	ERROR	\$ERRMSG Unable to access template resource \"\\$TemplateTagName\"	<p><b>Cause:</b> The tag being extended doesn't exist on the template system.</p> <p><b>Action:</b> Ensure that the hierarchy is correct on the template system before extending.</p>
124134	ERROR	\$ERRMSG Detected conflict in expected tag name \"\\$TargetTagName\" on target machine.	<p><b>Cause:</b> A resource already exists on the target system with the same tag as the resource being extended.</p> <p><b>Action:</b> Recreate one of the conflicting resources with a different tag.</p>
124135	ERROR	\$ERRMSG Resource \"\\$TemplateTagName\" does not have required device resource dependency or unable to access this resource on template machine.	<p><b>Cause:</b> The resource or its underlying disk resource cannot be found on the template system.</p> <p><b>Action:</b> Ensure that the hierarchy is correct on the template system before extending.</p>
124136	ERROR	\$ERRMSG Resource \"\\$TemplateTagName\" must have one and only one device resource dependency	<p><b>Cause:</b> The resource has multiple underlying devices in the hierarchy on the template system.</p> <p><b>Action:</b> Ensure the hierarchy is correct before extending and that the filesystem resource only depends on a single disk resource.</p>
124137	ERROR	\$ERRMSG Can not access extend for scsi/\$DeviceResType resources on machine \"\\$TargetSysName\"	<p><b>Cause:</b> The files required to support the given storage type aren't available on the target system.</p> <p><b>Action:</b> Ensure that the required kits are installed on the target system and licensed.</p>
124138	ERROR	\$ERRMSG Unable to access target device resource \"\\$DeviceTagName\" on machine \"\\$TargetSysName\"	<p><b>Cause:</b> The required underlying disk resource doesn't exist on the target system.</p> <p><b>Action:</b> Check adjacent log messages for further details and ensure that the target system is properly configured for hosting the resources being extended.</p>

Code	Severity	Message	Cause/Action
124139	ERROR	\$ERRMSG Unable to access template \"/etc/mtab" file	<p><b>Cause:</b> The target system cannot read the template system's /etc/mtab file.</p> <p><b>Action:</b> Check adjacent log messages for further details. Ensure that the /etc/mtab file exists on the template system.</p>
124140	ERROR	\$ERRMSG Unable to find mount point entry \"\$TemplateLkId\" in template \"/etc/mtab\" file. Is template resource in-service?	<p><b>Cause:</b> The resource doesn't appear to be mounted on the template system.</p> <p><b>Action:</b> Make sure the resource is in service before extending.</p>
124141	ERROR	\$ERRMSG Unable to find mount point \"\$TemplateLkId\" mode on template machine	<p><b>Cause:</b> The details of the mount point on the template system cannot be determined.</p> <p><b>Action:</b> Ensure that the resource is in service and accessible on the template system before extending.</p>
124142	ERROR	\$ERRMSG Unable to create or access mount point \"\$TargetLkId\" on target machine	<p><b>Cause:</b> The mount point could not be created on the target system.</p> <p><b>Action:</b> Ensure that the mount point's parent directory exists and is accessible on the target system.</p>
124143	ERROR	\$ERRMSG Two or more conflicting entries found in /etc/fstab on \"\$TargetSysName\"	<p><b>Cause:</b> The device or mount point appears to be mounted more than once on the target system.</p> <p><b>Action:</b> Ensure that the mount point is not mounted on the target system before extending.</p>
124144	ERROR	\$ERRMSG Failed to create resource instance on \"\$TargetSysName\"	<p><b>Cause:</b> The resource creation on the target system failed.</p> <p><b>Action:</b> Check adjacent log messages for further details. Make sure to check the logs on the target server.</p>

Code	Severity	Message	Cause/Action
124145	ERROR	\$ERRMSG Failed to set resource instance state for \"\\$TargetTagName\" on \"\\$TargetSysName\	<b>Cause:</b> The source state could not be changed to OSU on the target system. <b>Action:</b> Check adjacent log messages for further details.
124146	ERROR	must specify machine name containing primary hierarchy	<b>Cause:</b> Invalid arguments were specified for the filesyshier operation. <b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.
124147	ERROR	must specify primary mount point	<b>Cause:</b> Invalid arguments were specified for the filesyshier operation. <b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.
124149	ERROR	create file system hierarchy failure	<b>Cause:</b> The process of finding the resource instance failed. <b>Action:</b> Check adjacent log messages for further details.
124150	ERROR	create file system hierarchy failure	<b>Cause:</b> The system failed to read the /etc/mtab file. <b>Action:</b> Check adjacent log messages for further details.
124151	ERROR	create file system hierarchy failure	<b>Cause:</b> The mount point could not be found in the /etc/mtab file. <b>Action:</b> Check adjacent log messages for further details.
124152	ERROR	create file system hierarchy failure	<b>Cause:</b> The underlying disk resource could not be found. <b>Action:</b> Check adjacent log messages for further details.
124153	ERROR	create file system hierarchy failure	<b>Cause:</b> Creating the filesystem resource failed. <b>Action:</b> Check adjacent log messages for further details.

Code	Severity	Message	Cause/Action
124154	ERROR	create file system hierarchy failure	<b>Cause:</b> The info field for the resource could not be updated. <b>Action:</b> Check adjacent log messages for further details.
124155	ERROR	create file system hierarchy failure	<b>Cause:</b> The switchback strategy could not be set on the resource. <b>Action:</b> Check adjacent log messages for further details.
124157	ERROR	create file system hierarchy failure \{(conflicting entries in /etc/fstab\}	<b>Cause:</b> The mount point could not be removed from the /etc/fstab file. <b>Action:</b> Check adjacent log messages for further details.
124160	ERROR	Unknown error in script filesysins, err=\$err	<b>Cause:</b> This message should not occur under normal circumstances. <b>Action:</b> Check adjacent log messages for further details.
124161	ERROR	create filesys instance - existid - failure	<b>Cause:</b> This message should not occur under normal circumstances. <b>Action:</b> Check adjacent log messages for further details.
124163	ERROR	create filesys instance - ins_list - failure	<b>Cause:</b> Checking for an existing resource failed. <b>Action:</b> Check adjacent log messages for further details.
124164	ERROR	create filesys instance - newtag - failure	<b>Cause:</b> The system failed to generate a suggested tag for the resource. <b>Action:</b> If this error happens during normal operation, contact Support.
124168	ERROR	create filesys instance - ins_create - failure	<b>Cause:</b> The filesystem resource could not be created. <b>Action:</b> Check adjacent log messages for further details.

Code	Severity	Message	Cause/Action
124169	ERROR	filesys instance - ins_setstate - failure	<p><b>Cause:</b> The new filesystem resource's state could not be initialized.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124173	ERROR	create fileys instance - dep_create - failure	<p><b>Cause:</b> The resource's dependency relationship with its underlying disk could not be created.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124174	ERROR	machine not specified	<p><b>Cause:</b> Invalid arguments were specified for the mmenu_mp operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124175	ERROR	mount point not specified	<p><b>Cause:</b> Invalid arguments were specified for the mmenu_mp operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124177	ERROR	unexpected multiple matches found	<p><b>Cause:</b> One or more systems show a filesystem or mount point used more than once.</p> <p><b>Action:</b> Verify filesystem devices and mount points and ensure that filesystems are only mounted once. Look for additional log messages for more details.</p>
124178	ERROR	machine name not specified	<p><b>Cause:</b> Invalid arguments were specified for the menump operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>

Code	Severity	Message	Cause/Action
124180	ERROR	must specify filesystem type	<p><b>Cause:</b> Invalid arguments were specified for the validfstype operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124181	ERROR	mount point not specified	<p><b>Cause:</b> Invalid arguments were specified for the validmp operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124182	ERROR	The mount point \$MP is not an absolute path	<p><b>Cause:</b> A mount point was specified that isn't an absolute path (doesn't start with a '/').</p> <p><b>Action:</b> Specify a mount point as an absolute path starting with a '/'.</p>
124183	ERROR	\$MP is already mounted on \$MACH	<p><b>Cause:</b> The requested mount point is already in use on the system.</p> <p><b>Action:</b> Specify a mount point that isn't in use or unmount it before retrying the operation.</p>
124184	ERROR	The mount point \$MP is already protected by LifeKeeper on \$MACH	<p><b>Cause:</b> The system is already protecting the specified mount point.</p> <p><b>Action:</b> Choose a different mount point that isn't already being protected.</p>
124185	ERROR	The mount point \$MP is not a directory on \$MACH	<p><b>Cause:</b> The mount point refers to a non-directory such as a regular file.</p> <p><b>Action:</b> Choose a mount point that refers to a directory.</p>

Code	Severity	Message	Cause/Action
124186	ERROR	The mount point directory \$MP is not empty on \$MACH	<p><b>Cause:</b> The specified mount point refers to a directory that isn't empty.</p> <p><b>Action:</b> Choose a mount point that is empty or remove the contents of the specified directory before retrying the operation.</p>
124187	ERROR	server name not specified	<p><b>Cause:</b> Invalid arguments were specified for the valuepmp operation.</p> <p><b>Action:</b> Ensure the script is called correctly. If this error happens during normal operation, please contact Support.</p>
124188	ERROR	There are no mount points on server \$MACH	<p><b>Cause:</b> There are no possible mount points for filesystem resource on the server.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124194	WARN	Please correct conflicting \"/etc/fstab\" entries on server \$UNAME for: \$FSDEV, \$FSNAME	<p><b>Cause:</b> After deleting a filesystem resource, some entries in /etc/fstab need to be manually cleaned up.</p> <p><b>Action:</b> Manually clean up the /etc/fstab file.</p>
124195	ERROR	getchildinfo found no \$OKAPP child for \$PTAG	<p><b>Cause:</b> The system could not find a child resource in the hierarchy.</p> <p><b>Action:</b> Check adjacent log messages for further details and ensure that the hierarchy is correct before retrying the operation.</p>
124196	ERROR	enablequotas - quotacheck may have failed for \$FS_NAME	<p><b>Cause:</b> The quota operation failed.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and in /var/log/messages.</p>



Code	Severity	Message	Cause/Action
124198	ERROR	enablequotas - quotaon failed to turn on quotas for \$FS_NAME, reason	<p><b>Cause:</b> The quota operation failed.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and /var/log/messages.</p>
124200	ERROR	The device node \$dev was not found or did not appear in the udev create time limit of \$delay seconds	<p><b>Cause:</b> A device node (/dev/...) was not created by udev. This may indicate an issue with the storage or the server's connection to the storage.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and in /var/log/messages.</p>
124201	WARN	Device \$device not found. Will retry wait to see if it appears.	<p><b>Cause:</b> This can happen under normal conditions while udev creates device node entries for storage. This message should not happen repeatedly.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and in /var/log/messages.</p>
124202	ERROR	Command \"\$commandwithargs\" failed. Retrying ....	<p><b>Cause:</b> The given command failed but may have failed temporarily. This failure may happen during normal operations but should not keep failing.</p> <p><b>Action:</b> Check adjacent log messages for further details if this message continues.</p>
124204	WARN	cannot make file system \$FSNAME mount point	<p><b>Cause:</b> The mount point directory could not be created.</p> <p><b>Action:</b> Ensure that the mount point can be created. This may be due to filesystem permissions, mount options, etc.</p>
124207	ERROR	\"fsck\"ing file system \$FSNAME failed, trying alternative superblock	<p><b>Cause:</b> This message indicates that the typical filesystem check failed. This message may be ok for ext2 filesystems or other filesystems where an alternative superblock location is used.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>

Code	Severity	Message	Cause/Action
124209	ERROR	\\"fsck\\"ing file system \$FSNAME with alternative superblock failed	<p><b>Cause:</b> This indicates that an ext2 filesystem (or other filesystem where an alternative superblock location is used) check failed with the alternative superblock location.</p> <p><b>Action:</b> Check adjacent log messages for further details and instructions on how to proceed.</p>
124210	WARN	POSSIBLE FILESYSTEM CORRUPTION ON \$FSNAME (\$FPNAME	<p><b>Cause:</b> A filesystem was put in service or failed over when it was out of sync with its mirror source.</p> <p><b>Action:</b> Check adjacent log messages for further details and review the product documentation for information on how to bring the filesystem in service safely.</p>
124211	ERROR	Reason for fsck failure (\$retval): \$ret	<p><b>Cause:</b> This log message is part of a series of messages and gives the actual exit code from the fsck process.</p> <p><b>Action:</b> Check adjacent log messages for further details and instructions on how to proceed.</p>
124212	ERROR	\\"fsck\\" of file system \$FSNAME failed	<p><b>Cause:</b> The check of the filesystem failed. This is usually due to the filesystem having corruption.</p> <p><b>Action:</b> Check adjacent log messages for further details. Review the product documentation for instructions on how to handle possible filesystem corruption.</p>
124213	WARN	POSSIBLE FILESYSTEM CORRUPTION ON \$FSNAME (\$FPNAME	<p><b>Cause:</b> The system or user tried to bring into service a filesystem that may be corrupted. This can happen if a filesystem is switched or failed over when it was out of sync with its mirror source.</p> <p><b>Action:</b> Check adjacent log messages for further details and review the product documentation for instructions on how to bring the resource into service safely.</p>

Code	Severity	Message	Cause/Action
124214	ERROR	Reason for fsck failure (\$retval)	<p><b>Cause:</b> This message should follow a previous log message about a filesystem check failure and gives the process exit code of the fsck process.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124218	ERROR	File system \$FSNAME was found to be already	<p><b>Cause:</b> This message is part of a series of messages.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124219	ERROR	mounted after initial mount attempt failed.	<p><b>Cause:</b> This message is part of a series of messages. This should not happen under normal circumstances but may not be fatal if the resource can be put in service.</p> <p><b>Action:</b> Check adjacent log messages for further details in both the lifekeeper log and in /var/log/messages.</p>
124220	ERROR	File system \$FSNAME failed to mount.	<p><b>Cause:</b> The filesystem could not be mounted.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
124221	WARN	Protected Filesystem \$ID is full	<p><b>Cause:</b> The filesystem is full.</p> <p><b>Action:</b> Remove unused data from the filesystem or migrate to a larger filesystem.</p>
124222	WARN	Dependent Applications may be affected <>	<p><b>Cause:</b> This indicates that an operation on a resource is likely to cause operation on other resources based on the resource hierarchy.</p> <p><b>Action:</b> Make sure it's acceptable for the indicated resources to be affected before continuing.</p>
124223	ERROR	Put \"\$t\" Out-Of-Service Failed By Signal	<p><b>Cause:</b> This message should not occur under normal circumstances.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>

Code	Severity	Message	Cause/Action
124227	ERROR	Put \"\$i\" Out-Of-Service Failed	<b>Cause:</b> The operation failed. <b>Action:</b> Check adjacent log messages for further details.
124230	ERROR	Put \"\$t\" In-Service Failed By Signal	<b>Cause:</b> This message should not occur under normal circumstances. <b>Action:</b> Check adjacent log messages for further details.
124231	ERROR	Put \"\$t\" In-Service Failed	<b>Cause:</b> The operation failed. <b>Action:</b> Check adjacent log messages for further details.
124234	ERROR	Put \"\$t\" In-Service Failed	<b>Cause:</b> The operation failed. <b>Action:</b> Check adjacent log messages for further details.

## Gen/App Kit Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
126105	ERROR	script not specified - \$PTH is a directory	<b>Cause:</b> The specified script path is a directory. <b>Action:</b> Correct the path of the script.
126110	ERROR	script \$PTH does not exist	<b>Cause:</b> The specified script path does not exist. <b>Action:</b> Correct the path of the script.
126115	ERROR	script \$PTH is a zero length file	<b>Cause:</b> The specified script is an empty file. <b>Action:</b> Correct the script's file path and check the contents inside the script.
126117	ERROR	script \$PTH is not executable	<b>Cause:</b> The specified script is not executable. <b>Action:</b> Correct the script's file path, check the contents inside the script file and make sure it has the proper execute permissions.
126125	ERROR	required template machine name is null	<b>Cause:</b> The input template machine name is null. <b>Action:</b> Correct the input template machine name.
126130	ERROR	required template resource tag name is null	<b>Cause:</b> The input template resource {tag} is null. <b>Action:</b> Correct the input template resource tag name.

Code	Severity	Message	Cause/Action
126135	ERROR	Unable to generate a new tag	<p><b>Cause:</b> Failed to generate a new tag as the same as the template tag name on the target node using the "newtag" script during the extension. The tag name is already existing.</p> <p><b>Action:</b> Avoid using duplicate tag name on the same node and check the log for detail.</p>
126140	ERROR	Unable to generate a new tag	<p><b>Cause:</b> Failed to generate a new tag as input target tag name on the target node using the "newtag" script during the extension. The tag name is already existing.</p> <p><b>Action:</b> Avoid using duplicate tag name on the same node and check log for detail.</p>
126150	ERROR	unable to remote copy template \"\$_lscript\" script file	<p><b>Cause:</b> Failed to remote copy template script file. The cause may be due to the non-existence/availability of template script file on template node or any transaction failure during "lcdrcp" process.</p> <p><b>Action:</b> Check the existence/availability of template script and the connection to template node. Also check the logs for related errors and try to resolve the reported problem.</p>
126155	ERROR	failed to create resource instance on \"\${TargetSysName}	<p><b>Cause:</b> Failed to create resource instance using "ins_create".</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126160	ERROR	failed to set resource instance state for \"\${TargetTagName}\" on \"\${TargetSysName}	<p><b>Cause:</b> Failed to set resource instance state using "ins_setstate" during GenApp resource extension.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
126170	ERROR	getlocks failure	<p><b>Cause:</b> Failed to get the administrative lock when creating a resource hierarchy.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126175	ERROR	instance create failed	<p><b>Cause:</b> Failed to create a GenApp instance using "appins".</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126180	ERROR	unable to set state to OSU	<p><b>Cause:</b> Failed to set resource instance state using "ins_setstate" during GenApp resource creation.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126190	ERROR	resource restore has failed	<p><b>Cause:</b> Failed to restore GenApp resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126200	ERROR	create application hierarchy rlocks failure	<p><b>Cause:</b> Failed to release lock after GenApp resource created.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126210	ERROR	copy \$ltype script \$lscript failure	<p><b>Cause:</b> Failed to copy user provided script to appropriate GenApp directory during resource creation.</p> <p><b>Action:</b> Check the existence/availability of user provided script and the GenApp directory as well. Also check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
126215	ERROR	no \$ltype script specified	<p><b>Cause:</b> Missing user defined script during GenApp resource creation.</p> <p><b>Action:</b> Check the input action script and run resource creation again.</p>
126220	ERROR	no machine name specified	<p><b>Cause:</b> Missing specified machine name during GenApp resource creation. Failed to copy specified user script due to missing the input for machine name.</p> <p><b>Action:</b> Check the input for machine name and run resource creation again.</p>
126225	ERROR	no resource tag specified	<p><b>Cause:</b> Missing specified tag name during resource creation.</p> <p><b>Action:</b> Check the input for source tag name and run resource creation again.</p>
126230	ERROR	\$ERRMSG Script was terminated for unknown reason	<p><b>Cause:</b> Failed to extend GenApp resource due to unknown reason.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126235	ERROR	\$ERRMSG Required template machine name is null	<p><b>Cause:</b> Missing the input for template machine name during GenApp resource extension.</p> <p><b>Action:</b> Check the input for template machine name and do the resource extension again.</p>
126240	ERROR	\$ERRMSG Required template resource tag name is null	<p><b>Cause:</b> Missing the input for template resource tag name during GenApp resource extension.</p> <p><b>Action:</b> Check the input for template resource tag name and do the resource extension again.</p>



Code	Severity	Message	Cause/Action
126245	ERROR	\$ERRMSG Can not access extend for \$AppType/\$ResType resources on machine \"\$TargetSysName\	<p><b>Cause:</b> Failed to locate "extend" script during GenApp resource extension on target node.</p> <p><b>Action:</b> Check the existence/availability of "extend" script and do GenApp resource extension again.</p>
126250	ERROR	create application failure - ins_list failed	<p><b>Cause:</b> Failed when calling "ins_list" during GenApp resource creation.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126255	ERROR	create application failure - unable to generate a new tag	<p><b>Cause:</b> Failed to generate a new tag during the GenApp resource creation.</p> <p><b>Action:</b> Avoid using duplicate tag name on the same node. Also check the logs for related errors and try to resolve the reported problem.</p>
126270	ERROR	create application failure - ins_create failed	<p><b>Cause:</b> Failed using "ins_create" to create GenApp instance.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
126275	ERROR	create application failure - copy_actions failed	<p><b>Cause:</b> Failed using "copy_actions" to copy user specified template script file.</p> <p><b>Action:</b> Check the existence/availability of template script. Also check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
126290	ERROR	Unable to obtain tag for resource with id \$ID	<p><b>Cause:</b> Failed to fetch GenApp resource tag name by input ID during recovery.</p> <p><b>Action:</b> Check the correctness of input ID and existence/availability of GenApp resource in LCD. Also check the logs for related errors and try to resolve the reported problem.</p>
126300	ERROR	generic application recover script for \$TAG was not found or was not executable	<p><b>Cause:</b> Failed to locate the user defined script for GenApp resource during recovery.</p> <p><b>Action:</b> Check the existence/availability of the user defined script and do the GenApp recovery process again.</p>
126310	ERROR	-t flag not specified	<p><b>Cause:</b> Missing the input for resource tag name during GenApp resource restore.</p> <p><b>Action:</b> Check the input for resource tag name and do resource restore again.</p>
126315	ERROR	-i flag not specified	<p><b>Cause:</b> Missing the input for resource internal id during GenApp resource restore.</p> <p><b>Action:</b> Check the input for resource internal id and do resource restore again.</p>
126335	ERROR	restore script \"\$LCDAS/\$APP_RESTOREDIR/\$TAG\" was not found or is not executable	<p><b>Cause:</b> Failed to locate the user defined script for GenApp resource during restore.</p> <p><b>Action:</b> Check the existence/availability of the user defined script and do the GenApp restore process again.</p>
126340	ERROR	-t flag not specified	<p><b>Cause:</b> Missing the input for resource tag name during GenApp resource remove.</p> <p><b>Action:</b> Check the input for resource tag name and do resource remove again.</p>

Code	Severity	Message	Cause/Action
126345	ERROR	-i flag not specified	<p><b>Cause:</b> Missing the input for resource internal id during GenApp resource remove.</p> <p><b>Action:</b> Check the input for resource internal id and do resource remove again.</p>
126365	ERROR	remove script \"\$LCDAS/\$APP_REMOVEDIR/\$TAG\" was not found or was not executable	<p><b>Cause:</b> Failed to locate the user defined script for GenApp resource during remove.</p> <p><b>Action:</b> Check the existence/availability of the user defined script and do the GenApp remove process again.</p>
126375	ERROR	Script has hung checking \"\$tag\". Forcibly terminating.	<p><b>Cause:</b> The "quickCheck" Script will be forcibly terminated for GenApp resource with tag name {tag} due to a waiting time over the user defined timeout.</p> <p><b>Action:</b> Check the GenApp resource performance and restart quickChecking. Also check the logs for related errors and try to resolve the reported problem.</p>
126380	ERROR	Usage error: no tag specified	<p><b>Cause:</b> Missing the input for resource tag name during GenApp resource quickCheck.</p> <p><b>Action:</b> Check the input for resource tag name and retry resource quickCheck.</p>
126385	ERROR	Internal error: ins_list failed on \$tag.	<p><b>Cause:</b> Failed using "ins_list" to fetch the GenApp resource information by input tag name during the quickCheck process.</p> <p><b>Action:</b> Correct the input tag name and do the quickCheck process again. Also check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
126390	FATAL	Failed to fork process to execute \$userscript: \$!	<p><b>Cause:</b> Failed to fork process to execute user defined "quickCheck" script during the GenApp resource "quickCheck" process.</p> <p><b>Action:</b> Check the existency/availability of the user defined "quickCheck" script and do the "quickCheck" process again.</p>
126391	ERROR	quickCheck has failed for \"\$tag\". Starting recovery.	<p><b>Cause:</b> The GenApp resource with tag name {tag} is determined to be failed by using the user defined health monitoring script - "quickCheck" and the recovery process will be initiated.</p> <p><b>Action:</b> Check the performance of the GenApp resource when local recovery finished. Also check the logs for related errors and try to resolve the reported problem.</p>
126400	ERROR	-t flag not specified	<p><b>Cause:</b> Missing the input for resource tag name during GenApp resource deletion process.</p> <p><b>Action:</b> Check the input for resource tag name and do resource deletion process again.</p>
126405	ERROR	-i flag not specified	<p><b>Cause:</b> Missing the input for resource internal id during GenApp resource deletion process.</p> <p><b>Action:</b> Check the input for resource internal id and do resource deletion process again.</p>

## IP Kit Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
123006	FATAL	Unknown version %s of IP address	<p><b>Cause:</b> The IP address does not appear to be valid for either IPv4 or IPv6.</p> <p><b>Action:</b> Provide a valid IP address.</p>
123008	ERROR	No pinglist found for %s.	<p><b>Cause:</b> Problem while opening the pinglist for this IP address.</p> <p><b>Action:</b> Make sure you have provided a pinglist for this IP address.</p>
123009	ERROR	List ping test failed for virtual IP %s	<p><b>Cause:</b> No response was received from any of the addresses in the ping list.</p> <p><b>Action:</b> Check network connectivity of this node and the systems on which the IPs in the ping list reside.</p>
123013	ERROR	Link check failed for virtual IP %s on interface %s.	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present on the physical layer connection.</p> <p><b>Action:</b> Check the physical connections for the interface and bring the physical layer link up.</p>
123015	ERROR	Link check failed for virtual IP %s on interface %s.	<p><b>Cause:</b> The requested interface is a bonded interface, and one of the slaves is showing 'NO-CARRIER' indicating that no link is present on the physical layer connection.</p> <p><b>Action:</b> Check the physical connections for the slave interface and bring the physical layer link up.</p>

Code	Severity	Message	Cause/Action
123024	ERROR	IP address seems to still exist somewhere else.	<p><b>Cause:</b> The IP address appears to be in use elsewhere on the network.</p> <p><b>Action:</b> Either select a different IP address to use or locate and disable the current use of this IP address.</p>
123027	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The quickCheck of a virtual IP ended due to a timeout.</p> <p><b>Action:</b> Correct the condition or provide a more appropriate value for IP_QUICKCHECK_TIMEOUT in /etc/default/LifeKeeper.</p>
123037	ERROR	must specify machine name containing primary hierarchy	<p><b>Cause:</b> Not enough arguments were provided to crelPhier.</p> <p><b>Action:</b> Supply all of the needed arguments to crelPhier.</p>
123038	ERROR	must specify IP resource name	<p><b>Cause:</b> Not enough arguments were passed to crelPhier.</p> <p><b>Action:</b> Supply all of the needed arguments to crelPhier.</p>
123039	ERROR	must specify primary IP Resource tag	<p><b>Cause:</b> The argument specifying the primary IP Resource tag was missing from the "crelPhier" command.</p> <p><b>Action:</b> Supply all of the needed arguments.</p>
123042	ERROR	An unknown error has occurred in utility validmask on machine %s.	<p><b>Cause:</b> There was an unexpected error running the "validmask" utility.</p> <p><b>Action:</b> Check adjacent log messages for additional details.</p>
123045	ERROR	An unknown error has occurred in utility getlocks.	<p><b>Cause:</b> There was an unexpected error running the "getlocks" utility.</p> <p><b>Action:</b> Check adjacent log messages for additional details.</p>

Code	Severity	Message	Cause/Action
123053	ERROR	Cannot resolve hostname %s	<p><b>Cause:</b> A hostname was provided for the IP address, but the system was unable to resolve the name to an IP address.</p> <p><b>Action:</b> Check the correctness of the hostname and verify that name resolution (DNS or /etc/hosts) is working correctly and returns the IP for the hostname.</p>
123055	ERROR	An unknown error has occurred in utility %s on machine %s.	<p><b>Cause:</b> There was a failure while creating the IP resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
123056	ERROR	create ip hierarchy failure: perform_action failed	<p><b>Cause:</b> Unexpected error trying to restore the IP address during creation.</p> <p><b>Action:</b> Check adjacent log messages for additional details.</p>
123059	ERROR	Resource already exists on machine %s	<p><b>Cause:</b> Attempted to create an IP address that already exists.</p> <p><b>Action:</b> Reuse the existing resource or manually remove the IP address if it exists or use a different IP address.</p>
123060	ERROR	ins_create failed on machine %s	<p><b>Cause:</b> An unexpected failure occurred while creating an IP resource.</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>
123064	ERROR	An unknown error has occurred in utility %s on machine %s.	<p><b>Cause:</b> There was a failure while creating a dependency for the IP resource.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
123066	ERROR	An error occurred during creation of LifeKeeper application=comm on %s.	<p><b>Cause:</b> A failure occurred while calling "app_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
123068	ERROR	An error occurred during creation of LifeKeeper resource type=ip on %s.	<p><b>Cause:</b> A failure occurred while calling "typ_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
123091	ERROR	the link for interface %s is down	<p><b>Cause:</b> The requested interface is showing 'NO-CARRIER' indicating that no link is present on the physical layer connection.</p> <p><b>Action:</b> Check the physical connections for the interface and bring the physical layer link up.</p>
123093	ERROR	the ping list check failed	<p><b>Cause:</b> No response was received from any of the addresses in the ping list.</p> <p><b>Action:</b> Check network connectivity of this node and the systems on which the IPs in the ping list reside.</p>
123095	ERROR	broadcast ping failed	<p><b>Cause:</b> No replies were received from a broadcast ping.</p> <p><b>Action:</b> Verify that at least one host on the subnet will respond to broadcast pings. Verify that virtual IP is on the correct network interface. Consider using a pinglist instead of a broadcast ping.</p>
123096	ERROR	\$msg	<p><b>Cause:</b> The broadcast ping used to determine the viability of the virtual IP failed.</p> <p><b>Action:</b> Please ensure that the ping list for this resource is properly configured in the properties panel or that broadcast ping checking is disabled by adding NOBCASTPING=1 to the /etc/default/LifeKeeper configuration file.</p>



Code	Severity	Message	Cause/Action
123097	ERROR	exec_list_ping(): broadcast ping failed.	<p><b>Cause:</b> The broadcast ping used to determine the viability of the virtual IP failed.</p> <p><b>Action:</b> Ensure that the ping list for this resource is properly configured in the properties panel or that broadcast ping checking is disabled by adding NOBCASTPING=1 to the /etc/default/LifeKeeper configuration file.</p>

## Oracle Kit Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
122501	ERROR	DB instance "%s" is already protected on "%s".	<p><b>Cause:</b> An attempt was made to protect an Oracle database instance {sid} that is already under LifeKeeper protection on {server}.</p> <p><b>Action:</b> You must select a different database instance {sid} for LifeKeeper protection.</p>
122502	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122503	ERROR	Unable to locate the oratab file "%s" on "%s".	<p><b>Cause:</b> The oratab file was not found at the default or alternate locations on {server}.</p> <p><b>Action:</b> Verify the oratab file exists and has proper permissions for the Oracle user. A valid oratab file is required to complete the "create" operation.</p>
122504	ERROR	Unable to determine Oracle user for "%s" on "%s".	<p><b>Cause:</b> The Oracle Application Recovery Kit was unable to determine the ownership of the Oracle database installation binaries.</p> <p><b>Action:</b> The owner of the Oracle binaries must be a valid non-root user on {server}. Correct the permissions and ownership of the Oracle database installation and retry the operation.</p>

Code	Severity	Message	Cause/Action
122505	ERROR	The Oracle database "%s" is not running or no open connections are available on "%s".	<p><b>Cause:</b> The database instance {sid} was not running or connections to the database were not available via the credentials provided.</p> <p><b>Action:</b> The database instance {sid} must be started on {server} and the proper credentials must be provided for the completion of the "create" operation.</p>
122506	ERROR	Unable to determine Oracle dbspaces and logfiles for "%s" on "%s".	<p><b>Cause:</b> A query to determine the location of required tablespaces, logfiles and related database files failed. This may have been caused by an internal database error.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>
122507	ERROR	Unknown chunk type found for "%s" on "%s".	<p><b>Cause:</b> The specified tablespace, logfile or other required database file is not one of the LifeKeeper supported file or character device types.</p> <p><b>Action:</b> The specified file {database_file} must reference an existing character device or file. Consult the Oracle installation documentation to recreate the specified file {database_file} as a supported file or character device type.</p>

Code	Severity	Message	Cause/Action
122508	ERROR	DB Chunk "%s" for "%s" on "%s" does not reside on a shared file system.	<p><b>Cause:</b> The specified tablespace, logfile or other required database file {database_file} does not reside on a file system that is shared with other systems in the cluster.</p> <p><b>Action:</b> Use the LifeKeeper UI or "lcdstatus (1M)" to verify that communication paths have been properly created. Use "rpm" to verify that the necessary Application Recovery Kits for storage protection have been installed. Verify that the file is, in fact, not on shared storage, and if not, move it to a shared storage device.</p>
122510	ERROR	File system create failed for "%s" on "%s". Reason	<p><b>Cause:</b> LifeKeeper was unable to create the resource {filesystem} on the specified server {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the "create" operation.</p>
122511	ERROR	%s	<p><b>Cause:</b> The message contains the output of the "filesyshier" command.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
122513	ERROR	Dependency creation between Oracle database "%s (%s)" and the dependent resource "%s" on "%s" failed. Reason	<p><b>Cause:</b> LifeKeeper was unable to create a dependency between the database resource {tag} and the necessary child resource {childtag}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Once any problems have been corrected, it may be possible to create the dependency between {tag} and {childtag} manually.</p>

Code	Severity	Message	Cause/Action
122514	ERROR	Unable to "%s" on "%s" during resource create.	<p><b>Cause:</b> The Oracle Application Recovery Kit was unable to release the administrative lock using the "rislocks" command.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
122516	ERROR	Raw device resource created failed for "%s" on "%s". Reason	<p><b>Cause:</b> LifeKeeper was unable to create the resource {raw device} on the specified server {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the "create" operation.</p>
122519	ERROR	In-service attempted failed for tag "%s" on "%s".	<p><b>Cause:</b> The "perform_action" command for {tag} on {server} failed to start the database {sid}. The in-service operation has failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the "create" operation.</p>
122521	ERROR	Create of app "%s" on "%s" failed with return code of "%d".	<p><b>Cause:</b> There was an error running the command "app_create" to create the internal application type.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122522	ERROR	Create of typ "%s" for app "%s" on "%s" failed with return code of "%d".	<p><b>Cause:</b> There was an error running the command "typ_create" to create the internal resource type.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
122524	ERROR	Setting "resstate" for resource "%s" on "%s" failed with return code of "%d".	<p><b>Cause:</b> There was an error running the command "ins_setstate" to set the resource state to {state}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122525	ERROR	The values specified for the target and the template servers are the same: "%s".	<p><b>Cause:</b> The value specified for the target and template servers for the "extend" operation were the same.</p> <p><b>Action:</b> You must specify the correct parameter for the {target server} and {template server}. The {target server} is the server where the {tag} will be extended.</p>
122526	ERROR	Unable to locate the oratab file in "/etc" or in "%s" on "%s".	<p><b>Cause:</b> The oratab file was not found at the default or alternate locations on {server}.</p> <p><b>Action:</b> Verify the oratab file exists and has proper permissions for the Oracle user. A valid oratab file is required to complete the "extend" operation.</p>
122527	ERROR	Unable to retrieve the Oracle user on "%s".	<p><b>Cause:</b> An attempt to retrieve the Oracle user from {template server} during a "canextend" or "extend" operation failed.</p> <p><b>Action:</b> The owner of the Oracle binaries must be a valid user on {target server} and {template server}. Correct the permissions and ownership of the Oracle database installation and retry the operation.</p>

Code	Severity	Message	Cause/Action
122528	ERROR	The Oracle user and/or group information for user "%s" does not exist on the server "%s".	<p><b>Cause:</b> LifeKeeper is unable to find the Oracle user and/or group information for the Oracle user {user} on the server {server}.</p> <p><b>Action:</b> Verify the Oracle user {user} exists on the specified {server}. If the user {user} does not exist, it should be created with the same uid and gid on all servers in the cluster.</p>
122529	ERROR	The id for user "%s" is not the same on template server "%s" and target server "%s".	<p><b>Cause:</b> The user id on the target server {target server} for the Oracle user {user} does not match the value of the user {user} on the template server {template server}.</p> <p><b>Action:</b> The user ids for the Oracle user {user} must match on all servers in the cluster. The user id mismatch should be corrected manually on all servers before retrying the "extend" operation.</p>
122530	ERROR	The group id for user "%s" is not the same on template server "%s" and target server "%s".	<p><b>Cause:</b> The group id on the target server {target server} for the Oracle user {user} does not match the value of the user {user} on the template server {template server}.</p> <p><b>Action:</b> The group ids for the Oracle user {user} must match on all servers in the cluster. The group id mismatch should be corrected manually on all servers before retrying the "extend" operation.</p>
122532	ERROR	No file system or raw devices found to extend for "%s" on "%s".	<p><b>Cause:</b> There were no dependent file system or raw device resources found for the Oracle resource {tag} on server {template server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>

Code	Severity	Message	Cause/Action
122533	WARN	A RAMDISK (%s) was detected in the ORACLE Database configuration for "%s" on "%s". LifeKeeper cannot protect RAMDISK. This RAMDISK resource will not be protected by LifeKeeper! ORACLE hierarchy creation will continue.	<p><b>Cause:</b> The specified tablespace, logfile or other database file {database_file} was detected as a ramdisk. No protection is available for this type of resource in the current LifeKeeper product.</p> <p><b>Action:</b> The ramdisk will not be protected. You must manually ensure that the required database file {database_file} will be available during all Oracle database operations.</p>
122534	ERROR	Failed to initialize object instance for Oracle sid "%s" on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122537	ERROR	Update of instance info field for "%s" on "%s" failed (%s).	<p><b>Cause:</b> There was an error while running the command "ins_setinfo" to update the internal resource information field.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122538	ERROR	Initial connect with query buffer to database "%s" on "%s" failed, testing output.	<p><b>Cause:</b> A connection attempt to the Oracle database {sid} to determine the database status has failed.</p> <p><b>Action:</b> The connection attempt failed with the specified credentials. Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>



Code	Severity	Message	Cause/Action
122542	ERROR	The "%s [ %s ]" attempt of the database "%s" appears to have failed on "%s".	<p><b>Cause:</b> The attempted Oracle action {action} using method {action_method} for the database instance {sid} failed on the server {server}.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>
122543	ERROR	All attempts to "%s" database "%s" on "%s" failed	<p><b>Cause:</b> All efforts to perform the action {action} on the Oracle database {sid} on server {server} have failed.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>
122544	ERROR	Update of "%s" sid "%s" on "%s" failed. Reason: "%s" "%s" failed: "%s".	<p><b>Cause:</b> An unexpected error occurred while attempting to update the oratab entry for the database {sid}. The error occurred while attempting to open the oratab file.</p> <p><b>Action:</b> The oratab file entry for {sid} will need to be updated manually to turn off the automatic start up of the database at system boot.</p>
122545	ERROR	Unable to locate the oratab file in "/etc" or in "%s" on "%s".	<p><b>Cause:</b> The oratab file was not found at the default or alternate locations on {server}.</p> <p><b>Action:</b> Verify the oratab file exists and has proper permissions for the oracle user. A valid oratab file is required to complete the "extend" operation.</p>

Code	Severity	Message	Cause/Action
122546	ERROR	Unable to open file "%s" on "%s" (%s).	<p><b>Cause:</b> The specified file {file} could not be opened or accessed on the server {server} due to the error {error}.</p> <p><b>Action:</b> Verify the existence and permissions on the specified file {file}. Check adjacent log messages for further details and related errors. You must correct any reported errors before retrying the operation.</p>
122547	ERROR	(cleanUpPids):Forcefully killing hung pid(s):pid(s)="%s"	<p><b>Cause:</b> The process {pid} failed to respond to the request to terminate gracefully. The process {pid} will be forcefully terminated.</p> <p><b>Action:</b> Use the command line to verify that the process {pid} has been terminated. Check the adjacent log messages for further details and related messages.</p>
122548	ERROR	Unable to locate the DB utility (%s/%s) on this host.	<p><b>Cause:</b> The Oracle binaries and required database utility {utility} located at {path/utility} were not found on this server {server}.</p> <p><b>Action:</b> Verify that the Oracle binaries and required software utilities are installed and properly configured on the server {server}. The Oracle binaries must be installed locally on each node or located on shared storage available to all nodes in the cluster.</p>
122549	ERROR	Oracle internal error or non-standard Oracle configuration detected. Oracle User and/or Group set to "root".	<p><b>Cause:</b> The detected ownership of the Oracle database installation resolves to the root user and/or root group. Ownership of the Oracle installation by root is a non-standard configuration.</p> <p><b>Action:</b> The owner of the Oracle binaries must be a valid non-root user on {server}. Correct the permissions and ownership of the Oracle database installation and retry the operation.</p>

Code	Severity	Message	Cause/Action
122550	ERROR	Initial inspection of "%s" failed, verifying failure or success of received output.	<p><b>Cause:</b> The previous Oracle query {query} or command {cmd} failed to return success.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related errors. Check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct the reported problem(s).</p>
122551	ERROR	Logon failed with "%s" for "%s" on "%s". Please check username/password and privileges.	<p><b>Cause:</b> The logon with the credentials {credentials} for the database instance {sid} on server {server} failed. An invalid user {user} or password was specified.</p> <p><b>Action:</b> Verify that the Oracle database user {user} and password {password} are indeed valid. In addition, the Oracle database user {user} must have sufficient privileges for the attempted action.</p>
122552	ERROR	%s	<p><b>Cause:</b> The message contains the output of the "sqlplus" command.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages.</p>
122553	ERROR	Unable to open file "%s" on "%s" (%s).	<p><b>Cause:</b> The specified file {file} could not be opened or accessed on the server {server} due to the error {error}.</p> <p><b>Action:</b> Verify the existence and permissions on the specified file {file}. Check adjacent log messages for further details and related errors. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
122554	ERROR	The tag "%s" on "%s" is not an Oracle instance or it does not exist.	<p><b>Cause:</b> The specified tag {tag} on server {server} does not refer to an existing and valid Oracle resource instance.</p> <p><b>Action:</b> Use the UI or "lcdstatus (1M)" to verify the existence of the resource tag {tag}. The resource tag {tag} must be an Oracle resource instance to use the command "ora-display."</p>
122555	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to update the authorized user, password and database role for the Oracle resource instance.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122557	ERROR	Update of user and password failed for "%s" on "%s".	<p><b>Cause:</b> A request to update the user and password for the resource tag {tag} failed. The specified credentials failed the initial validation/connection attempt on server {server}.</p> <p><b>Action:</b> Verify the correct credentials {user/password} were specified for the attempted operation. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122559	ERROR	Update of user and password failed for "%s" on "%s".	<p><b>Cause:</b> The update of the user and password information for the resource tag {tag} on server {server} failed.</p> <p><b>Action:</b> Verify the correct credentials {user/password} were specified for the attempted operation. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
122562	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The required Oracle executable {exe} was not found on this server {server}.</p> <p><b>Action:</b> Verify that the Oracle binaries and required software utilities are installed and properly configured on the server {server}. The Oracle binaries must be installed locally on each node or located on shared storage available to all nodes in the cluster.</p>
122566	ERROR	Unable to find Oracle home for "%s" on "%s".	<p><b>Cause:</b> The Oracle home directory {Oracle home} does not appear to contain files necessary for the proper operation of the Oracle instance {sid}.</p> <p><b>Action:</b> Verify using the command line that the Oracle home directory {Oracle home} contains the Oracle binaries, a valid spfile{sid}.ora or init{sid}.ora file.</p>
122567	ERROR	Oracle SID mismatch. The instance SID "%s" does not match the SID "%s" specified for the command.	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected. The specified internal ID {id} does not match the expected SID {sid}.</p> <p><b>Action:</b> Verify the parameters are correct. Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>
122568	ERROR	DB Processes are not running on "%s".	<p><b>Cause:</b> A process check for the Oracle instance did not find any processes running on server {server}.</p> <p><b>Action:</b> If local recovery is enabled, the Oracle instance will be restarted locally. Check adjacent log messages for further details and related messages.</p>

Code	Severity	Message	Cause/Action
122572	ERROR	Failed to create flag "%s" on "%s".	<p><b>Cause:</b> An unexpected error occurred attempting to create a flag for controlling Oracle local recovery processing causing a failover to the standby node.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
122574	ERROR	all attempts to shutdown the database %s failed on "%s".	<p><b>Cause:</b> The shutdown of the Oracle database failed during a local recovery process most likely caused because the maximum number of database connections has been reached.</p> <p><b>Action:</b> Check the Oracle logs for connection failures caused by the maximum number of available connections being reached, and if found, consider increasing the value. Additionally, set the tunable LK_ORA_NICE to 1 to prevent connection failures from causing a quickCheck failure followed by a local recovery attempt.</p>
122597	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected during pre-extend checking.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the pre-extend.</p>
122598	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being created while attempting to determine the validity of the Oracle home directory.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the "create."</p>

Code	Severity	Message	Cause/Action
122599	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to look up the Oracle user on the template system.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the extend.</p>
122600	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to display the resource properties.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the display of the resource properties.</p>
122601	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to check for valid database authorization.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the command.</p>
122603	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to perform health checks on the Oracle resource instance.</p> <p><b>Action:</b> Check that correct arguments were passed to the quickCheck command and also check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the restore.</p>

Code	Severity	Message	Cause/Action
122604	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> There was an unexpected error creating an internal representation of the Oracle instance being protected while attempting to perform a local recovery on the Oracle resource instance.</p> <p><b>Action:</b> Check that correct arguments were passed to the "recover" command, and also check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the recover.</p>
122606	ERROR	The Oracle database "%s" is not running or no open connections are available on "%s".	<p><b>Cause:</b> The database instance {sid} was not running or connections to the database are not available via the credentials provided.</p> <p><b>Action:</b> The database instance {sid} must be started on {server} and the proper credentials must be provided for the completion of the selected operation.</p>
122607	ERROR	The Oracle database "%s" is not running or no open connections are available on "%s".	<p><b>Cause:</b> The database instance {sid} was not running or connections to the database are not available via the credentials provided.</p> <p><b>Action:</b> The database instance {sid} must be started on {server} and the proper credentials must be provided for the completion of the selected operation.</p>
122608	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> The "remove" operation failed to create the resource object instance required to take the Oracle resource Out of Service.</p> <p><b>Action:</b> Check that correct arguments were passed to the "remove" command and also check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the restore.</p>



Code	Severity	Message	Cause/Action
122609	ERROR	Failed to create object instance for Oracle on "%s".	<p><b>Cause:</b> The "restore" operation failed to create the resource object instance required to put the Oracle resource In Service.</p> <p><b>Action:</b> Check that correct arguments were passed to the "restore" command and also check the adjacent log messages for further details and related messages. Correct any reported errors before retrying the "restore."</p>
122610	ERROR	Unable to "%s" on "%s" during resource create.	<p><b>Cause:</b> The Oracle Application Recovery Kit was unable to create the administrative lock using the "getlocks" command during resource creation.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create.</p>
122611	ERROR	%s	<p><b>Cause:</b> The requested dependency creation between the parent Oracle resource and the child File System resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create operation.</p>
122612	ERROR	%s	<p><b>Cause:</b> The requested dependency creation between the parent Oracle resource and the child Raw resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create operation.</p>

Code	Severity	Message	Cause/Action
122613	ERROR	%s	<p><b>Cause:</b> The requested dependency creation between the parent Oracle resource and the child Raw resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create operation.</p>
122614	ERROR	%s	<p><b>Cause:</b> The requested dependency creation between the parent Oracle resource and the child Listener resource failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the create operation.</p>
122616	ERROR	%s	<p><b>Cause:</b> The requested start up or shutdown of the Oracle database failed.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors before retrying the "restore" or "remove" operation.</p>
122618	ERROR	Dependency creation between Oracle database "%s (%s)" and the dependent resource "%s" on "%s" failed. Reason	<p><b>Cause:</b> LifeKeeper was unable to create a dependency between the database resource {tag} and the necessary child resource {childtag}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Once any problems have been corrected, it may be possible to create the dependency between {tag} and {childtag} manually.</p>

Code	Severity	Message	Cause/Action
122619	ERROR	Dependency creation between Oracle database "%s (%s)" and the dependent resource "%s" on "%s" failed. Reason	<p><b>Cause:</b> LifeKeeper was unable to create a dependency between the database resource {tag} and the necessary child resource {childtag}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Once any problems have been corrected, it may be possible to create the dependency between {tag} and {childtag} manually.</p>
122625	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The quickCheck process was unable to find the Oracle executable "sqlplus."</p> <p><b>Action:</b> Check the Oracle configuration and also check adjacent log messages for further details and related messages. Correct any reported problems.</p>
122626	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The remove process was unable to find the Oracle executable "sqlplus."</p> <p><b>Action:</b> Check the Oracle configuration and also check adjacent log messages for further details and related messages. Correct any reported problems.</p>
122627	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The restore process was unable to find the Oracle executable "sqlplus."</p> <p><b>Action:</b> Check the Oracle configuration and also check adjacent log messages for further details and related messages. Correct any reported problems.</p>
122628	ERROR	Unable to find the Oracle executable "%s" on "%s".	<p><b>Cause:</b> The recover process was unable to find the Oracle executable "sqlplus."</p> <p><b>Action:</b> Check the Oracle configuration and also check adjacent log messages for further details and related messages. Correct any reported problems.</p>

Code	Severity	Message	Cause/Action
122632	ERROR	Oracle SID mismatch. The instance SID "%s" does not match the SID "%s" specified for the command.	<p><b>Cause:</b> During a remove, the resource instance {sid} passed to the remove process does not match internal resource instance information for the {sid}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122633	ERROR	Oracle SID mismatch. The instance SID "%s" does not match the SID "%s" specified for the command.	<p><b>Cause:</b> During a restore, the resource instance {sid} passed to restore does not match internal resource instance information for the {sid}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122634	ERROR	Oracle SID mismatch. The instance SID "%s" does not match the SID "%s" specified for the command.	<p><b>Cause:</b> During resource recovery, the resource instance {sid} passed to recovery does not match internal resource instance information for the {sid}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122636	ERROR	END failed hierarchy "%s" of resource "%s" on server "%s" with return value of %d	<p><b>Cause:</b> The create of the Oracle resource hierarchy {tag} failed on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122638	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The create action for the Oracle database resource {tag} on server {server} failed. The signal {sig} was received by the create process.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. You must correct any reported errors before retrying the operation.</p>

Code	Severity	Message	Cause/Action
122640	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create the Oracle resource instance {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122641	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create the Oracle resource instance {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122642	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create the Oracle resource instance {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122643	ERROR	Cannot extend resource "%s" to server "%s"	<p><b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
122644	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to retrieve resource instance information for {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors and retry the extend.</p>
122645	ERROR	Cannot access canextend script "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to run pre-extend checks because it was unable to find the "canextend" script on {server} for a dependent child resource.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>

Code	Severity	Message	Cause/Action
122646	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to retrieve resource instance information for {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors and retry the extend.</p>
122647	ERROR	Cannot extend resource "%s" to server "%s"	<p><b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122648	ERROR	Resource with either matching tag "%s" or id "%s" already exists on server "%s" for App "%s" and Type "%s"	<p><b>Cause:</b> During the database resource extension, a resource instance was found using the same {tag} and/or {id} but with a different resource application and type.</p> <p><b>Action:</b> Resource IDs must be unique. The resource instance with the ID matching the Oracle resource instance must be removed.</p>
122649	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> An unexpected error occurred attempting to create the Oracle resource instance {tag} on {server}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Correct any reported errors.</p>
122650	ERROR	Cannot access extend script "%s" on server "%s"	<p><b>Cause:</b> The request to extend the database resource {resource} to {server} failed because it was unable to find the script {extend} on {server} for a dependent child resource.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>

Code	Severity	Message	Cause/Action
122651	ERROR	Cannot extend resource "%s" to server "%s"	<p><b>Cause:</b> The request to extend the database resource {resource} to {server} failed because of an error attempting to extend a dependent child resource.</p> <p><b>Action:</b> Check the adjacent log messages for further details and related messages. Correct any reported errors.</p>
122654	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The health check for the database {sid} was terminated because the quickCheck process received a signal. This is most likely caused by the quickCheck process requiring more time to complete than was allotted.</p> <p><b>Action:</b> The health check time for an Oracle resource is controlled by the tunable value ORACLE_QUICKCHECK_TIMEOUT. Set it to a value greater than 45 seconds to allow more time for the health check process to complete.</p>
122655	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The request to take database {sid} "Out of Service" was terminated because the remove process received a signal. This is most likely caused by the remove process requiring more time to complete than was allotted.</p> <p><b>Action:</b> The remove time for an Oracle resource is controlled by the tunable value ORACLE_REMOVE_TIMEOUT. Set the tunable to a value greater than 240 seconds to allow more time for the remove process to complete.</p>

Code	Severity	Message	Cause/Action
122659	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The request to place database {sid} "In Service" was terminated because the restore process received a signal. This is most likely caused by the restore process requiring more time to complete than was allotted.</p> <p><b>Action:</b> The restore time for an Oracle resource is controlled by the tunable value ORACLE_RESTORE_TIMEOUT. Set the tunable to a value greater than 240 seconds to allow more time for the restore process to complete.</p>
122663	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> The recovery of the failed database was terminated because the recovery process received a signal. This is most likely caused by the recovery process requiring more time to complete than was allotted.</p> <p><b>Action:</b> The recovery time for an Oracle resource is controlled by the tunable values ORACLE_RESTORE_TIMEOUT and ORACLE_REMOVE_TIMEOUT. Set one or both of these to a value greater than 240 seconds to allow more time for a recovery to complete.</p>
122670	ERROR	Update of "%s" sid "%s" on "%s" failed. Reason: "%s" "%s" failed: "%s".	<p><b>Cause:</b> An unexpected error occurred while attempting to update the oratab entry for the database {sid}. The error occurred while attempting to open the temporary file used in the update process.</p> <p><b>Action:</b> The oratab file entry for {sid} will need to be updated manually to turn off the automatic start up of the database at system boot.</p>



Code	Severity	Message	Cause/Action
122671	ERROR	Update of "%s" sid "%s" on "%s" failed. Reason: "%s" "%s" failed: "%s".	<p><b>Cause:</b> An unexpected error occurred while attempting to update the oratab entry for the database {sid}. The error occurred while attempting to close the temporary file used in the update process.</p> <p><b>Action:</b> The oratab file entry for {sid} will need to be updated manually to turn off the automatic start up of the database at system boot.</p>
122672	ERROR	Update of "%s" sid "%s" on "%s" failed. Reason: "%s" "%s" failed: "%s".	<p><b>Cause:</b> An unexpected error occurred while attempting to update the oratab entry for the database {sid}. The error occurred while attempting to rename the temporary file back to oratab.</p> <p><b>Action:</b> The oratab file entry for {sid} will need to be updated manually to turn off the automatic start up of the database at system boot.</p>
122673	ERROR	Unable to log messages queued while running as oracle user %s on %s. Reason: \$!	<p><b>Cause:</b> An unexpected error {reason} occurred while attempting to add messages to the log file. These messages were generated while running as the Oracle user.</p> <p><b>Action:</b> Review the reason for the failure and take corrective action.</p>
122674	ERROR	Unable to open %s Reason: %s.	<p><b>Cause:</b> An unexpected error occurred while attempting to open a connection to the Oracle database and run the database {cmd}.</p> <p><b>Action:</b> Check adjacent log messages for further details and related messages. Additionally, check the Oracle log (alert.log) and related trace logs (*.trc) for additional information and correct any reported problems.</p>

## Oracle Listener Kit Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
122005	ERROR	Unable to "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "getlocks".</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122007	ERROR	Unable to "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "rlslocks".</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122009	ERROR	The path %s is not a valid file.	<p><b>Cause:</b> There is no listener.ora file.</p> <p><b>Action:</b> Ensure the file exists and retry the operation.</p>
122010	ERROR	The listener user does not exist on the server %s.	<p><b>Cause:</b> "Stat" command could not get user id.</p> <p><b>Action:</b> Retry the operation.</p>
122011	ERROR	The listener user does not exist on the server %s.	<p><b>Cause:</b> UID is not in passwd file.</p> <p><b>Action:</b> Ensure the UID exists in passwd file and retry the operation.</p>
122012	ERROR	The listener user does not exist on the server %s.	<p><b>Cause:</b> User name is not in passwd file.</p> <p><b>Action:</b> Ensure the user name exists in passwd file; retry the operation.</p>

Code	Severity	Message	Cause/Action
122023	ERROR	The %s command failed (%d	<p><b>Cause:</b> This message contains the return code of the "lsnrctl" command.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122024	ERROR	\$line	<p><b>Cause:</b> The message contains the output of the "lsnrctl" command.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122039	ERROR	Usage error	<p><b>Cause:</b> Invalid parameters were specified for the restore operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122040	ERROR	Script \$cmd has hung on the restore of \"\$opt_t\". Forcibly terminating.	<p><b>Cause:</b> The listener restore script reached its timeout value.</p> <p><b>Action:</b> Ensure listener.ora is valid and that LSNR_START_TIME (default 35 seconds) in /etc/default/LifeKeeper is set to a value greater than or equal to the time needed to start the listener.</p>
122041	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> LifeKeeper was unable to restore the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122045	ERROR	Error getting resource information for resource "%s" on server "%s"	<p><b>Cause:</b> Failed to get resource information.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>

Code	Severity	Message	Cause/Action
122046	ERROR	Usage error	<p><b>Cause:</b> Invalid parameters were specified for the restore operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122049	ERROR	The script \$cmd has hung on remove of \"\$opt_t\". Forcibly terminating.	<p><b>Cause:</b> The listener remove script reached its timeout value.</p> <p><b>Action:</b> Ensure listener.ora is valid and that LSNR_STOP_TIME (default 35 seconds) in /etc/default/LifeKeeper is set to a value greater than or equal to the time needed to stop the listener.</p>
122051	ERROR	Error getting resource information for resource \"%s\" on server \"%s\"	<p><b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122055	ERROR	END failed %s of \"%s\" on server \"%s\" due to a \"%s\" signal	<p><b>Cause:</b> LifeKeeper was unable to quickCheck the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122057	ERROR	Error getting resource information for resource \"%s\" on server \"%s\"	<p><b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122064	WARN	The %s level is set to %s a %s will not occur.	<p><b>Cause:</b> The minimal Listener protection level is Start and Monitor.</p> <p><b>Action:</b> Start the listener manually.</p>

Code	Severity	Message	Cause/Action
122066	ERROR	Script has hung checking \"\$tag\". Forcibly terminating.	<p><b>Cause:</b> The listener quickCheck script reached its timeout value.</p> <p><b>Action:</b> Ensure listener.ora is valid and that LSNR_STATUS_TIME (default 15 seconds) in /etc/default/LifeKeeper is set to a value greater than or equal to the time needed to check the listener.</p>
122067	ERROR	Usage error	<p><b>Cause:</b> Invalid parameters were specified for the quickCheck operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122069	ERROR	Usage error	<p><b>Cause:</b> Invalid parameters were specified for the delete operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122072	ERROR	%s: resource "%s" not found on local server	<p><b>Cause:</b> Invalid parameters were specified for the recover operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122074	WARN	The local recovery attempt has failed but %s level is set to %s preventing a failover to another node in the cluster. With %s recovery set all local recovery failures will exit successfully to prevent resource failovers.	<p><b>Cause:</b> The optional listener recovery level is set to local recovery only.</p> <p><b>Action:</b> Switch over the resource tree manually.</p>
122078	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> LifeKeeper was unable to recover the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
122082	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122083	ERROR	\$cmd has hung checking \"\$tag\". Forcibly terminating	<b>Cause:</b> The recover script was stopped by signal. <b>Action:</b> Ensure listener.ora is valid.
122084	ERROR	Cannot extend resource "%s" to server "%s"	<b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}. <b>Action:</b> Verify the parameters and retry the operation.
122085	ERROR	Usage: %s %s	<b>Cause:</b> Invalid parameters were specified for the canextend operation. <b>Action:</b> Verify the parameters and retry the operation.
122086	ERROR	The values specified for the target and the template servers are the same. Please specify the correct values for the target and template servers.	<b>Cause:</b> The values specified for the target and the template servers are the same. <b>Action:</b> Perform the steps listed in the message text.
122087	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122088	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> Failed to get listener user name from resource information. <b>Action:</b> Ensure the resource info field is valid then retry the operation.
122089	ERROR	The listener user %s does not exist on the server %s.	<b>Cause:</b> User name is not in passwd file. <b>Action:</b> Ensure the user name exists in passwd file and retry the operation.

Code	Severity	Message	Cause/Action
122090	ERROR	The id for user %s is not the same on template server %s and target server %s.	<b>Cause:</b> User ID should be same on both servers. <b>Action:</b> Trim user ID to the same.
122091	ERROR	The group id for user %s is not the same on template server %s and target server %s.	<b>Cause:</b> Group ID should be same on both servers. <b>Action:</b> Trim group ID to the same.
122092	ERROR	Cannot access canextend script "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to run pre-extend checks because it was unable to find the "canextend" script on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122097	ERROR	Usage: %s %s	<b>Cause:</b> Invalid arguments were specified for the "configActions" operation. <b>Action:</b> Verify the arguments and retry the operation.
122098	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122099	ERROR	Unable to update the resource %s to change the %s to %s on %s.	<b>Cause:</b> LifeKeeper failed to put information into the info field. <b>Action:</b> Restart LifeKeeper and retry the operation.
122100	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122101	ERROR	Unable to update the resource %s to change the %s to %s on %s.	<b>Cause:</b> LifeKeeper failed to put information to info field on {server}. <b>Action:</b> Restart LifeKeeper on {server} and retry the operation.

Code	Severity	Message	Cause/Action
122103	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid parameters were specified for the create operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122124	ERROR	END failed hierarchy "%s" of resource "%s" on server "%s" with return value of %d	<p><b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122126	ERROR	Unable to "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "rlslocks".</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122127	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122129	ERROR	Unable to "%s" on "%s"	<p><b>Cause:</b> There was an unexpected error running "getlocks."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122131	ERROR	Error creating resource "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122133	ERROR	Unable to create a file system resource hierarchy for the file system %s.	<p><b>Cause:</b> There was an unexpected error running "filesyshier."</p> <p><b>Action:</b> Check adjacent log messages for further details.</p>



Code	Severity	Message	Cause/Action
122135	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122140	ERROR	Resource "%s" is not ISP on server "%s" Manually bring the resource in service and retry the operation	<p><b>Cause:</b> IP resource {tag} which the listener resource depends on should be ISP.</p> <p><b>Action:</b> Perform the steps listed in the message text.</p>
122141	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122144	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid parameters were specified for the "create_ins" operation.</p> <p><b>Action:</b> Verify the parameters and retry the operation.</p>
122145	ERROR	An error has occurred in utility %s on server %s. View the LifeKeeper logs for details and retry the operation.	<p><b>Cause:</b> There was an unexpected error running "app_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122146	ERROR	An error has occurred in utility %s on server %s. View the LifeKeeper logs for details and retry the operation.	<p><b>Cause:</b> There was an unexpected error running "typ_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122147	ERROR	An error has occurred in utility %s on server %s. View the LifeKeeper logs for details and retry the operation.	<p><b>Cause:</b> There was an unexpected error running "newtag."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>

Code	Severity	Message	Cause/Action
122148	ERROR	Error creating resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122149	ERROR	An error has occurred in utility %s on server %s. View the LifeKeeper logs for details and retry the operation.	<b>Cause:</b> There was an unexpected error running "ins_setstate." <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
122150	ERROR	Error creating resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to create the resource {resource} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122151	ERROR	Usage: %s %s	<b>Cause:</b> Invalid arguments were specified for the "depstoextend" operation. <b>Action:</b> Verify the arguments and retry the operation.
122152	ERROR	Usage: %s %s	<b>Cause:</b> Invalid parameters were specified for the "extend" operation. <b>Action:</b> Verify the parameters and retry the operation.
122153	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122154	ERROR	Cannot extend resource "%s" to server "%s"	<b>Cause:</b> LifeKeeper was unable to extend the resource {resource} on {server}.

Code	Severity	Message	Cause/Action
122155	ERROR	Resource with either matching tag "%s" or id "%s" already exists on server "%s" for App "%s" and Type "%s"	<p><b>Cause:</b> During the Listener resource extension, a resource instance was found using the same {tag} and/or {id} but with a different resource application and type.</p> <p><b>Action:</b> Resource IDs must be unique. The resource instance with the ID matching the Oracle Listener resource instance must be removed.</p>
122156	ERROR	Cannot access extend script "%s" on server "%s"	<p><b>Cause:</b> LifeKeeper was unable to extend the resource hierarchy because it was unable to find the script EXTEND on {server}.</p> <p><b>Action:</b> Check your LifeKeeper configuration.</p>
122157	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid arguments were specified for the "getConfigIps" operation.</p> <p><b>Action:</b> Verify the arguments and retry the operation.</p>
122158	ERROR	The file %s is not a valid listener file. The file does not contain any listener definitions.	<p><b>Cause:</b> Failed to find any listener definitions.</p> <p><b>Action:</b> Ensure listener definition is in the listener.ora and retry the operation.</p>
122159	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid arguments were specified for the "getSidListeners" operation.</p> <p><b>Action:</b> Verify the arguments and retry the operation.</p>
122160	ERROR	The file %s is not a valid listener file. The file does not contain any listener definitions.	<p><b>Cause:</b> Failed to find any listener definitions.</p> <p><b>Action:</b> Ensure listener definition is in the listener.ora and retry the operation.</p>
122161	ERROR	Usage: %s %s	<p><b>Cause:</b> Invalid arguments were specified for the "Isn-display" operation.</p> <p><b>Action:</b> Verify the arguments and retry the operation.</p>

Code	Severity	Message	Cause/Action
122162	ERROR	Error getting resource information for resource "%s" on server "%s"	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}. <b>Action:</b> Check your LifeKeeper configuration.
122163	ERROR	Usage: %s %s	<b>Cause:</b> Invalid parameters were specified for the updateHelper operation. <b>Action:</b> Verify the parameters and retry the operation.
122164	ERROR	END failed hierarchy "%s" of resource "%s" on server "%s" with return value of %d	<b>Cause:</b> LifeKeeper was unable to update the resource {resource} on {server}. <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
122166	ERROR	Usage: %s %s	<b>Cause:</b> Invalid parameters were specified for the "updateHelper" operation. <b>Action:</b> Verify the parameters and retry the operation.
122170	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<b>Cause:</b> There was an unexpected error running "dep_create." <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
122171	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<b>Cause:</b> There was an unexpected error running "dep_create." <b>Action:</b> Check the logs for related errors and try to resolve the reported problem.
122172	ERROR	Usage: %s %s	<b>Cause:</b> Invalid arguments were specified for the "updIPDeps" operation. <b>Action:</b> Verify the arguments and retry the operation.

Code	Severity	Message	Cause/Action
122173	ERROR	END failed hierarchy "%s" of resource "%s" on server "%s" with return value of %d	<p><b>Cause:</b> LifeKeeper was unable to update the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122175	ERROR	Unable to "%s" on "%s	<p><b>Cause:</b> There was an unexpected error running "rlslocks."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122177	ERROR	Unable to "%s" on "%s	<p><b>Cause:</b> There was an unexpected error running "getlocks."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122180	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122181	ERROR	Unable to create a dependency between parent tag %s and child tag %s.	<p><b>Cause:</b> There was an unexpected error running "dep_create."</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122183	ERROR	The path %s is not a valid file.	<p><b>Cause:</b> There is no listener.ora file.</p> <p><b>Action:</b> Ensure the file exists and retry the operation.</p>
122185	ERROR	The file %s is not a valid listener file. The file does not contain any listener definitions.	<p><b>Cause:</b> LifeKeeper failed to find any valid listener definitions.</p> <p><b>Action:</b> Ensure there are valid listener definitions in the listener.ora and retry the operation.</p>

Code	Severity	Message	Cause/Action
122186	ERROR	The value specified for %s cannot be empty. Please specify a value for this field.	<b>Cause:</b> The config and/or executable {path} field is empty. <b>Action:</b> Input a non-empty value for {path} and retry the operation.
122187	ERROR	The path %s is not a valid file or directory.	<b>Cause:</b> The defined {path} is invalid. <b>Action:</b> Ensure the {path} exists and retry the operation.
122188	ERROR	The path %s is not a valid file or directory.	<b>Cause:</b> There is no {path}. <b>Action:</b> Ensure the {path} exists and retry the operation.
122189	ERROR	The value specified for %s cannot be empty. Please specify a value for this field.	<b>Cause:</b> The config and/or executable Path field is empty. <b>Action:</b> Input path for the field.
122190	ERROR	Usage: %s %s	<b>Cause:</b> Invalid arguments were specified for the "valid_rpath" operation. <b>Action:</b> Verify the arguments and retry the operation.
122191	ERROR	The values specified for the target and the template servers are the same.	<b>Cause:</b> Invalid argument of valid_rpath. <b>Action:</b> Ensure arguments and retry the operation.
122192	ERROR	Unable to find the configuration file "oratab" in its default locations, /etc/oratab or %s on "%s"	<b>Cause:</b> There is no oratab file in /etc/oratab or {path}. <b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.
122193	ERROR	Unable to find the configuration file "oratab" in its default locations, /etc/oratab or %s on "%s"	<b>Cause:</b> There is no oratab file in /etc/oratab or {path}. <b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.

Code	Severity	Message	Cause/Action
122194	ERROR	Unable to find the configuration file "oratab" in its default locations, /etc/oratab or %s on "%s"	<p><b>Cause:</b> There is no oratab file in /etc/oratab or {path}.</p> <p><b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.</p>
122195	ERROR	Unable to find the configuration file "oratab" in its default locations, /etc/oratab or %s on "%s"	<p><b>Cause:</b> There is no oratab file in /etc/oratab or {path}.</p> <p><b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.</p>
122196	ERROR	END failed %s of "%s" on server "%s" due to a "%s" signal	<p><b>Cause:</b> LifeKeeper was unable to remove the resource {resource} on {server}.</p> <p><b>Action:</b> Check the logs for related errors and try to resolve the reported problem.</p>
122197	ERROR	Unable to find the configuration file \"oratab\" in its default locations, /etc/oratab or \$listener::oraTab on \"\$me\"	<p><b>Cause:</b> There is no oratab file in /etc/oratab or {path}.</p> <p><b>Action:</b> Ensure oratab file exists in {path} or ORACLE_ORATABLOC in /etc/default/Lifekeeper is set to a valid path.</p>

## SCSI Kit Message Catalog

Use **Control F** to search for a specific error code in each catalog.

Code	Severity	Message	Cause/Action
125102	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$TemplateName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125103	ERROR	`printf '%s is not shareable with any machine.' \$DEV`	<b>Cause:</b> The device does not appear to be shared with any other systems.  <b>Action:</b> Verify that the device is accessible from all servers in the cluster. Ensure that all relevant storage drivers and software are installed and configured properly.
125104	ERROR	`printf 'Failed to create disk hierarchy for "%s" on "%s"' \$PRIMACH \$DEV`	<b>Cause:</b> The creation of a resource to protect a physical disk failed.  <b>Action:</b> Check adjacent log messages for more details and try to resolve the reported problem.
125107	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$TemplateName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125114	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$TemplateName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125120	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$TemplateName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125123	ERROR	`printf 'Cannot access depstoextend script "%s" on server "%s"' \$depstoextend \$TargetSysName`	<b>Cause:</b> LifeKeeper was unable to run pre-extend checks on the resource hierarchy because it was unable to find the script "DEPSTOEXTEND" on {server}.  <b>Action:</b> Check your LifeKeeper configuration.



Code	Severity	Message	Cause/Action
125126	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$ChildTag \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125129	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$TemplateName \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.
125155	ERROR	SCSI \$DEV failed to lock.	<b>Cause:</b> There was a problem locking a SCSI device. <b>Action:</b> Check adjacent log messages for more details and try to resolve the reported problem.
125164	ERROR	SCSI \$INFO failed to unlock.	<b>Cause:</b> There was a problem unlocking a SCSI device. <b>Action:</b> Check adjacent log messages for more details and try to resolve the reported problem.
125181	ERROR	`printf 'Template resource "%s" on server "%s" does not exist' \$TemplateTag \$TemplateSysName`	<b>Cause:</b> LifeKeeper was unable to find the resource {tag} on {server}.